

https://dspace.org/

Data adaptor unit for an electronic exchange: system design and simulation study

Reinink, Kasper

2015
http://hdl.handle.net/10539/19196

Downloaded from a DSpace repository. https://dspace.org/

```
L.259         DO 255 J=1,8
L.260         DO 255 K=1,4
L.261         FIELD1(I,J,K)=0
L.262         FIELD2(I,J,K)=0
L.263         FIELD3(I,J,K)=0
L.264   255   CONTINUE
L.265         DO 256 J=1,8
L.266         FIELD1(I,J,5)=0
L.267   256   CONTINUE
L.268   220   CONTINUE
L.269         DO 275 I=1,NOICPS
L.270         DRSICP(I)=0
L.271         DO 275 J=1,CMAX
L.272         DO 275 K=1,8
L.273         PT1ICP(I,J,K)=0
L.274         PT2ICP(I,J,K)=0
L.275   275   CONTINUE
L.276         DO 280 I=1,NONDS
L.277         SWCONT(I)=1
L.278         SEMPH(I)=3
L.279         BUSSEM(I)=3
L.280         DATABS(I)=3
L.281         SEMPRC(I,3)=(-200)
L.282         DO 276 J=1,NOPCKS
L.283         DO 276 K=1,3
L.284         NODEST(I,J,K)=0
L.285   276   CONTINUE
L.286         DO 280 J=1,QUS
L.287         DO 280 K=1,8
L.288         QLIST(I,J,K)=0
L.289         IF (K.GT.2) GO TO 280
L.290         Q(I,J,K)=0
L.291   280   CONTINUE
L.292         DO 285 I=1,NONCPS
L.293         DO 285 M=1,8
L.294         FIELD2(I,M,1)=1
L.295   285   CONTINUE
L.296         DO 292 I=1,NOPCKS
L.297         DO 290 J=1,6
L.298         PACKET(I,J)=0
L.299   290   CONTINUE
L.300         DO 291 J=1,NONCPS
L.301         DUPLCT(I,J)=0
L.302   291   CONTINUE
L.303   292   CONTINUE
L.304 C
L.305         DO 298 I=1,N
L.306         PMEAN=IOP(I,8)
L.307         CALL GGUBS(DSEED,NRDN,R)
L.308         DO 294 K=1,NRDN
L.309         MSGLNZ(I,K)=(-PMEAN)*ALOG(1-R(K))
L.310   294   CONTINUE
L.311         PMEAN=IOP(I,9)
L.312         CALL GGUBS(DSEED,NRDN,R)
L.313         DO 296 K=1,NRDN
L.314         MSGEXP(I,K)=(-1.0/PMEAN)*ALOG(1-R(K))
L.315   296   CONTINUE
L.316   298   CONTINUE
```

BLOCK: MAIN EXECUTION



Figure B.5 Main Execution Block

BLOCK: MAIN EXECUTION

MODULE: PACKET INJECTION

Subroutine GGUBS (DSEED, NUMBER, W)

GGUBS is a routine called from the International Mathematical and Statistics Library (IMSL) for generating variates with a Poisson distribution.

DSEED: initial seed - double precision

NUMBER: number of variates generated

W(K): output array of subroutine, where K is greater than or equal to the number of variates generated

Generation of interarrival times (and lengths) with a Poisson distribution for packets:

$$p(K) = e^{-t/m} (t/m)^K/K!$$

p(K): probability of K arrivals in interval t

$$p(0) = e^{-t/m}$$ m: mean

probability of an arrival in time t:

$$p = 1 - p(0) = 1 - e^{-t/m}$$

$$t = -m\ln (1 - P)$$

P: is the variate generated by GGUBS

```
BLOCK:    MAIN EXECUTION

MODULE:   PACKET INJECTION

VIRTM (I)  =  PGM CONTROL  :  I VIRTUAL CIRCUIT NUMBER

INITIAL VALUE VIRTM (I) IS 1

DO FOR EACH VIRTUAL CIRCUIT (4080):

                          PGM CONTROL VIRTM (I):

IF VIRTM (I)  =  1:

     SET VIRTM (I)  =  2;

     GENERATE INTERARRIVAL INTERVAL;

     PERFORM INTERVAL GENERATION ON CLOCK;


IF VIRTM (I)  =  2:

     IF INTERVAL HAS NOT YET ELAPSED GO TO LBL (4080);

     SET VIRTM (I)  =  1;

          DO FOR PACKET ARRAY (4010):

          SEARCH FOR FREE LOCATION AND

          INSERT PACKET PARAMETERS

          4010 CONTINUE

     IF NO FREE LOCATION:  ABNORMAL TERMINATION

          DO FOR NODEST ARRAY (4040):

          SEARCH FOR FREE LOCATION AND

          INSERT PACKET PARAMETERS

          4040 CONTINUE

     IF NO FREE LOCATION:  ABNORMAL TERMINATION

          4080 CONTINUE

                  PACKET GENERATION FOR VIRTUAL CIRCUITS
```

```
L.317 C      ************************************************************
L.318 C      ************************************************************
L.319 C
L.320 C      MODEL  EXECUTION
L.321        DO 9999 INTERV=1,NUMBER
L.322 C
L.323        CNZ=4
L.324        CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L.325 C
L.326 C
L.327        DO 9999 KQU=1,SCAN
L.328 C
L.329 C      NETWORK  PACKET  INJECTION  FACILITY
L.330        DO 4080 I=NTTLI,NTTL
L.331        NSTAT=VIRTM(I)
L.332        GOTO (4005,4008), NSTAT
L.333  4005 VIRTM(I)=2
L.334        ID=I
L.335        CALL GGUBS(DSEED,NRRN,R)
L.336        TIMERZ(ID)=(-PMEANC)*ALOG(1-R(1))
L.337        CNZ=2
L.338        CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L.339  4008 IF (SIGNTM(I).NE.3) GOTO 4080
L.340        VIRTM(I)=1
L.341 C
L.342        DO 4010 M=1,NOPCKS
L.343        IF (PACKET(M,1).NE.0) GOTO 4010
L.344        DO 4000 NRU=1,NONCPS
L.345        IF (DUPLCT(M,NRU).NE.0) GOTO 4010
L.346  4000 CONTINUE
L.347        MPKO=M
L.348        PACKET(M,1)=I
L.349        PML N=IOP(I,8)
L.350        CALL GGUBS(DSEED,NRRN,R)
L.351        PACKET(M,2)=(-PMEAN)*ALOG(1-R(1))
L.352        PACKET(M,3)=1
L.353        PACKET(M,4)=0
L.354        PACKET(M,5)=7
L.355        PACKET(M,6)=0
L.356        CNZ=5
L.357        CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L.358        GOTO 4030
L.359  4010 CONTINUE
L.360        WRITE (6,4020)
L.361  4020 FORMAT (T2,'ERROR - PACKET ARRAY OVERFLOW')
L.362        GOTO 1111
L.363  4030 DO 4040 MM=1,NOPCKS
L.364        IF (NODEST(IOP(I,2),MM,1).NE.0) GOTO 4040
L.365        NODEST(IOP(I,2),MM,1)=MPKO
L.366        NODEST(IOP(I,2),MM,2)=IOP(I,3)
L.367        NODEST(IOP(I,2),MM,3)=1
L.368        GOTO 4080
L.369  4040 CONTINUE
L.370        WRITE (6,4050)
L.371  4050 FORMAT (T2,'ERROR - NODEST ARRAY OVERFLOW')
L.372        GOTO 1111
L.373  4080 CONTINUE
L.374 C
```

BLOCK: MAIN EXECUTION

MODULES: SOURCE HOST - NETWORK COMMUNICATION

DESTINATION HOST - NETWORK COMMUNICATION

I : IS LOGICAL LINK NUMBER

DO FOR EACH LOGICAL LINK (8999):

POISSON SOURCE GENERATOR

SOURCE-HOST

SOURCE MESSAGE GENERATION

N W COMM

ICP MESSAGE PROCESSING

DEST-HOST

DEST-HOST

REASSEMBLY

N W COMM

8999 CONTINUE

SUBMODULES OF ICP SIMULATION

BLOCK: MAIN EXECUTION

MODULE SOURCE HOST - NETWORK COMMUNICATION

SUBMODULE: POISSON SOURCE GENERATOR

DO FOR EACH LOGICAL LINK:

STATEG (I) = PGM CONTROL : I LOGICAL LINK NUMBER

INITIAL VALUE STATEG (I) = 2

IF QUOTA OF PACKETS GENERATED STATEG (I) = 1;

PROGRAM CONTROL STATEG (I);

IF STATEG (I) = 2:

SET STATEG (I) = 3;

GENERATE MESSAGE INTERARRIVAL TIME;

PERFORM INTERVAL GENERATION ON CLOCK;

IF STATEG (I) = 3:

IF INTERVAL HAS NOT YET ELAPSED GOTO LBL (320);

SET STATEG (I) = 2;

INCREMENT MESSAGE COUNTER TO INDICATE PACKET HAS BEEN GENERATED;

DECREMENT COUNTER IOP (I,10) TO INDICATE NUMBER OF MESSAGES STILL TO BE GENERATED;

IF STATEG (I) = 1:

320 CONTINUE

NO MORE MESSAGES GENERATED

POISSON SOURCE GENERATOR

```
L.375 C
L.376 C      USER - NETWORK INTERACTION
L.377 C
L.378        DO 8999 I=1,N
L.379 C
L.380 C      POISSON SOURCE GENERATOR
L.381        IF (IOP(I,10).EQ.0) STATEG(I)=1
L.382        NSTAT=STATEG(I)
L.383        GO TO (320,300,310), NSTAT
L.384   300  STATEG(I)=3
L.385        ID=I
L.386        TIMERZ(ID)=MSGEXP(I,RDNCTR(I))
L.387        CNZ=2
L.388        CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L.389   310  IF (SIGNTM(I).NE.3) GOTO 320
L.390        STATEG(I)=2
L.391        IOP(I,11)=IOP(I,11)+1
L.392        IOP(I,10)=IOP(I,10)-1
L.393   320  CONTINUE
L.394 C
```

BLOCK: MAIN EXECUTION

MODULE: SOURCE HOST-NETWORK COMMUNICATION

SUBMODULE: SOURCE MESSAGE GENERATION

DO FOR EACH LOGICAL LINK:

MESSAG (I) = PGM CONTROL : I LOGICAL LINK NUMBER;

INITIAL VALUE MESSAG (I) = 1

PROGRAM CONTROL MESSAG (I)

IF MESSAG (I) = 1:

IF MESSAGE COUNTER ZERO GOTO LBL (460);

DECREMENT MESSAGE COUNTER;

INSERT LENGTH INTO MESSAGE BUFFER;

INCREMENT MESSAGE LENGTH GENERATION COUNT;

IF MESSAGE LENGTH COUNT EQUALS MAXIMUM

THEN WRITE ERROR MESSAGE;

GENERATE TIME REQUIRED TO TRANSMIT CALLES

PACKET OVER CHANNEL;

PERFORM INTERVAL GENERATION ON CLOCK;

SET MESSAG (I) = 1;

IF MESSAG (I) = 2:

IF INTERVAL HAS NOT YET ELAPSED GOTO LBL (460);

SIGNAL CALLES: CALL ESTABLISHMENT TO ICP;

SET MESSAG (I) = 3;

IF MESSAG (I) = 3:

LBL 415 IF "READY FOR NEXT SEGMENT" - RFNS - NOT YET RECEIVED

GOTO LBL (460);

IF MESSAGE SIZE LESS THAN OR EQUAL TO
SEGMENT SIZE GOTO LBL (430);

DECREASE MESSAGE LENGTH BY SEGMENT LENGTH;

INSERT SEGMENT LENGTH INTO ICP BUFFER;

GENERATE TIME REQUIRED TO TRANSMIT SEGMENT OVER CHANNEL;

PERFORM INTERVAL GENERATION ON CLOCK;

SET MESSAG (I) = 4;

IF MESSAG (I) = 4:

IF INTERVAL NOT ELAPSED GOTO LBL (460);

SIGNAL MSGRDY: MESSAGE SEGMENT READY;

SET MESSAG (I) = 3;

GOTO LBL 415

LBL 430 INSERT SEGMENT LENGTH INTO ICP BUFFER;

GENERATE TIME REQUIRED TO TRANSMIT SEGMENT OVER CHANNEL;

PERFORM INTERVAL GENERATION ON CLOCK;

SET MESSAG (I) = 5;

IF MESSAG (I) = 5:

IF INTERVAL NOT ELAPSED GOTO LBL (460);

SIGNAL EOM: END OF MESSAGE;

SET MESSAG (I) = 6;

```
IF MESSAG (I) = 6:

     WAIT FOR SDEOM:  SOURCE-DESTINATION END OF MSG;

     IF NO SDEOM GOTO LBL (460);

     SET MESSAG (I) = 1;


LBL 460   CONTINUE
```

SOURCE MESSAGE GENERATION

```
L.395 C
L.396 C      MESSAGE GENERATION BY SOURCE
L.397        MESSG=MESSAG(I)
L.398        GO TO (400,410,415,420,440,450), MESSG
L.399   400  IF (IOP(I,11).EQ.0) GO TO 460
L.400        IOP(I,11)=IOP(I,11)-1
L.401        IOP(I,13)=MSGLNZ(I,RDNCTR(I))
L.402        RDNCTR(I)=RDNCTR(I)+1
L.403        IF (RDNCTR(I).EQ.NRDN) WRITE (6,405)
L.404   405  FORMAT (T2,'ERROR - NO.OF DEVIATES FOR RANDOM NO. GEN. EXC')
L.405        CALL TIMER (BITLNG,IOP(I,6),RIMR1)
L.406        ID=I+N
L.407        TIMERZ(ID)=RIMR1
L.408        CNZ=2
L.409        CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L.410        MESSAG(I)=2
L.411   410  IF (SIGNTM(I+N).NE.3) GOTO 460
L.412        CALLES=1
L.413        IOP(I,15)=CALLES
L.414        MESSAG(I)=3
L.415   415  RFNS=2
L.416        IF (IOP(I,15).NE.RFNS) GO TO 460
L.417        IF ((IOP(I,13)-SGMENT).LE.0) GO TO 430
L.418        IOP(I,13)=IOP(I,13)-SGMENT
L.419        IOP(I,14)=SGMENT
L.420        CALL TIMER (IOP(I,14),IOP(I,6),RIMR2)
L.421        ID=I+N
L.422        TIMERZ(ID)=RIMR2
L.423        CNZ=2
L.424        CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L.425        MESSAG(I)=4
L.426   420  IF (SIGNTM(I+N).NE.3) GOTO 460
L.427        MSGRDY=3
L.428        IOP(I,15)=MSGRDY
L.429        MESSAG(I)=3
L.430        GO TO 415
L.431   430  IOP(I,14)=IOP(I,13)
L.432        CALL TIMER (IOP(I,14),IOP(I,6),RIMR3)
L.433        ID=I+N
L.434        TIMERZ(ID)=RIMR3
L.435        CNZ=2
L.436        CALL PROGTM(TIMERZ,CLOCK,CNZ,I
L.437        MESSAG(I)=5
L.438   440  IF (SIGNTM(I+N).NE.3) GOTO 460
L.439        EOM=4
L.440        IOP(I,15)=EOM
L.441        MESSAG(I)=6
L.442   450  SDEOM=5
L.443        IF(IOP(I,15).NE.SDEOM) GO TO 460
L.444        MESSAG(I)=1
L.445   460  CONTINUE
L.446 C
```

FLAGS:

'WAIT-STATE' FLAG	IOP (I, 15)	=	11	SET
	IOP (I, 15)	=	12	RESET
'FIRST PACKET' FLAG	IOP (I, 16)	=	O/1	S/R
'MULTISEGMENT TRM' FLAG	IOP (I, 17)	=	O/1	S/R
'TRM CONTROL' FLAG	IOP (I, 19)	=	O/1	S/R

BLOCK: MAIN EXECUTION

MODULE: SOURCE HOST-NETWORK COMMUNICATION

SUBMODULE: ICP MESSAGE PROCESSING

DO FOR EACH LOGICAL LINK

SRCIO (I) = PGM CONTROL : I LOGICAL LINK NUMBER;

INITIAL VALUE SRCIO (I) = 1

PROGRAM CONTROL SRCIO (I)

IF SRCIO (I) = 1:

IF NO CALLES SIGNAL GOTO LBL (899);

CALL SUBR ACCESS TO ATTEMPT TO ALLOCATE
BUFFERS - DOUBLE BUFFERING INITIALLY;

IF ACCESS GRANTED GO TO LBL (506);

CALL SUBR RESERV TO RESERVE CALL REQUEST;

IF RESERVATION REFUSED (ALL LOCATIONS FOR
REQUESTS OCCUPIED): SIGNAL SDEOM;
SET SRCIO (I) = 1;
GOTO LBL (899);

SET ICP FLAG 'WAIT-STATE';

SET SRCIO (I) = 2;

SET LOGICAL LINK FLAG;

IF SRCIO (I) = 2:

IF LOGICAL LINK FLAG NOT RESET GOTO LBL (899);

- INDICATES BUFFERS ALLOCATED

LBL 506 GENERATE TIME TO TRANSMIT RFNS PACKET
OVER CHANNEL TO SOURCE;

PERFORM INTERVAL GENERATION ON CLOCK;

SET SRCIO (I) = 3;

IF SRCIO (I) = 3:

IF INTERVAL NOT ELAPSED GOTO LBL (899);

SIGNAL RFNS;

SET SRCIO (I) = 4;

IF SRCIO (I) = 4:

IF AN EOM OR MSGRDY NOT RECEIVED GOTO LBL (899);

SET "FIRST PACKET" FLAG;

SET "MULTISEGMENT TRM" FLAG;

LBL 700: DIVIDE SEGMENT IN ICP BUFFER INTO PACKETS;

KNTR (I): SET TO NUMBER OF PACKETS;

LBL 715: SET TRM COUNTER TO KNTR (I) - 1;

SET VARIABLE 'NRE' TO NUMBER OF PACKETS
TO BE TRANSMITTED;

IF "FIRST PACKET" FLAG SET NRE TO 1;

```
LBL 720:  DO FOR PACKET ARRAY (722) NRE:
             SEARCH FOR FREE LOCATIONS AND
             INSERT PACKET PARAMETERS;
          722 CONTINUE
          IF NO FREE LOCATION:  ABNORMAL TERMINATION
             DO FOR NODEST ARRAY (727) NRE:
             SEARCH FOR FREE LOCATIONS AND
             INSERT PACKET PARAMETERS;
          727 CONTINUE
          IF NO FREE LOCATION:  ABNORMAL TERMINATION

RESET "FIRST PACKET" FLAG;
          IF A SEGMENT HAS ALREADY BEEN SENT OR IF
          EOM NOT RECEIVED (BUT MSGRDY) GOTO LBL (760);

          RELEASE BUFFERS NOT USED BY MESSAGE (LESS THAN
          ONE SEGMENT SIZE) BY CALLING SUBR ACCESS;

          RESET "MULTISEGMENT TRM" FLAG;

LBL 760:  RESET 'TRM CONTROL' FLAG;
          IF EOM SET 'TRM CONTROL' FLAG;

          IF 'FIRST PACKET' FLAG RESET AND 'TRM COUNTER' ZERO
          (i.e. ALL PACKETS IN SEGMENT HAVE BEEN TRANSMITTED -
          MULTISEGMENT) GO TO LBL (870);

          IF 'FIRST PACKET' FLAG RESET AND EOM RECEIVED (ALL
          PACKETS TRANSMITTED IN MESSAGE) GO TO LBL (870);
```

IF 'FIRST PACKET' FLAG RESET (i.e., FIRST PACKET HAS BEEN TRANSMITTED AND REST TO FOLLOW) GOTO LBL (790);

SET SRCIO (I) = 5;

IF SRCIO (I) = 5:

IF 'NEGATIVE ACK' PACKET, OR 'READY FOR NEXT SEGMENT' PACKET, OR 'BUFFER ACCESS ACK' PACKET NOT RECEIVED GOTO LBL (899);

RESET 'SOURCE-TO-ICP TRM' FLAG;

IF 'NEGATIVE ACK' PACKET RECEIVED (NO DEST BUFFERS AVAILABLE) GOTO LBL (850);

SET TRM COUNTER CONTENTS TO NRE: NO OF PACKETS TO BE SENT

IF 'BUFFER ACCESS ACK' PACKET RECEIVED
INCREMENT NRE (TRANSMIT ALL REMAINING
PACKETS ANF RETRANSMIT THE FIRST PACKET);
GOTO LBL (720);

LBL 790: GENERATE TIME TO TRANSMIT PACKET OVER CHANNEL TO SOURCE HOST; PERFORM INTERVAL GENERATION ON CLOCK;

SET SRCIO (I) = 6

IF SRCIO (I) = 6:

IF INTERVAL HAS NOT ELAPSED GOTO LBL (899);

TRANSMIT 'RFNS' TO SOURCE ICP;

SET SRCIO (I) = 7;

IF SRCIO (I) = 7:

IF MSGRDY OR EOM: i.e., A SEGMENT NOT RECEIVED YET:

WAIT - GOTO LBL (899);

SET SRCIO (I) = 8;

IF SRCIO (I) = 8;

IF 'SOURCE-TO-ICP TRM' FLAG NOT SET: WAIT -

GOTO LBL (899);

RESET 'SOURCE-TO-ICP TRM' FLAG;

GO TO LBL 700, i.e., PREPARE TO TRM NEXT SEGM;

LBL 850 RELEASE ALL UNUSED BUFFERS THAT HAVE BEEN

ALLOCATED (DOUBLE BUFFERING IS PROVIDED AT

CALLES (CALL ESTABLISHMENT) OR MULTISGM TRM

GOTO LBL 875;

LBL 870 SET SRCIO (I) = 9;

```
IF SRCIO (I)  =  9:

     IF 'SDEOM' (ACK OF END OF TRM:  SOURCE ICP-TO-DEST
     ICP) OR 'TRMNCK' (CALL TERMINATION, NO BUFFERS
     AT DEST ICP) WAIT:  GOTO LBL (899);

LBL 875 SET SRCIO (I)  =  10;

     GENERATE TIME TO TRANSMIT SDEOM PACKET TO SOURCE
     HOST BY SOURCE ICP (END OF CALL);

     PERFORM INTERVAL GENERATION ON CLOCK;

IF SRCIO (I)  =  10:

     IF INTERVAL HAS NOT ELAPSED GOTO LBL (899);

     SET SRCIO (I)  =  1;

     SIGNAL SDEOM

899 CONTINUE;

     END;
```

SOURCE ICP PROCESSING

```
L.447 C
L.448 C       WAITING  FOR  MESSAGE  ARRIVALS
L.449         MSRC=SRCIO(I)
L.450         GO TO (500,505,510,515,780,800,820,840,870,880), MSRC
L.451   500   CALLES=1
L.452         IF (IOP(I,15).NE.CALLES) GO TO 899
L.453 C       REQUEST  FOR  SOURCE  BUFFER
L.454         RST=2
L.455         NRB=2*NSOURC
L.456         LINKNR=I
L.457         ICPNR=IOP(I,3)
L.458         TNR=1
L.459         CALL ACCESS(RST,NRB,LINKNR,ICPNR,TNR,ACC,SDM,NCR,NSOU,NSING,NMUL)
L.460         IF (ACC.EQ.1) GO TO 506
L.461         IF (ACC.NE.2) WRITE (6,501)
L.462   501   FORMAT (T2,'ERROR NO8')
L.463         ST=3
L.464         ICP=IOP(I,3)
L.465         LNK=I
L.466         NO=2*NSOURC
L.467         CNZ=5
L.468         CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L.469         CL=CLOCK
L.470         TPE=1
L.471 C       REQUEST  RESERVATION
L.472         CALL RESERV(ST,ICP,LNK,NO,CL,RES,TPE)
L.473         IF (RES.EQ.1) GO TO 503
L.474         IF (RES.NE.2) WRITE (6,502)
L.475   502   FORMAT (T2,'ERROR NO9')
L.476 C       PURGE  MESSAGE
L.477         IOP(I,15)=5
L.478         SRCIO(I)=1
L.479         GO TO 899
L.480 C       MESSAGE WAITING FOR BUFFER
L.481   503   WAITST=11
L.482         IOP(I,15)=WAITST
L.483         SRCIO(I)=2
L.484         LGLINK(I,1)=1
L.485   505   WAITFN=12
L.486         IF (LGLINK(I,1).NE.2) GOTO 899
L.487   506   CALL TIMER (BITLNG,IOP(I,6),RIMR4)
L.488         ID=I+(2*N)
L.489         TIMERZ(ID)=RIMR4
L.490         CNZ=2
L.491         CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L.492         SRCIO(I)=3
L.493   510   IF (SIGNTM(I+(2*N)).NE.3) GOTO 899
L.494 C       SOURCE NODE READY TO RECEIVE MESSAGE
L.495         RFNS=2
L.496         IOP(I,15)=RFNS
L.497         SRCIO(I)=4
L.498   515   IF (IOP(I,15).NE.3 .AND. IOP(I,15).NE.4) GO TO 899
L.499         IOP(I,16)=0
L.500         IOP(I,17)=0
```

```
.501   700  KNTR(I)=0
L.502       KNS=IOP(I,14)
L.503       IOP(I,20)=IOP(I,14)
L.504  710  KNF=PSZNO-KNS
L.505       KNTR(I)=KNTR(I)+1
L.506       IF (KNF.GE.0) GO TO 715
L.507       KNS=KNS-PSZNO
L.508       GO TO 710
L.509  715  IOP(I,12)=KNTR(I)-1
L.510       NRE=KNTR(I)
L.511       IF (IOP(I,16).EQ.0) NRE=1
L.512  720  DO 728 NS=1,NRE
L.513       DO 722 M=1,NOPCKS
L.514       IF (PACKET(M,1).NE.0) GO TO 722
L.515       DO 721 NRY=1,NONCPS
L.516       IF (DUPLCT(M,NRY).NE.0) GOTO 722
L.517  721  CONTINUE
L.518       PACKET(M,1)=I
L.519       NTST=PSZNO-IOP(I,20)
L.520       IF (NTST.LT.0) PACKET(M,2)=PSZNO
L.521       IF (NTST.LT.0) IOP(I,20)=IOP(I,20)-PSZNO
L.522       IF (NTST.GE.0) PACKET(M,2)=IOP(I,20)
L.523       PACKET(M,3)=0
L.524       PACKET(M,4)=KNTR(I)
L.525       PACKET(M,5)=1
L.526       IF (IOP(I,15).EQ.4) PACKET(M,5)=7
L.527       PACKET(M,6)=0
L.528       MPK1=M
L.529       GOTO 726
L.530  722  CONTINUE
L.531       WRITE (6,723)
L.532  723  FORMAT (T2,'ERROR - PACKET ARRAY OVERFLOW')
L.533  726  DO 727 MM=1,NOPCKS
L.534       IF (NODEST(IOP(I,2),MM,1).NE.0) GO TO 727
L.535       NODEST(IOP(I,2),MM,1)=MPK1
L.536       NODEST(IOP(I,2),MM,2)=IOP(I,3)
L.537       NODEST(IOP(I,2),MM,3)=1
L.538       GO TO 728
L.539  727  CONTINUE
L.540       WRITE (6,729)
L.541  729  FORMAT (T2,'ERROR - NODEST ARRAY OVERFLOW')
L.542  728  CONTINUE
L.543       IOP(I,16)=IOP(I,16)+1
L.544       IF (IOP(I,17).EQ.1) GO TO 760
L.545       IF (IOP(I,15) EQ.3) GO TO 760
L.546       NX=0
L.547       ND=IOP(I,14)
L.548  750  ND=ND-BUFBLK
L.549       NX=NX+1
L.550       IF (ND.GT.0) GO TO 750
L.551       NRB=(2*NSOURC)-NX
L.552       RST=1
L.553       LINKNR=I
L.554       ICPNR=IOP(I,3)
L.555       TNR=1
L.556       CALL ACCESS(RST,NRB,LINKNR,ICPNR,TNR,ACC,SDM,NCR,NSOU,NSING,NMUL)
```

```
L.557          IOP(I,17)=1
L.558    760   IOP(I,19)=1
L.559          IF (IOP(I,15).EQ.4) IOP(I,19)=2
L.560          IF (IOP(I,16).EQ.1 .AND. IOP(I,12).EQ.0) GO TO 870
L.561          IF (IOP(I,16).GE.2 .AND. IOP(I,15).EQ.4) GO TO 870
L.562          IF (IOP(I,16).GE.2) GO TO 790
L.563          SRCIO(I)=5
L.564    780   IF (IOP(I,15).NE.9 .AND. IOP(I,18).NE.1 .AND. IOP(I,15).NE.23) GO T
CONT:    899
L.565          IOP(I,18)=0
L.566          IF (IOP(I,15).EQ.9) GO TO 850
L.567          NRE=IOP(I,12)
L.568          IF (IOP(I,15).EQ.23) NRE=NRE+1
L.569          GO TO 720
L.570    790   CALL TIMER(BITLNG,IOP(I,6),RIMR5)
L.571          ID=I+(2*N)
L.572          TIMERZ(ID)=RIMR5
L.573          CNZ=2
L.574          CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L.575          SRCIO(I)=6
L.576    800   IF (SIGNTM(I+(2*N)).NE.3) GOTO 899
L.577          IOP(I,15)=2
L.578          SRCIO(I)=7
L.579    820   IF (IOP(I,15).NE.3 .AND. IOP(I,15).NE.4) GO TO 899
L.580          SRCIO(I)=8
L.581    840   IF (IOP(I,18).NE.1) GO TO 899
L.582          IOP(I,18)=0
L.583          GO TO 700
L.584    850   NRB=0
L.585          IOP(I,14)=IOP(I,14)-PSZNO
L.586    860   IOP(I,14)=IOP(I,14)-BUFBLK
L.587          NRB=NRB+1
L.588          IF (IOP(I,14).GE.0) GO TO 860
L.589          IF (IOP(I,19).EQ.1) NRB=2*NSOURC
L.590          RST=1
L.591          LINKNR=I
L.592          ICPNR=IOP(I,3)
L.593          TNR=1
L.594          CALL ACCESS(RST,NRB,LINKNR,ICPNR,TNR,ACC,SDM,NCR,NSOU,NSING,NMUL)
L.595          GO TO 875
L.596    870   SRCIO(I)=9
L.597          IF (IOP(I,15).NE.10 .AND. IOP(I,15).NE.9) GO TO 899
L.598    875   SRCIO(I)=10
L.599          CALL TIMER(BITLNG,IOP(I,6),RTMZ)
L.600          ID=I+(2*N)
L.601          TIMERZ(ID)=RTMZ
L.602          CNZ=2
L.603          CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L.604    880   IF (SIGNTM(I+(2*N)).NE.3) GOTO 899
L.605          SRCIO(I)=1
L.606          IOP(I,15)=5
L.607    899   CONTINUE
L.608  C
```

BLOCK: MAIN EXECUTION

MODULE: DESTINATION HOST-NETWORK COMMUNICATION

DO FOR EACH LOGICAL LINK

DEST(I): PGM CONTROL: I LOGICAL LINK NUMBER

INITIAL VALUE DEST (I) = 1

PROGRAM CONTROL DEST(I)

IF DEST (I) = 1:

IF NO PACKET IN INPUT BUFFER (FROM NETWORK)
GOTO LBL (8900)

IF PACKET IS DATA PACKET GOTO LBL (8030)
CONTROL PACKET SORTING:

IF PACKET CONTROL = 2 SET 'BUFFER ACCESS ACK' FLAG;

IF PACKET CONTROL = 4 SET 'SOURCE-TO-ICP TRM' FLAG;

IF PACKET CONTROL = 5 SET 'TRMNCK' - NO BUFFERS;

IF PACKET CONTROL = 6 SET 'READY FOR NEXT SGM';

GOTO LBL (8900)

LBL 8030 DATA PACKET RECEIVED: FIRST IN SEGMENT:

STORE PARAMETERS OF PACKETS;

IF EOM MESSAGE INDICATED SET 'BUFFERING' FLAG;

IF BUFFERING FLAG RESET CALL ACCESS TO PROVIDE
DOUBLE BUFFERING FOR CALL;

IF BUFFERING FLAG SET CALL ACCESS TO PROVIDE
REQUIRED NO BLOCKS TO STORE MSG;

IF BUFFERS PROVIDED GO TO LBL (8080);

```
NO BUFFERS AVAILABLE:  CALL RESERV TO RESERVE
   BUFFERS WHEN THESE BECOME FREE;

SET DEST (I)  =  2;

SET 'WAIT' FLAG;


IF DEST (I)  =  2:

     IF 'WAIT' FLAG NOT RESET GO TO LBL (8900);
        i.e. BUFFER BLOCKS NOT YET FREE

     TRANSMIT CONTROL PACKET TO SOURCE ICP -
        'BUFFER ACCESS ACK':  ALL PACKETS TO BE
        TRM INCLUDING RETRM OF FIRST (NOT STORED)

     GOTO LBL (8090)


LBL (8080):  TRANSMIT CONTROL PACKET TO SOURCE ICP -
     'SOURCE-TO-ICP TRM':  ALL REMAINING PACKETS TO
     BE TRM, SIGNAL SOURCE HOST TO TRM
     NEXT SEGMENT TO SOURCE ICP;

     IF ONLY ONE PACKET IN MESSAGE (SINGLE PCK)
        GOTO LBL 8220;


LBL 8090:  DO FOR PACKET ARRAY (8092):

     SEARCH FOR FREE LOCATIONS AND INSERT PACKET PARAMETERS;

     8092 CONTINUE;
     IF NO FREE LOCATION:  ABNORMAL TERMINATION
     DO FOR NODEST ARRAY (8100):
     SEARCH FOR FREE LOCATIONS AND
     INSERT PACKET PARAMETERS;

8100 CONTINUE;
```

```
NO BUFFERS AVAILABLE:  CALL RESERV TO RESERVE
   BUFFERS WHEN THESE BECOME FREE;

SET DEST (I)  =  2;

SET 'WAIT' FLAG;


IF DEST (I)  =  2:

IF 'WAIT' FLAG NOT RESET GO TO LBL (8900);
   i.e. BUFFER BLOCKS NOT YET FREE

TRANSMIT CONTROL PACKET TO SOURCE ICP -
   'BUFFER ACCESS ACK':  ALL PACKETS TO BE
   TRM INCLUDING RETRM OF FIRST (NOT STORED)

GOTO LBL (8090)


LBL (8080):  TRANSMIT CONTROL PACKET TO SOURCE ICP -
     'SOURCE-TO-ICP TRM':  ALL REMAINING PACKETS TO
     BE TRM, SIGNAL SOURCE HOST TO TRM
     NEXT SEGMENT TO SOURCE ICP;

     IF ONLY ONE PACKET IN MESSAGE (SINGLE PCK)
        GOTO LBL 8220;


LBL 8090:  DO FOR PACKET ARRAY (8092):

     SEARCH FOR FREE LOCATIONS AND INSERT PACKET PARAMETERS;

     8092 CONTINUE;
     IF NO FREE LOCATION:  ABNORMAL TERMINATION
     DO FOR NODEST ARRAY (8100):
     SEARCH FOR FREE LOCATIONS AND
     INSERT PACKET PARAMETERS;

8100 CONTINUE;
```

```
IF 'MULTISEGMENT TRM' FLAG RESET, i.e. NO MORE SEGMENTS
     TO BE RECEIVED GOTO LBL (8240);
     SET DEST (I)  =  3;
IF DEST (I)  =  3:
     WAIT FOR REST OF SEGMENTS CONSTITUTING SEGMENT:
        IF NO PACKET GOTO LBL (8900);
     STORE PACKET PARAMETERS;
     RESET BUFFERING FLAG;
     IF 'EOM' SET BUFFERING FLAG;
     IF ALL PACKETS CONSTITUTING SEGMENT NOT YET RECEIVED
     WAIT FOR REST:  GOTO LBL (8900);  IF BUFFERING FLAG
     SET AND FLOW CONTROL FLAG RESET GOTO LBL 8200:
     PREPARE TO TRM SGM TO HOST AND RELEASE BUFFERS;
     SET DEST (I)  =  4;

GENERATE TIME TO TRM SEGMENT TO DEST HOST;
PERFORM INTERVAL GENERATION ON CLOCK;

IF DEST (I)  =  4:
     IF INTERVAL NOT ELAPSED GO TO LBL (8900);
     SET BUFFERING FLAG
     TRANSMIT 'RFNS' PACKET TO SOURCE ICP
     GO TO LBL 8090
```

LBL 8200 IF MULTISGM TRM FLAG RESET i.e. MESSAGE WAS
SINGLE SGM GO TO LBL (8220)
RELEASE UNUSED BUFFERS: BUFFERING REVERTS FROM
DOUBLE TO EXACT BLOCK ALLOCATION GENERATE TIME FOR
SEGMENT TRM TO DEST HOST;
PERFORM INTERVAL GENERATION ON CLOCK;
SET DEST (I) = 5;

IF DEST (I) = 5:

LBL (8220) IF INTERVAL NOT ELAPSED GOTO LBL (8900);
RELEASE ALL BUFFERS;
TRANSMIT FINAL ACK PACKET TO SOURCE ICP;
GO TO LBL (8090);
RESET ALL PARAMETER STORAGE LOCATIONS;
SET DEST (I) = 1;

8900 IF RESERVATION REQUESTED AT SOURCE ICP
SET ICP RESERV FLAG (1);
IF RESERVATION REQUESTED AT DEST ICP
SET ICP RESERV FLAG (2);

LBL 8999 CONTINUE END;

DESTINATION ICP PROCESSING

```
      DO FOR ALL ICP's (5000):
      IF ANY ICP RESERV FLAGS ARE SET THEN ACTIVATE
      RESERVATION ALGORITHM BY CALLING SUBR RESERV;
      RESET ICP RESERV FLAGS;

LBL 5000   CONTINUE;
      END;
```

RESERV SUBR CALLING

```
      NDES=DF-1(I)
      GO TO (8010,8070,81[illegible],81[illegible],8[illegible]30),NDES
 8010 IF (REASSM(I,1).EQ.0) GO TO 8900
      PKNR=REASSM(I,1)
      REASSM(I,1)=0
      IF (PACKET(PKNR,5).EQ.1 .OR. PACKET(PKNR,5).EQ.7) GOTO 8030
 8015 IF (PACKET(PKNR,5).EQ.4) IOP(I,18)=1
      IF (PACKET(PKNR,5).EQ.5) IOP(I,15)=9
      IF (PACKET(PKNR,5).EQ.6) IOP(I,15)=10
      IF (PACKET(PKNR,5).EQ.2) IOP(I,15)=23
      PACKET(PKNR,1)=0
      GO TO 8900
 8030 REASSM(I,2)=PACKET(PKNR,4)
      REASSM(I,3)=1
      REASSM(I,4)=PACKET(PKNR,2)
      REASSM(I,7)=0
      REASSM(I,6)=0
      IF (PACKET(PKNR,5).EQ.7) REASSM(I,6)=1
      PACKET(PKNR,1)=0
      IF (REASSM(I,6).EQ.0) NRB=2*NSOURC
      IF (REASSM(I,6).EQ.0) GOTO 8065
      NRB=0
      LISM=BUFBLK
      LITM=PSZNO*REASSM(I,2)
 8060 LMLQ=LISM-LITM
      NRB=NRB+1
      LITM=LITM-BUFBLK
      IF (LMLQ.LT.0) GO TO 8060
      REASSM(I,8)=NRB
 8065 RST=2
      LINKNR=I
      ICPNR=IOP(I,5)
      TNR=3
      IF (REASSM(I,2).EQ.1) TNR=2
      CALL ACCESS(RST,NRB,LINKNR,ICPNR,TNR,ACC,SDM,NCR,NSOU,NSING,NMUL)
      IF (ACC.EQ.1) GOTO 8080
      CNZ=5
      CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
      CL=CLOCK
      ST=3
      ICP=IOP(I,5)
      CALL RESERV(ST,ICP,I,NRB,CL,RES,TNR)
      IF (RES.EQ.2) REASSM(I,5)=2
      IF (RES.EQ.2) MSMG=5
      IF (RES.EQ.2) GO TO 8090
      DEST(I)=2
      LGLINK(I,2)=1
 8070 IF (LGLINK(I,2).NE.2) GOTO 8900
C     RESERVED BUFFERS ACCESSED
      MSMG=2
      REASSM(I,5)=1
      REASSM(I,4)=0
      REASSM(I,3)=0
      GOTO 8090
 8080 REASSM(I,5)=1
      MSMG=4
      IF (REASSM(I,2).EQ.1) GO TO 8220
 8090 DO 8095 M=1,NOPCKS
      IF (PACKET(M,1).NE.0) GOTO 8095
      DO 8092 NRD=1,NONCPS
      IF (DUPLCT(M,NRD).NE.0) GOTO 8095
 8092 CONTINUE
```

```
L.672          PACKET(M,1)=
L.673          PACKET(M,2)=PKTLNG
L.674          PACKET(M,3)=0
L.675          PACKET(M,4)=1
L.676          PACKET(M,5)=MSMG
L.677          PACKET(M,6)=0
L.678          MPK2=M
L.679          GO TO 8097
L.680    8095  CONTINUE
L.681          WRITE (6,8096)
L.682    8096  FORMAT (T2,'ERROR - PACKET ARRAY OVERFLOW')
L.683    8097  DO 8100 M=1,NOPCKS
L.684          IF (NODEST(IOP(I,4),M,1).NE.0) GOTO 8100
L.685          NODEST(IOP(I,4),M,1)=MPK2
L.686          NODEST(IOP(I,4),M,2)=IOP(I,5)
L.687          NODEST(IOP(I,4),M,3)=1
L.688          GOTO 8120
L.689    8100  CONTINUE
L.690          WRITE (6,8110)
L.691    8110  FORMAT (T2,'ERROR - NODEST ARRAY OVERFLOW')
L.692    8120  IF (REASSM(I,5).EQ.1) GOTO 8140
L.693          IF (REASSM(I,5).EQ.2) GOTO 8240
L.694    8140  DEST(I)=3
L.695          IF (REASSM(I,1).EQ.0) GO TO 8900
L.696          PKNR=REASSM(I,1)
L.697          REASSM(I,1)=0
L.698          IF (PACKET(PKNR,5).NE.1 .AND. PACKET(PKNR,5).NE.7) GOTO 8015
L.699          REASSM(I,2)=PACKET(PKNR,4)
L.700          REASSM(I,3)=REASSM(I,3)+1
L.701          REASSM(I,4)=REASSM(I,4)+PACKET(PKNR,2)
L.702          REASSM(I,6)=0
L.703          IF (PACKET(PKNR,5).EQ.7) REASSM(I,6)=1
L.704          PACKET(PKNR,1)=0
L.705          IF (REASSM(I,2).NE.REASSM(I,3)) GOTO 8900
L.706          IF (REASSM(I,6).EQ.1 .AND. REASSM(I,7).EQ.0) GOTO 8200
L.707          IF (REASSM(I,7).EQ.0) GOTO 8170
L.708    8160  DEST(I)=4
L.709          IF (SIGNTM(I+(3*N)+NONCPS+NONDS).NE.3) GOTO 8900
L.710          IF (REASSM(I,6).EQ.1) GOTO 8200
L.711    8170  CALL TIMER(REASSM(I,4),IOP(I,7),RIMR9)
L.712          ID=I+(3*N)+NONCPS+NONDS
L.713          TIMERZ(ID)=RIMR9
L.714          CNZ=2
L.715          CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L.716          DO 8180 M=1,6
L.717          REASSM(I,M)=0
L.718    8180  CONTINUE
L.719          REASSM(I,7)=1
L.720          MSMG=4
L.721          REASSM(I,5)=1
L.722          GO TO 8090
L.723    8200  IF (REASSM(I,7).NE.1) GO TO 8220
```

```
L.724         KCC=0
L.725         LISM=BUFBLK
L.726         LITM=PSZNO*REASSM(I,2)
L.727   8210 LMLQ=LISM-LITM
L.728         KCC=KCC+1
L.729         LITM=LITM-BUFBLK
L.730         IF (LMLQ.LT.0) GO TO 8210
L.731         REASSM(I,8)=KCC
L.732         NRB=(2*NSOURC)-REASSM(I,8)
L.733         RST=1
L.734         LINKNR=I
L.735         ICPNR=IOP(I,5)
L.736         TNR=3
L.737         CALL ACCESS(RST,NRB,LINKNR,ICPNR,TNR,ACC,SDM,NCR,NSOU,NSING,NMUL)
L.738   8220 CALL TIMER(REASSM(I,4),IOP(I,7),RIMR10)
L.739         ID=I+(3*N)+NONCPS+NONDS
L.740         TIMERZ(ID)=RIMR10
L.741         CNZ=2
L.742         CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L.743         DEST(I)=5
L.744   8230 IF (SIGNTM(I+(3*N)+NONCPS+NONDS).NE.3) GOTO 8900
L.745         NRB=REASSM(I,8)
L.746         RST=1
L.747         LINKNR=I
L.748         ICPNR=IOP(I,5)
L.749         TNR=3
L.750         IF (REASSM(I,2).EQ.1) TNR=2
L.751         IF (REASSM(I,7).EQ.1) TNR=3
L.752         CALL ACCESS(RST,NRB,LINKNR,ICPNR,TNR,ACC,SDM,NCR,NSOU,NSING,NMUL)
L.753         MSMG=6
L.754         REASSM(I,5)=2
L.755         GOTO 8090
L.756   8240 DO 8250 M=1,8
L.757         REASSM(I,M)=0
L.758   8250 CONTINUE
L.759         DEST(I)=1
L.760 C
L.761   8900 IF (IOP(I,15).EQ.11) DRSICP(IOP(I,3))=1
L.762         IF (DEST(I).EQ.2) DRSICP(IOP(I,5))=1
L.763   8999 CONTINUE
L.764 C
L.765         DO 5000 I=1,NOICPS
L.766         IF (DRSICP(I).EQ.0) GO TO 5000
L.767         ST=7
L.768         CALL RESERV(ST,I,LNK,NO,CL,RES,TPE)
L.769         DRSICP(I)=0
L.770   5000 CONTINUE
L.771 C
```

BLOCK: MAIN EXECUTION

MODULES: NODE-TO-NODE PROTOCOL

```
I IS NCP NUMBER
DO FOR EACH NCP (3999):
PACKET RECEPTION AND STORAGE FROM BUS
RETRM AND PARTITION TIMING
LINE TRANSMISSION: FIELD SETTING
LINE TRANSMISSION                                   SUB-MODULES
RECEIVING PHASE
BUFFER RELEASE
BUFFER RELEASE
ACKNOWLEDGEMENT PROCESSING & STORAGE

3999 CONTINUE
```

SUBMODULES FOR INTERNODAL TRANSMISSION

BLOCK: MAIN EXECUTION

MODULE: INTERNODAL TRM

SUBMODULE: DATA BUS TO NCP PACKET TRM - STORAGE

DO FOR EACH NCP:

I: LOGICAL LINK NUMBER

IF INTERFACE BUFFER EMPTY i.e. NO PACKET TO BE TRM TO THE DEST NODE GOTO LBL 3070;

A) DETERMINE PARTITION TO WHICH PACKET IS ALLOCATED:

STORE LOGICAL LINK ID: LOGLNO

DETERMINE FINAL DEST NODE: DESTND - CONTROL PACKETS BELONGING TO A GIVEN LOGICAL LINK MOVE IN THE OPPOSITE DIRECTION TO DATA PACKETS, THESE THUS HAVE A DIFFERENT DEST.

DO LOOP (3006): DETERMINE PRESENT NODE

3008 THEN PARTITION: PARTON - MAY BE FOUND

B) ALLOCATE PRIORITY TO PACKET: TRANSMISSION PRIORITY IS FCFS

DO LOOP (3002): FIND HIGHEST PRIORITY FACTOR IN PARTITION BUFFERS

DO LOOP (3004): FIND HIGHEST PRIORITY FACTOR IN COMMON BUFFERS

ALLOCATE NEXT HIGHEST PRIORITY FACTOR TO PACKET

NB. PACKET WITH LOWEST PRIORITY FACTORS TRANSMITTED FIRST

C) PACKET STORAGE

DO LOOP (3000): SEARCH FOR ADDRESS OF PARTITION BUFFERS WHERE PACKET MAY BE STORED, ATTEMPT TO STORE PACKET IN PARTITION TRMBUF BUFFER, IF OCCUPIED THEN ATTEMPT TO STORE PACKET IN PARTITION QBUF BUFFER, IF OCCUPIED THEN STORE PACKET IN A COMMON BUFFER

END LBL 3070

NB. THE SWITCH PROCESSOR MAINTAINS A LIST OF THE NUMBER OF FREE BUFFER BLOCKS IN EACH NCP. A PACKET SENT TO AN NCP FROM WITHIN THE NODE MUST THEREFORE ALWAYS BE ABLE TO FIND A FREE BUFFER (TRANSMISSION AND RECEIVING BUFFERS ARE SEPARATED) OTHERWISE AN ABNORMAL TERMINATION RESULTS

DATA BUS SIMULATION

```
L.772         INTERNODE PACKET TRANSMISSION: LOCAL PROTOCOLS
L.773         DO 3999 I=1,NONCPS
L.774 C       DATA BUS TO NCP BUFFERING INTERFACE
L.775         IF (IFBUFR(I).EQ.0) GO TO 3070
L.776         PCKNO=IFBUFR(I)
L.777         LOGLNO=PACKET(PCKNO,1)
L.778         DESTND=IOP(LOGLNO,4)
L.779         IF (PACKET(PCKNO,5).NE.1 .AND. PACKET(PCKNO,5).NE.7) DESTND=IOP(LOG
CONT: NO,2)
L.780         DO 3006 KM=1,NONDS
L.781         DO 3006 KN=1,NMAXIN
L.782         IF (MAPNCP(KM,KN).EQ.I) PRSNND=KM
L.783         IF (MAPNCP(KM,KN).EQ.I) GO TO 3008
L.784  3006 CONTINUE
L.785         WRITE (6,3007)
L.786  3007 FORMAT (T2,'ERROR - "PRESENT NODE" NOT FOUND')
L.787         GO TO 1111
L.788  3008 PARTON=NODPLT(PRSNND,DESTND,1)
L.789         KRRS=0
L.790         DO 3002 J=1,8
L.791         DO 3002 K=2,3
L.792         MPPK=PRTNS1(I,J,K)
L.793         IF (MPPK.EQ.0) GOTO 3002
L.794         IF (PACKET(MPPK,6).GT.KRRS) KRRS=PACKET(MPPK,6)
L.795  3002 CONTINUE
L.796         DO 3004 K=1,MNOBFS
L.797         MPPK=BFPOOL(I,K,1)
L.798         IF (MPPK.EQ.0) GOTO 3004
L.799         IF (PACKET(MPPK,6).GT.KRRS) KRRS=PACKET(MPPK,6)
L.800  3004 CONTINUE
L.801         KRRS=KRRS+1
L.802         PACKET(PCKNO,6)=KRRS
L.803         IF (DUPLCT(PCKNO,I).NE.0) WRITE (6,3014)
L.804         IF (DUPLCT(PCKNO,I).NE.0) GOTO 1111
L.805  3014 FORMAT (T2,'ERROR - DUPLICATION PROCEDURE  STM 3014 MAIN PGM')
L.806         DUPLCT(PCKNO,I)=1
L.807         DO 3000 K=1,8
L.808         IF (PRTNS1(I,K,1).EQ.PARTON) KDUMM=K
L.809         IF (PRTNS1(I,K,1).EQ.PARTON) GO TO 3010
L.810  3000 CONTINUE
L.811         WRITE (6,3015)
L.812         GO TO 1111
L.813  3015 FORMAT (T2,'  ERROR NCP SIM1  STM 3015  MAIN PGM')
L.814  3010 IF (PRTNS1(I,KDUMM,2).NE.0) GO TO 3030
L.815         PRTNS1(I,KDUMM,2)=PCKNO
L.816         GO TO 3070
L.817  3030 IF (PRTNS1(I,KDUMM,3).NE.0) GO TO 3040
L.818         PRTNS1(I,KDUMM,3)=PCKNO
L.819         GO TO 3070
L.820  3040 DO 3050 J=1,MNOBFS
L.821         IF (BFPOOL(I,J,1).EQ.0) JDUMM=J
L.822         IF (BFPOOL(I,J,1).EQ.0) GO TO 3060
L.823  3050 CONTINUE
L.824         WRITE (6,3055)
L.825  3055 FORMAT(T2,'  ERROR NCP SIM2')
L.826         GO TO 1111
L.827  3060 BFPOOL(I,JDUMM,1)=PCKNO
L.828         BFPOOL(I,JDUMM,2)=PARTON
L.829 C
```

BLOCK: MAIN EXECUTION

MODULE: INTERNODAL TRM

SUBMODULE: RETRM AND PARTITION TIMING

DO FOR EACH NCP

A) PERFORM RETRM TIMING

DO LOOP 3110: FOR EACH FIELD DO THE FOLLOWING:

IF A PACKET IS IN TRM THEN CHECK WHETHER
TIME-OUT INTERVAL ELAPSED,
IF ELAPSED SIGNAL 'TIME-OUT'

IF NO PACKET IN TRM THEN CHECK WHETHER
A TIME-OUT IS REQUIRED, IF NOT GO TO (B)

IF SO INITIALIZE CLOCKS

B) PERFORM PARTITION TIMING

DO LOOP 3140: FOR EACH PARTITION DO THE FOLLOWING:

IF A PARTITION NOT BLOCKED GO TO END

IF A PARTITION TIMED, CHECK WHETHER INTERVAL
ELAPSED, IF SO SIGNAL

OTHERWISE GO TO END

REQUEST FOR TIME-OUT: INITIALIZE CLOCKS

END

```
L.830  3070 IFBUFR(I)=0
L.831 C     UPDATE OF INTERVAL TIMERS
L.832       DO 3110 K=1,8
L.833       IF (FIELD3(I,K,1).NE.1) GOTO 3090
L.834       FIELD3(I,K,1)=0
L.835       FIELD3(I,K,2)=1
L.836       ID=K+(4*N)+NONCPS+(2*NONDS)
L.837       TIMERZ(ID)=TXMAX
L.838       CNZ=2
L.839       CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L.840  3090 IF (FIELD3(I,K,2).NE.1) GOTO 3110
L.841       IF (SIGNTM(K+(4*N)+NONCPS+(2*NONDS)).NE.3) GOTO 3110
L.842       FIELD3(I,K,2)=0
L.843       FIELD3(I,K,3)=1
L.844  3110 CONTINUE
L.845       DO 3140 K=1,8
L.846       IF (PRTNS2(I,K,5).NE.1) GOTO 3140
L.847       IF (PRTNS2(I,K,6).EQ.1) GOTO 3130
L.848       PRTNS2(I,K,6)=1
L.849       ID=K+8+(4*N)+NONCPS+(2*NONDS)
L.850       TIMERZ(ID)=PXMAX
L.851       CNZ=2
L.852       CALL PROGTM(TIMERZ,CLOCK,CNZ,I
L.853  3130 IF (SIGNTM(K+8+(4*N)+NONCPS+(2*NONDS)).NE.3) GOTO 3140
L.854       PRTNS2(I,K,5)=0
L.855       PRTNS2(I,K,6)=0
L.856  3140 CONTINUE
L.857 C     END OF DATABUS-NCP TRANSFER PHASE
L.858 C
```

BLOCK: MAIN EXECUTION

MODULE: INTERNODAL TRM

SUBMODULE: LINE TRANSMISSION: FIELD SETTING

DO FOR EACH NCP

A) LINE TESTING

IF CHANNEL BUSY THEN GO TO LBL 3320 IN NEXT SUBMODULE

B) PACKET RETRANSMISSION

NB. PACKETS THAT REQUIRE TO BE RETRANSMITTED
ARE GIVEN PRIORITY

DO LOOP (3150): IF ANY FIELDS CONTAIN PACKETS
FOR RETRM CHOOSE FIRST PACKET ENCOUNTERED, OTHERWISE
GO TO NEXT SECTION (NEW PACKET TRM).

TRANSFER FIELD CONTENTS TO TRANSMISSION
LOCATIONS: PACTR; PARTITION MUST BE UNBLOCKED

INITIATE TIME-OUT INTERVAL

GO TO LINE TRM SUBMODULE

C) NEW PACKET TRANSMISSION

DETERMINE WHETHER FIELD AVAILABLE

IF NO FIELD GO TO NEXT SECTION (ACK TRM).

SELECT PACKET WITH LOWEST PRIORITY FACTOR FOR TRM.
CHECK PARTITION UNBLOCKED. TRANSFER FIELD CONTENTS
TO TRANSMISSION LOCATIONS: PACTR;

SET TRANSMISSION TIMER

GO TO NEXT MODULE

NB. Synchronization of transmitter and receiver, transfer of packets, acknowledgement, etc., is done via flags, these are discussed in Chapter 5.

D) ACK TRANSMISSION

IF NO PACKET RETRM OR TRM AND LINE NOT BUSY, DETERMINE WHETHER ACK CONTROL PACKET TO BE TRM.

IN THIS CASE ONLY FLAGS TRM

IT IS NOT NECESSARY TO MAKE USE OF A FIELD FOR CONTROL PACKET TRM

EACH TIME A PACKET IS RECEIVED AN ACK FLAG IS SET

IF THERE ARE NO DATA PACKETS THAT REQUIRE TO BE SENT A CONTROL PACKET IS SENT AND THE FLAG RESET

THIS METHOD IS NOT INFALLIBLE SINCE THE CONTROL PACKET MAY INCUR ERRORS AND BE DISCARDED, BUT IT DOES PROVIDE A MEANS FOR OBTAINING A REASONABLE RESPONSE TIME FOR STORE-AND-FORWARD BUFFERING

```
L.859 C      TRANSMISSION PHASE
L.860 C
L.861 C      LINE NOT BUSY
L.862        IF (LINE(I).EQ.1) GO TO 3320
L.863 C      LINE FREE: PACKET SELECTION
L.864 C      RETRANSMISSION DUE TO TIMEOUT
L.865  3145 DO 3150 K=1,8
L.866        IF (FIELD3(I,K,3).EQ.1) LLF=K
L.867        IF (FIELD3(I,K,3).EQ.1) GO TO 3160
L.868  3150 CONTINUE
L.869        GO TO 3180
L.870  3160 PACTR(I,1,1)=LLF
L.871        PACTR(I,1,2)=FIELD1(I,LLF,3)
L.872        PACTR(I,1,3)=FIELD1(I,LLF,4)
L.873        PACTR(I,1,4)=FIELD1(I,LLF,1)
L.874        PACTR(I,1,5)=FIELD1(I,LLF,2)
L.875        PACTR(I,1,6)=0
L.876        PACTR(I,1,7)=0
L.877        IF (PACTR(I,1,4).EQ.0 .AND. PACTR(I,1,5).EQ.0) FIELD3(I,LLF,3)=0
L.878        IF (PACTR(I,1,4).EQ.0 .AND. PACTR(I,1,5).EQ.0) GOTO 3145
L.879        DO 3170 M=1,8
L.880        PACTR(I,2,M)=FIELD2(I,M,3)
L.881        PACTR(I,3,M)=FIELD2(I,M,1)
L.882        PACTR(I,4,M)=FIELD2(I,M,2)
L.883  3170 CONTINUE
L.884        FIELD3(I,LLF,1)=1
L.885        FIELD3(I,LLF,3)=0
L.886        GO TO 3270
L.887 C      NEW PACKET SELECTION (FCFS)
L.888 C      DETERMINE WHETHER FIELD AVAILABLE
L.889  3180 DO 3200 K=1,8
L.890        IF (FIELD1(I,K,1).EQ.0) LLH=K
L.891        IF (FIELD1(I,K,1).EQ.0) GO TO 3220
L.892  3200 CONTINUE
L.893        GO TO 3250
L.894  3220 KPRTY=2147483647
L.895        LPM=0
L.896        LQM=0
L.897        DO 3230 J=1,8
L.898        DO 3230 K=2,3
L.899        MPPCK=PRTNS1(I,J,K)
L.900        IF (MPPCK.EQ.0) GO TO 3230
L.901        IF (PACKET(MPPCK,6).GT.KPRTY .OR. DUPLCT(MPPCK,I).EQ.2 .OR. PRTNS
CONT: ,J,5).EQ.1) GO TO 3230
L.902        KPRTY=PACKET(MPPCK,6)
L.903        LQM=PRTNS1(I,J,K)
L.904        LPM=PRTNS1(I,J,1)
L.905  3230 CONTINUE
L.906        DO 3240 J=1,MNOBFS
L.907        MPPCK=BFPOOL(I,J,1)
L.908        MPARTN=BFPOOL(I,J,2)
L.909        IF (MPPCK.EQ.0) GO TO 3240
L.910        IF (PACKET(MPPCK,6).GT.KPRTY .OR. DUPLCT(MPPCK,I).EQ.2) GO TO 324
L.911        DO 3235 K=1,8
L.912        IF (PRTNS2(I,K,4).EQ.MPARTN .AND. PRTNS2(I,K,5).EQ.1) GO TO 3240
L.913  3235 CONTINUE
L.914        KPRTY=PACKET(MPPCK,6)
L.915        LQM=BFPOOL(I,J,1)
L.916        LPM=BFPOOL(I,J,2)
L.917  3240 CONTINUE
L.918        IF (KPRTY.EQ.2147483647) GO TO 3250
L.919        DUPLCT(LQM,I)=2
L.920 C      LQM=SELECTED PACKET NUMBER
L.921 C      LPM=SELECTED PARTITION NUMBER
```

```
L.922 C
L.923 C      ALLOCATION OF TRANSMISSION FIELDS
L.924        IF (FIELD1(I,LLH,3).EQ.0 .AND. FIELD1(I,LLH,4).EQ.0) GO TO 3242
L.925        IF (FIELD1(I,LLH,3).EQ.0 .AND. FIELD1(I,LLH,4).EQ.1) GO TO 3243
L.926        WRITE (6,3241)
L.927  3241 FORMAT (T2,'ERROR - TRANSMISSION FIELDS')
L.928  3242 FIELD1(I,LLH,3)=0
L.929        FIELD1(I,LLH,4)=1
L.930        FIELD1(I,LLH,5)=1
L.931        GO TO 3244
L.932  3243 FIELD1(I,LLH,3)=0
L.933        FIELD1(I,LLH,4)=0
L.934        FIELD1(I,LLH,5)=1
L.935 C
L.936 C      TRANSFER PACKET AND PARTITION NUMBERS TO FIELDS
L.937  3244 FIELD1(I,LLH,1)=LQM
L.938        FIELD1(I,LLH,2)=LPM
L.939        FIELD3(I,LLH,1)=1
L.940 C      TRANSMISSION
L.941        PACTR(I,1,1)=LLH
L.942        PACTR(I,1,2)=FIELD1(I,LLH,3)
L.943        PACTR(I,1,3)=FIELD1(I,LLH,4)
L.944        PACTR(I,1,4)=FIELD1(I,LLH,1)
L.945        PACTR(I,1,5)=FIELD1(I,LLH,2)
L.946        PACTR(I,1,6)=0
L.947        PACTR(I,1,7)=0
L.948        DO 3245 M=1,8
L.949        PACTR(I,2,M)=FIELD2(I,M,3)
L.950        PACTR(I,3,M)=FIELD2(I,M,1)
L.951        PACTR(I,4,M)=FIELD2(I,M,2)
L.952  3245 CONTINUE
L.953 C      SET TRANSMISSION TIMER
L.954        FIELD3(I,LLH,1)=1
L.955        GO TO 3270
L.956 C
L.957 C      ACK TRANSMISSION - NO DATA PACKET SENT
L.958  3250 IF (ERRORG(I,3).NE.1) GO TO 3999
L.959        DO 3255 M=1,7
L.960        PACTR(I,1,M)=0
L.961  3255 CONTINUE
L.962        DO 3260 M=1,8
L.963        PACTR(I,2,M)=FIELD2(I,M,3)
L.964        PACTR(I,3,M)=FIELD2(I,M,1)
L.965        PACTR(I,4,M)=FIELD2(I,M,2)
L.966  3260 CONTINUE
L.967 C
```

BLOCK: MAIN EXECUTION

MODULE: INTERNODAL TRM

SUBMODULE: LINE TRANSMISSION

DO FOR EACH NCP

LBL 3270 SET LINE TO BUSY

CALCULATE TIME REQUIRED TO TRANSMIT PACKET
OVER CHANNEL

INCORPORATE ESTIMATED NODAL PROCESSING TIME

DETERMINE IF PACKET INCURS ERROR:
ERROR DISTRIBUTION IS ASSUMED TO BE POISSON AND
PERFORMED ON A LINE ERROR BIT RATE BASIS

NB. THE ACTUAL ERROR DISTRIBUTION ON THE
PCM CHANNEL IS NOT CONSIDERED IMPORTANT,
EMPHASIS IS ON WHETHER PROTOCOL CAN CAUSE
A RETRANSMISSION, AND DO SO WITHOUT
TRANSMITTING DUPLICATES OR PACKETS BEING LOST.
TIME THE INTERVAL BY INTERVAL GENERATION
PERFORMED ON CLOCK.

TRANSFER CONTENTS OF TRANSMISSION ARRAY
TO CONTENTS OF RECEIVER ARRAY.

PACTR → PACRC

```
L.968 C      LINE TRANSMISSION
L.969  3270 LINE(I)=1
L.970       ERRORG(I,3)=0
L.971       IF (PACTR(I,1,4).EQ.0) LBITS=BITLNG
L.972       IF (PACTR(I,1,4).EQ.0) GO TO 3280
L.973       PKNN=PACTR(I,1,4)
L.974       LBITS=PACKET(PKNN,2)+BITLNG
L.975  3280 CONTINUE
L.976       LLBPS=15000
L.977       CALL TIMER (LBITS,LLBPS,RIMR6)
L.978       ID=I+(3*N)
L.979 C      NODAL PROCESSING TIME PER PACKET: NODPRC
L.980       TIMERZ(ID)=RIMR6+NODPRC
L.981       CNZ=2
L.982       CALL PROGTM (TIMERZ,CLOCK,CNZ,ID)
L.983 C      ERROR GENERATION
L.984  3300 ERRORG(I,2)=ERRORG(I,2)+LBITS
L.985       IF (ERRORG(I,2).LT.ERRORG(I,1)) GO TO 3320
L.986       NRY=1
L.987       PZZCX=100000
L.988       CALL GGUBS(DSEED,NRY,R)
L.989       ERRORG(I,1)=(PZZCX)*ALOG(1-R(1))
L.990       PACTR(I,1,6)=1
L.991       ERRORG(I,2)=0
L.992 C      PACKET IN TRANSMISSION
L.993  3320 IF (SIGNTM(I+(3*N)).NE.3) GOTO 3999
L.994       J=NCPCNT(I)
L.995       DO 3330 M=1,7
L.996       PACRC(J,1,M)=PACTR(I,1,M)
L.997  3330 CONTINUE
L.998       DO 3335 M=1,8
L.999       PACRC(J,2,M)=PACTR(I,2,M)
L1000       PACRC(J,3,M)=PACTR(I,3,M)
L1001       PACRC(J,4,M)=PACTR(I,4,M)
L1002  3335 CONTINUE
L1003       LINE(I)=0
L1004       PACRC(J,1,7)=1
L1005 C      END OF TRANSMISSION PHASE
L1006 C
```

BLOCK: MAIN EXECUTION

MODULE: INTERNODAL TRM

SUBMODULE: RECEIVING PHASE

DO FOR EACH NCP

RECEIVE THE PACKET

IF PACKET HAS BIT ERRORS DELETE IT

THIS SUBMODULE OPERATES ON BOTH DATA AND CONTROL PACKETS

DO LOOP (3460) FOR ALL FIELDS:

BY COMPARING THE ARRIVED PACKET'S ACK FLAGS (PACRC)
WITH THE NCP's TRANSMISSION FLAGS (FIELD 1), THE NCP
MAY DETERMINE THE STATUS OF ITS OWN PACKETS THAT IT
HAS SENT TO THE OTHER NCP, i.e. THE NCP WHICH
TRANSMITTED THE ABOVE ARRIVED PACKET.

THE PACKET STATUS OF EACH FIELD MAY BE

NO-OPERATION

RELEASE OF BUFFER (SUCCESSFUL TRM)

RETRANSMISSION (DUE TO BLOCKED PARTITIONS, i.e.
PARTITION TO WHICH SENT PACKET BELONGED, AND
COMMON BUFFERS ALL OCCUPIED)

END

THE ABOVE OPERATIONS ARE CONDUCTED IN THE NEXT SUBMODULE

```
L1007 C      RECEIVING PHASE
L1008 C
L1009 C      PACKETS WITH BIT ERRORS ARE DELETED
L1010        IF (PACRC(J,1,6).EQ.1) GO TO 3999
L1011 C      PROCESSING OF ACK INFORMATION
L1012 C      RELEASE OF BUFFERS
L1013        DO 3460 K=1,8
L1014 C      NO-OP
L1015        IF (FIELD1(J,K,3).EQ.0 .AND. FIELD1(J,K,4).EQ.0 .AND. PACRC(J,2,K).
CONT: Q.0 .AND. PACRC(J,3,K).EQ.1 .AND. PACRC(J,4,K).EQ.1) GO TO 3460
L1016        IF (FIELD1(J,K,3).EQ.0 .AND. FIELD1(J,K,4).EQ.1 .AND. PACRC(J,2,K).
CONT: Q.0 .AND. PACRC(J,3,K).EQ.1 .AND. PACRC(J,4,K).EQ.0) GO TO 3460
L1017 C
L1018 C      NO-OP
L1019        IF (FIELD1(J,K,3).EQ.0 .AND. FIELD1(J,K,4).EQ.0 .AND. PACRC(J,2,K).
CONT: Q.1 .AND. PACRC(J,3,K).EQ.1 .AND. PACRC(J,4,K).EQ.1) GO TO 3460
L1020        IF (FIELD1(J,K,3).EQ.0 .AND. FIELD1(J,K,4).EQ.1 .AND. PACRC(J,2,K).
CONT: Q.1 .AND. PACRC(J,3,K).EQ.1 .AND. PACRC(J,4,K).EQ.0) GO TO 3460
L1021 C
L1022 C      RELEASE OF BUFFERS
L1023        IF (FIELD1(J,K,3).EQ.0 .AND. FIELD1(J,K,4).EQ.0 .AND. PACRC(J,2,K).
CONT: Q.0 .AND. PACRC(J,3,K).EQ.1 .AND. PACRC(J,4,K).EQ.0) GO TO 3350
L1024        IF (FIELD1(J,K,3).EQ.0 .AND. FIELD1(J,K,4).EQ.1 .AND. PACRC(J,2,K).
CONT: Q.0 .AND. PACRC(J,3,K).EQ.1 .AND. PACRC(J,4,K).EQ.1) GO TO 3350
L1025 C
L1026 C      RETRANSMISSION
L1027        IF (FIELD1(J,K,3).EQ.0 .AND. FIELD1(J,K,4).EQ.0 .AND. PACRC(J,2,K).
CONT: Q.1 .AND. PACRC(J,3,K).EQ.1 .AND. PACRC(J,4,K).EQ.0) GO TO 3430
L1028        IF (FIELD1(J,K,3).EQ.0 .AND. FIELD1(J,K,4).EQ.1 .AND. PACRC(J,2,K).
CONT: Q.1 .AND. PACRC(J,3,K).EQ.1 .AND. PACRC(J,4,K).EQ.1) GO TO 3430
L1029 C
L1030        WRITE (6,3345)
L1031  3345 FORMAT(T2,'ERROR - FRAME TRANSMISSION')
```

BLOCK: MAIN EXECUTION

MODULE: INTERNODAL TRM

SUBMODULE: RELEASE OF BUFFERS

DO FOR EACH NCP

THIS SUBMODULE IS CONCERNED WITH THE RELEASE OF BUFFERS IN ALL FIELDS DUE TO ACKS RECEIVED IN THE FLAGS OF THE ARRIVED PACKETS

DO FOR EACH FIELD

A) BUFFER RELEASE (LBL 3350)

RESET ALL FIELD FLAGS, INITIALIZING IT FOR THE NEXT PACKET TRANSMISSION

DELETE THE INTERVAL IDENTIFIER STORED IN CLOCK - RETRANSMISSION INTERVAL

SEARCH FOR PACKET IN PARTITION AND COMMON BUFFERS AND DELETE IT.

GO TO END (LBL (3460)

B) RETRANSMISSION DUE TO BLOCKED PARTITION

RESET ALL FIELD FLAGS, INITIALIZING IT FOR THE NEXT PACKET TRANSMISSION

DELETE THE INTERVAL IDENTIFIER STORED IN CLOCK - RETRM INTERVAL

INITIALIZE PARTITION TIME-OUT

LBL 3460 END

```
L1032 C      RELEASE OF BUFFERS
L1033  3350 IF (FIELD1(J,K,5).NE.1) GOTO 3460
L1034       PCCNO=FIELD1(J,K,1)
L1035       PAANO=FIELD1(J,K,2)
L1036       FIELD1(J,K,1)=0
L1037       FIELD1(J,K,2)=0
L1038       FIELD1(J,K,5)=0
L1039       FIELD3(J,K,1)=0
L1040       FIELD3(J,K,2)=0
L1041       CNZ=3
L1042       ID=K+(4*N)+NONCPS+(2*NONDS)
L1043       CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L1044       SIGNTM(K+(4*N)+NONCPS+(2*NONDS))=1
L1045 C     SEARCH FOR PACKET AND DELETE
L1046 C     TRMBUF/QBUF
L1047       DO 3360 KD=1,8
L1048       DO 3360 LD=2,3
L1049       IF (PRTNS1(J,KD,LD).NE.PCCNO) GO TO 3360
L1050       PRTNS1(J,KD,LD)=0
L1051       DUPLCT(PCCNO,J)=0
L1052       GO TO 3460
L1053  3360 CONTINUE
L1054       DO 3370 JD=1,MNOBFS
L1055       IF (BFPOOL(J,JD,1).NE.PCCNO) GO TO 3370
L1056       BFPOOL(J,JD,1)=0
L1057       DUPLCT(PCCNO,J)=0
L1058       GO TO 3460
L1059  3370 CONTINUE
L1060       WRITE (6,3380)
L1061  3380 FORMAT (T2,'ERROR - PACKET (CHANNEL) RELEASE')
L1062 C     RETRANSMISSION DUE TO BLOCKED PARTITION: TIME-OUT
L1063  3430 IF (FIELD1(J,K,5).NE.1) GOTO 3460
L1064       PAANO=FIELD1(J,K,2)
L1065       NPCS=FIELD1(J,K,1)
L1066       FIELD1(J,K,1)=0
L1067       FIELD1(J,K,2)=0
L1068       FIELD1(J,K,5)=0
L1069       DUPLCT(NPCS,J)=1
L1070       FIELD3(J,K,1)=0
L1071       FIELD3(J,K,2)=0
L1072       CNZ=3
L1073       ID=K+(4*N)+NONCPS+(2*NONDS)
L1074       CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L1075       SIGNTM(K+(4*N)+NONCPS+(2*NONDS))=1
L1076       DO 3440 M=1,8
L1077       IF (PRTNS2(J,M,4).EQ.PAANO) LLC=M
L1078       IF (PRTNS2(J,M,4).EQ.PAANO) GO TO 3450
L1079  3440 CONTINUE
L1080       WRITE (6,3445)
L1081  3445 FORMAT (T2,' ERROR - PARTITION MISSING')
L1082  3450 PRTNS2(J,LLC,5)=1
L1083       PRTNS2(J,LLC,6)=0
L1084  3460 CONTINUE
L1085 C
```

BLOCK: MAIN EXECUTION

MODULE: INTERNODAL TRM

SUBMODULE: ACK PROCESSING AND STORAGE

THIS MODULE DETERMINES WHETHER THE PACKET IS TO BE RECEIVED AND STORED PROPER, i.e. WHETHER IT IS TO BE TRM ON TO NEXT NODE, OR WHETHER IT IS A DUPLICATE AND IS TO BE DELETED

DETERMINE WHETHER PACKET IS TO BE RECEIVED OR WHETHER DELETED - DUPLICATE

DETERMINE NEW PARTITION OF PACKET

ATTEMPT TO STORE PACKET IN PARTITION OR COMMON BUFFERS

IF STORED INFORM NODAL SUPERVISOR OF PACKET PARAMETERS AND REQUEST FOR SERVICE

IF NOT STORED SET APPROPRIATE PARTITION FLAG INFORMING OF BLOCKED PARTITION

SET TRANSMITTER FLAGS ACCORDING TO WHETHER PACKET WAS SUCCESSFULLY RECEIVED OR NOT

RESET PACRC PARAMETERS

END

```
C       ACK ONLY
        IF (PACRC(J,1,1).EQ.0 .AND. PACRC(J,1,4).EQ.0) GO TO 3999
C       SYNCHRONIZE TRM AND REC FIELDS
C       DEPOSIT PACKET IN DESTINATION BUFFERS
        FRMFLD=PACRC(J,1,1)
C       ACK: 1 1  TRANSMITTED PREVIOUSLY - RECEIVE PACKET
        IF (FIELD2(J,FRMFLD,1).EQ.1 .AND. FIELD2(J,FRMFLD,2).EQ.1 .AND. F
CONT: C(J,1,2).EQ.0 .AND. PACRC(J,1,3).EQ.0) GO TO 3465
C       ACK: 0 1  TRANSMITTED PREVIOUSLY - RECEIVE PACKET
        IF (FIELD2(J,FRMFLD,1).EQ.1 .AND. FIELD2(J,FRMFLD,2).EQ.0 .AND. F
CONT: C(J,1,2).EQ.0 .AND. PACRC(J,1,3).EQ.1) GO TO 3465
C       ACK: 1 1  FIELD:10 - DUPLICATE
        IF (FIE    J,FRMFLD,1).EQ.1 .AND. FIELD2(J,FRMFLD,2).EQ.. .AND. F
CONT: C(J,1,2).EQ.0 .AND. PACRC(J,1,3).EQ.1) ERRORG(J,3)=1
        IF (FIELD2(J,FRMFLD,1).EQ.1 .AND. FIELD2(J,FRMFLD,2).EQ.1 .AND. F
CONT: C(J,1,2).EQ.0 .AND. PACRC(J,1,3).EQ.1) GO TO 3550
C       ACK: 0 1  FIELD:00 - DUPLICATE
        IF (FIELD2(J,FRMFLD,1).EQ.1 .AND. FIELD2(J,FRMFLD,2).EQ.0 .AND. F
CONT: C(J,1,2).EQ.0 .AND. PACRC(J,1,3).EQ.0) ERRORG(J,3)=1
        IF (FIELD2(J,FRMFLD,1).EQ.1 .AND. FIELD2(J,FRMFLD,2).EQ.0 .AND. F
CONT: C(J,1,2).EQ.0 .AND. PACRC(J,1,3).EQ.0) GO TO 3570
        WRITE (6,3464)
 3464   FORMAT(T2,' SYNCHRONIZATION ERROR')
C       STORAGE OF PACKET
 3465   DO 3470 K=1,8
        IF (PRTNS2(J,K,1).EQ.PACRC(J,1,5)) LDD=K
        IF (PRTNS2(J,K,1).EQ.PACRC(J,1,5)) GO TO 3480
 3470   CONTINUE
        WRITE (6,3475)
 3475   FORMAT (T2,'ERROR - PARTITIONS - RECEIVING')
        GOTO 1111
C       TRMBUF
 3480   IF (PRTNS2(J,LDD,2).NE.0) GO TO 3490
        PRTNS2(J,LDD,2)=PACRC(J,1,4)
        GO TO 3530
C       QBUF
 3490   IF (PRTNS2(J,LDD,3).NE.0) GO TO 3500
        PRTNS2(J,LDD,3)=PACRC(J,1,4)
        GO TO 3530
C       BUFPOLR
 3500   CONTINUE
        DO 3510 MKG=1,MNOBFS
        IF (BFPOLR(J,MKG,1).EQ.0) LLFG=MKG
        IF (BFPOLR(J,MKG,1).EQ.0) GO TO 3520
 3510   CONTINUE
C       NO BUFFERS FREE
        KSIGN=1
        GO TO 3540
 3520   BFPOLR(J,LLFG,1)=PACRC(J,1,4)
        BFPOLR(J,LLFG,2)=PACRC(J,1,5)
 3530   KSIGN=0
```

```
C      WRITE INFORMATION INTO NCPST ARRAY
       DO 3531 MKG=1,NONDS
       DO 3531 I=1,NMAXIN
       IF (MAPNCP(MKG,I).EQ.J) NV=MKG
       IF (MAPNCP(MKG,I).EQ.J) GO TO 3533
 3531  CONTINUE
       WRITE (6,3532)
 3532  FORMAT (T2,'ERROR - NODAL NUMBER NOT FOUND STM 3532 ')
 3533  DO 3534 MKG=1,NOPCKS
       IF (NODEST(NV,MKG,1).NE.0) GO TO 3534
       NODEST(NV,MKG,1)=PACRC(J,1,4)
       NODEST(NV,MKG,2)=J
       NODEST(NV,MKG,3)=2
       GO TO 3540
 3534  CONTINUE
       WRITE (6,3535)
 3535  FORMAT (T2,' ERROR - NODEST ARRAY OVERFLOW')
 3540  ERRORG(J,3)=1
C
C      FRAME FIELD ACKNOWLEDGEMENT
       IF (KSIGN.EQ.0 .AND. FIELD2(J,FRMFLD,1).EQ.1 .AND. FIELD2(J,FRMF
CONT: ).EQ.0) GO TO 3550
       IF (KSIGN.EQ.1 .AND. FIELD2(J,FRMFLD,1).EQ.1 .AND. FIELD2(J,FRMF
CONT: ).EQ.0) GO TO 3560
       IF (KSIGN.EQ.0 .AND. FIELD2(J,FRMFLD,1).EQ.1 .AND. FIELD2(J,FRMF
CONT: ).EQ.1) GO TO 3570
       IF (KSIGN.EQ.1 .AND. FIELD2(J,FRMFLD,1).EQ.1 .AND. FIELD2(J,FRMF
CONT: ).EQ.1) GO TO 3580

       WRITE (6,3545)
 3545  FORMAT (T2,'ERROR - FRAME ACK')
 3550  FIELD2(J,FRMFLD,1)=1
       FIELD2(J,FRMFLD,2)=1
       FIELD2(J,FRMFLD,3)=0
       GO TO 3590
 3560  FIELD2(J,FRMFLD,1)=1
       FIELD2(J,FRMFLD,2)=1
       FIELD2(J,FRMFLD,3)=1
       GO TO 3590
 3570  FIELD2(J,FRMFLD,1)=1
       FIELD2(J,FRMFLD,2)=0
       FIELD2(J,FRMFLD,3)=0
       GO TO 3590
 3580  FIELD2(J,FRMFLD,1)=1
       FIELD2(J,FRMFLD,2)=0
       FIELD2(J,FRMFLD,3)=1
 3590  CONTINUE
       KSIGN=0
C      RESET PACRC TO ZERO
       DO 3595 M=1,7
       PACRC(J,1,M)=0
 3595  CONTINUE
C
 3999  CONTINUE
C
```

```
C      WRITE INFORMATION INTO NCPST ARRAY
       DO 3531 MKG=1,NONDS
       DO 3531 K=1,NMAXIN
       IF (MAPNLP(MKG,K).EQ.J) NV=MKG
       IF (MAPNCP(MKG,K).EQ.J) GO TO 3533
 3531  CONTINUE
       WRITE (6,3532)
 3532  FORMAT (T2,'ERROR - NODAL NUMBER NOT FOUND STM 3532 ')
 3533  DO 3534 MKG=1,NOPCKS
       IF (NODEST(NV,MKG,1).NE.0) GO TO 3534
       NODEST(NV,MKG,1)=PACRC(J,1,4)
       NODEST(NV,MKG,2)=J
       NODEST(NV,MKG,3)=2
       GO TO 3540
 3534  CONTINUE
       WRITE (6,3535)
 3535  FORMAT (T2,' ERROR - NODEST ARRAY OVERFLOW')
 3540  ERRORG(J,3)=1
C
C      FRAME FIELD ACKNOWLEDGEMENT
       IF (KSIGN.EQ.0 .AND. FIELD2(J,FRMFLD,1).EQ.1 .AND. FIELD2(J,FRMF
CONT: ).EQ.0) GO TO 3550
       IF (KSIGN.EQ.1 .AND. FIELD2(J,FRMFLD,1).EQ.1 .AND. FIELD2(J,FRMF
CONT: ).EQ.0) GO TO 3560
       IF (KSIGN.EQ.0 .AND. FIELD2(J,FRMFLD,1).EQ.1 .AND. FIELD2(J,FRMF
CONT: ).EQ.1) GO TO 3570
       IF (KSIGN.EQ.1 .AND. FIELD2(J,FRMFLD,1).EQ.1 .AND. FIELD2(J,FRMF
CONT: ).EQ.1) GO TO 3580

       WRITE (6,3545)
 3545  FORMAT (T2,'ERROR - FRAME ACK')
 3550  FIELD2(J,FRMFLD,1)=1
       FIELD2(J,FRMFLD,2)=1
       FIELD2(J,FRMFLD,3)=0
       GO TO 3590
 3560  FIELD2(J,FRMFLD,1)=1
       FIELD2(J,FRMFLD,2)=1
       FIELD2(J,FRMFLD,3)=1
       GO TO 3590
 3570  FIELD2(J,FRMFLD,1)=1
       FIELD2(J,FRMFLD,2)=0
       FIELD2(J,FRMFLD,3)=0
       GO TO 3590
 3580  FIELD2(J,FRMFLD,1)=1
       FIELD2(J,FRMFLD,2)=0
       FIELD2(J,FRMFLD,3)=1
 3590  CONTINUE
       KSIGN=0
C      RESET PACRC TO ZERO
       DO 3595 M=1,7
       PACRC(J,1,M)=0
 3595  CONTINUE
C
 3999  CONTINUE
C
```

BLOCK: MAIN EXECUTION

MODULE: DATA BUS PACKET TRANSFERS

THIS MODULE SIMULATES THE TRANSFER OF PACKETS VIA THE DATA BUS BETWEEN ICP's AND NCP's UNDER THE COMMAND DIRECTIVES OF THE SWITCH PROCESSOR

DO FOR EACH NODE

DATABS (I): PGM CONTROL I: NODAL NUMBER

PROGRAM CONTROL DATABS (I)

IF DATABS (I) = 1:

WAIT FOR SYNCHRONIZATION SIGNAL BUSSEM = 1

TRANSFER THE COMMANDS FROM THE SWITCH TO THE PROCESSORS PT2ICP → PT1ICP

PT2NCP → PT1NCP

(NB. TRANSFER TIME INCORPORATED INTO ESTIMATED SWITCH ALGORITHM EXECUTION TIME)

SET CYCLE COUNTER TO 1 : NONCC

SEND SYNCHRONIZATION SIGNAL SEMPH = 3

RESET SYNCHRONIZATION SIGNAL BUSSEM = 3

(NB. THE TWO ABOVE SIGNALS ARE SIMULATION PROGRAM EXECUTION VARIABLES, AND HAVE NO RELATION TO THE SWITCH PROCESSOR AND ICP/NCP SYNCHRONIZATION. THE FOLLOWING DO.)

SIGNAL (BY SWITCH) FOR STARTING PROCESSOR TO USE BUS:

SEMPRC (I,4) PROCESSOR

SEMPRC (I,5) ADDRESS

LBL 6015 IF TRANSMITTING PROCESSOR IS ICP:

IF PACKET IS A DATA PACKET, THEN RELEASE BUFFERS IN ICP (BY REQUIRED NUMBER OF BLOCKS EQUIVALENT TO ONE PACKET), PROVIDED MESSAGE TO WHICH PACKET BELONGS IS EOM..

IF TRANSMITTING PROCESSOR IS NCP:

RELEASE APPROPRIATE NUMBER OF BLOCKS IN NCP.

LBL 6245: ICP OR NCP:

GENERATE TIME REQUIRED TO TRANSMIT PACKET ACROSS BUS

PERFORM INTERVAL GENERATION ON CLOCK

SET DATABS (I) = 2

IF DATABS (I) = 2:

WAIT UNTIL INTERVAL HAS ELAPSED

DO LOOP (6105):

IF PROCESSOR TRANSMITTING IS ICP TRANSFER COMMANDS TO SIMULATION VARIABLE VARTM

$$PT1^{ICP} \rightarrow VARTM$$

IF PROCESSOR TRANSMITTING IS NCP TRANSFER COMMANDS TO SIMULATION VARIABLE VARTM

$$PT1^{NCP} \rightarrow VARTM$$

USING VARTM:

IF PACKET BELONGS TO VIRTUAL CIRCUIT AND HAS REACHED DEST NODE THEN DELETE

IF PACKET BELONGS TO LOGICAL LINK AND HAS REACHED DEST NODE THEN STORE IN ICP BUFFER REASSM

IF PACKET AT INTERMEDIATE NODE THEN STORE IN NCP BUFFER IFBUFR

IF END OF PERIOD REACHED, i.e. ALL PROCESSORS IN A PERIOD HAVE FINISHED TRM THEN SET DATABS (I) = 1 AND GO TO END

IF END OF CYCLE REACHED THEN INCREMENT CYCLE COUNTER

TRANSFER ADDRESS OF NEXT PROCESSOR TO TRANSMIT

VARTM → SEMPRC

GO TO LBL 6015 (REPEAT ABOVE STEPS FOR EACH TRM PROCESSOR UNTIL END-OF-PERIOD)

END

```
C      DATA BUS PACKET TRANSFERS
       DO 9750 I=1,NONDS
       NDATB=DATABS(I)
       GO TO (6000,6250),NDATB
 6000  IF (BUSSEM(I).NE.1) GO TO 6999
       DO 6008 M=1,NMAXIC
       NZW=MAPICP(I,M)
       IF (MAPICP(I,M).EQ.0) GO TO 6008
       DO 6005 K=1,CMAX
       DO 6005 L=1,8
       PT1ICP(NZW,K,L)=PT2ICP(NZW,K,L)
 6005  CONTINUE
 6008  CONTINUE
       DO 6012 M=1,NMAXIN
       NZQ=MAPNCP(I,M)
       IF (MAPNCP(I,M).EQ.0) GO TO 6012
       DO 6010 K=1,CMAX
       DO 6010 L=1,8
       PT1NCP(NZQ,K,L)=PT2NCP(NZQ,K,L)
 6010  CONTINUE
 6012  CONTINUE
       NONCC(I)=1
       SEMPH(I)=3
       BUSSEM(I)=3
       SEMPRC(I,4)=SEMPRC(I,1)
       SEMPRC(I,5)=SEMPRC(I,2)
 6015  IF (SEMPRC(I,5).EQ.2) GO TO 6025
       PCCKNO=PT1ICP(SEMPRC(I,4),NONCC(I),3)
       IF (IOP(PACKET(PCCKNO,1),19).EQ.1) GO TO 6245
       IF (PACKET(PCCKNO,5).NE.1 .AND. PACKET(PCCKNO,5).NE.7) GO TO 6245
       IF (PACKET(PCCKNO,3).EQ.1) GOTO 6245
       NRB=0
       LNM=PACKET(PCCKNO,2)
 6020  LMLE=BUFBLK-LNM
       NRB=NRB+1
       LNM=LNM-BUFBLK
       IF (LMLE.LT.0) GO TO 6020
       RST=1
       LINKNR=PACKET(PCCKNO,1)
       ICPNR=IOP(PACKET(PCCKNO,1),3)
       TNR=1
       CALL ACCESS(RST,NRB,LINKNR,ICPNR,TNR,ACC,SDM,NCR,NSOU,NSING,NMUL)
       GO TO 6245
 6025  PCCKNO=PT1NCP(SEMPRC(I,4),NONCC(I),3)
       DO 6030 M=1,8
       DO 6030 LR=2,3
       IF (PRTNS2(SEMPRC(I,4),M,LR).NE.PCCKNO) GO TO 6030
       PRTNS2(SEMPRC(I,4),M,LR)=0
       GO TO 6245
 6030  CONTINUE
       DO 6035 M=1,MNOBFS
       IF (BFPOLR(SEMPRC(I,4),M,1).NE.PCCKNO) GO TO 6035
       BFPOLR(SEMPRC(I,4),M,1)=0
       GO TO 6245
 6035  CONTINUE
```

```
L1237   6245 LLGXZ=PACKET(PCCKNO,2)
L1238         CALL TIMER(LLGX2,MUXRT,RIMR7)
L1239         ID=I+(3*N)+NONCPS
L1240         TIMERZ(ID)=RIMR7+NPZ
L1241         CNZ=2
L1242         CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L1243         DATABS(I)=2
L1244   6250 IF (SIGNTM(I+(3*N)+NONCPS).NE.3) GOTO 6999
L1245         DO 6105 J=1,7
L1246         IF (SEMPRC(I,5).EQ.1) VARTM(J)=PT1ICP(SEMPRC(I,4),NONCC(I),J)
L1247         IF (SEMPRC(I,5).EQ.2) VARTM(J)=PT1NCP(SEMPRC(I,4),NONCC(I),J)
L1248   6105 CONTINUE
L1249         IF (VARTM(5).EQ.1 .AND. PACKET(VARTM(3),3).EQ.1) GOTO 6255
L1250         IF (VARTM(5).EQ.1) REASSM(PACKET(VARTM(3),1),1)=VARTM(3)
L1251         IF (VARTM(5).EQ.2) IFBUFR(VARTM(4))=VARTM(3)
L1252         GOTO 6260
L1253   6255 IOP(PACKET(VARTM(3),1),10)=IOP(PACKET(VARTM(3),1),10)-1
L1254         PACKET(VARTM(3),1)=0
L1255   6260 IF (VARTM(6).EQ.SEMPRC(I,3)) GOTO 6200
L1256         IF (SEMPRC(I,5).EQ.1 .AND. PT1ICP(SEMPRC(I,4),NONCC(I),8).EQ.1) NON
CONT: C(I)=NONCC(I)+1
L1257         IF (SEMPRC(I,5).EQ.2 .AND. PT1NCP(SEMPRC(I,4),NONCC(I),8).EQ.1) NON
CONT: C(I)=NONCC(I)+1
L1258         SEMPRC(I,4)=VARTM(6)
L1259         SEMPRC(I,5)=VARTM(7)
L1260         GO TO 6015
L1261   6200 DATABS(I)=1
L1262   6999 CONTINUE
```

BLOCK: MAIN EXECUTION

MODULE: SWITCHING ALGORITHM

DO FOR EACH NODE

SWCONT (I): PGM CONTROL I: NODAL NUMBER

PROGRAM CONTROL SWCONT (I)

(A) SERVICE REQUESTS AND SORTING

IF SWCONT (I) = 1:

WAIT FOR SYNCHRONIZATION SIGNAL SEMPH = 3

SET SWCONT (I) = 2

RESET SYNCHRONIZATION SIGNAL SEMPH = 2

DETERMINE TOTAL NUMBER OF FREE BUFFER BLOCKS IN EACH NCP AND STORE IN STO (TRANSMITTER SIDE OF NCP ONLY)

IF SWCONT (I) = 2:

STORE PACKET TRANSFER REQUESTS IN QLIST.

AT SAME TIME DETERMINE PARTITION AND DESTINATION OF PACKET, AND SELECT APPROPRIATE ICP OR NCP TO TRANSFER PACKET TO - STORE IN QLIST

IF MORE THAN ONE CHANNEL TO A NEXT NODE - SELECT NCP WITH MOST FREE BUFFERS, i.e. SMALLEST QUEUE

(B) WEIGHTING FACTOR ALLOCATION

A PACKET IS ALLOCATED A WEIGHTING FACTOR ACCORDING TO THE CLASS IT BELONGS TO:

ICP-TO-ICP : NON NETWORK TRAFFIC

ICP-TO-NCP : TRAFFIC ENTERING NETWORK

NCP-TO-NCP : TRANSIT TRAFFIC

NCP-TO-ICP : TRAFFIC LEAVING NETWORK

QUEUE PACKET IDENTIFIER (POINTER FROM QLIST) IN Q ACCORDING TO PRIORITY
(INITIAL PRIORITY SET EQUAL TO WEIGHTING FACTOR)

(C) FORMING SWITCH MATRIX

DETERMINE THE SWITCH MATRIX FOR DATA GIVEN IN QLIST

GIVING PRIORITY TO PACKETS FIRST IN Q

DETERMINE POINTER ALLOCATIONS FOR COMMANDS

INCREMENT PRIORITIES

GENERATE SWITCH ALG EXECUTION INTERVAL SET SWCONT (I) = 3

IF SWCONT (I) = 3:

IF INTERVAL NOT YET ELAPSED WAIT

SET SWCONT (I) = 1

SET SYNCHRONIZATION SIGNAL SEMPH = 1

SET SYNCHRONIZATION SIGNAL BUSSEM = 1

```
L1263 C
L1264 C      SWITCHING ALGORITHM
L1265        NSWC=SWCONT(I)
L1266        GOTO (9050,9080,9720), NSWC
L1267   9050 IF (SEMPH(I).NE.3) GOTO 9750
L1268        SWCONT(I)=2
L1269        SEMPH(I)=2
L1270        DO 9070 KS=1,NMAXIN
L1271        NZA=MAPNCP(I,KS)
L1272        IF (NZA.EQ.0) GOTO 9070
L1273        DO 9060 K=1,8
L1274        IF (PRTNS1(NZA,K,1).NE.0 .AND. PRTNS1(NZA,K,2).EQ.0) STO(NZA,1)=STO
CONT: NZA,1)+1
L1275        IF (PRTNS1(NZA,K,1).NE.0 .AND. PRTNS1(NZA,K,3).EQ.0) STO(NZA,1)=STO
CONT: NZA,1)+1
L1276        PARTNP(N7A,K,2)=PRTNS2(NZA,K,5)
L1277   9060 CONTINUE
L1278        DO 9065 K=1,MNOBFS
L1279        IF (BFPOOL(NZA,K,1).EQ.0) STO(NZA,1)=STO(NZA,1)+1
L1280   9065 CONTINUE
L1281        STO(NZA,2)=STO(NZA,1)
L1282   9070 CONTINUE
L1283   9080 DO 9200 J=1,NOPCKS
L1284        IF (NODEST(I,J,1).EQ.0) GOTO 9200
L1285        DO 9100 M=1,QUS
L1286        IF (QLIST(I,M,5).EQ.0) LMB=M
L1287        IF (QLIST(I,M,5).EQ.0) GOTO 9120
L1288   9100 CONTINUE
L1289        WRITE (6,9110)
L1290        GOTO 1111
L1291   9110 FORMAT (T2,'ERROR - QLIST ARRAY OVERFLOW')
L1292   9120 IDNODE=IOP(PACKET(NODEST(I,J,1),1),4)
L1293        IF (PACKET(NODEST(I,J,1),5).NE.1 .AND. PACKET(NODEST(I,J,1),5).NE.7
CONT:   IDNODE=IOP(PACKET(NODEST(I,J,1),1),2)
L1294        QLIST(I,LMB,1)=NODEST(I,J,2)
L1295        QLIST(I,LMB,2)=NODEST(I,J,3)
L1296        QLIST(I,LMB,5)=NODEST(I,J,1)
L1297        IF (I.NE.IDNODE) GOTO 9140
L1298        QLIST(I,LMB,3)=IOP(PACKET(NODEST(I,J,1),1),5)
L1299        IF (PACKET(NODEST(I,J,1),5).NE.1 .AND. PACKET(NODEST(I,J,1),5).NE.7
CONT:   QLIST(I,LMB,3)=IOP(PACKET(NODEST(I,J,1),1),3)
L1300        QLIST(I,LMB,4)=1
L1301        QLIST(I,LMB,6)=0
L1302        GO TO 9160
L1303   9140 ICNT=0
L1304        NOKAN=MAXCH+1
L1305        DO 9150 M=2,NOKAN
L1306        IF (NODPLT(I,IDNODE,M).EQ.0) GOTO 9150
L1307        IF (STO(NODPLT(I,IDNODE,M),1).GE.ICNT) LMY=M
L1308        IF (STO(NODPLT(I,IDNODE,M),1).GE.ICNT) ICNT=STO(NODPLT(I,IDNODE,M),
CONT: )
L1309   9150 CONTINUE
L1310        STO(NODPLT(I,IDNODE,LMY),1)=STO(NODPLT(I,IDNODE,LMY),1)-1
L1311        QLIST(I,LMB,3)=NODPLT(I,IDNODE,LMY)
L1312        QLIST(I,LMB,4)=2
L1313        QLIST(I,LMB,6)=NODPLT(I,IDNODE,1)
L1314 C
```

```
L1315 C      ICP-ICP:NON NW TRAFFIC

L1316  9160 IF (QLIST(I,LMB,2).EQ.1 .AND. QLIST(I,LMB,4).EQ.1) QLIST(I,LMB,7)=2
L1317 C      ICP-NCP:TRAFFIC ENTERING NW
L1318        IF (QLIST(I,LMB,2).EQ.1 .AND. QLIST(I,LMB,4).EQ.2) QLIST(I,LMB,7)=1
L1319 C      NCP-NCP:TRANSIT TRAFFIC
L1320        IF (QLIST(I,LMB,2).EQ.2 .AND. QLIST(I,LMB,4).EQ.2) QLIST(I,LMB,7)=5
L1321 C      NCP-ICP:TRAFFIC LEAVING NW
L1322        IF (QLIST(I,LMB,2).EQ.2 .AND. QLIST(I,LMB,4).EQ.1) QLIST(I,LMB,7)=8
L1323 C
L1324        DO 9170 M=1,3
L1325        NODEST(I,J,M)=0
L1326  9170 CONTINUE
L1327        DO 9180 ML=1,QUS
L1328        IF (QLIST(I,LMB,7).GT.Q(I,ML,2)) MK=ML
L1329        IF (QLIST(I,LMB,7).GT.Q(I,ML,2)) GOTO 9185
L1330  9180 CONTINUE
L1331  9185 MX1=LMB
L1332        MX2=QLIST(I,LMB,7)
L1333        DO 9190 M=MK,QUS
L1334        MY1=Q(I,M,1)
L1335        MY2=Q(I,M,2)
L1336        Q(I,M,1)=MX1
L1337        Q(I,M,2)=MX2
L1338        QLIST(I,Q(I,M,1),8)=M
L1339        IF (MY1.EQ.0) GOTO 9200
L1340        MX1=MY1
L1341        MX2=MY2
L1342  9190 CONTINUE
L1343  9200 CONTINUE
L1344 C
L1345  9450 IF (Q(I,1,1).EQ.0) GOTO 9750
L1346        NOCYC=0
L1347  9480 NOCYC=NOCYC+1
L1348        MCNT=0
L1349        DO 9500 K=1,NOI
L1350        DO 9500 J=1,5
L1351        SWITCH(K,J)=0
L1352  9500 CONTINUE
L1353        QCNTR=0
L1354        J=0
L1355        J=J+1
L1356  9510 IF (Q(I,J,1).EQ.0) GOTO 9620
L1357        DO 9520 M=1,NOI
L1358        IF (SWITCH(M,1).EQ.0) KMQ=M
L1359        IF (SWITCH(M,1).EQ.0) GOTO 9540
L1360        IF (SWITCH(M,1).EQ.QLIST(I,Q(I,J,1),1) .AND. SWITCH(M,2).EQ.QLIST(I,
CONT: Q(I,J,1),2)) GO TO 9600
L1361        IF (SWITCH(M,3).EQ.QLIST(I,Q(I,J,1),3) .AND. SWITCH(M,4).EQ.QLIST(I,
CONT: Q(I,J,1),4)) GO TO 9600
L1362  9520 CONTINUE
L1363  9540 IF (QLIST(I,Q(I,J,1),4).EQ.1) GOTO 9575
L1364        DO 9560 MX=1,8
L1365        IF (PARTNP(QLIST(I,Q(I,J,1),3),MX,1).EQ.QLIST(I,Q(I,J,1),6)) LLL=MX
L1366        IF (PARTNP(QLIST(I,Q(I,J,1),3),MX,1).EQ.QLIST(I,Q(I,J,1),6)) GOTO 95
CONT: 70
L1367  9560 CONTINUE
L1368        WRITE (6,9562)
L1369  9562 FORMAT (T2,'ERROR - MAIN PGM PARTITION NUMBER NOT FOUND STM 9570')
L1370        GOTO 1111
```

```
L1371   9570 IF (PARTNP(QLIST(I,Q(I,J,1),3),LLL,2).EQ.1) GOTO 9600
L1372        IF (STO(QLIST(I,Q(I,J,1),3),2).LT.1) GOTO 9600
L1373        STO(QLIST(I,Q(I,J,1),3),2)=STO(QLIST(I,Q(I,J,1),3),2)-1
L1374   9575 DO 9580 M=1,5
L1375        SWITCH(KMQ,M)=QLIST(I,Q(I,J,1),M)
L1376   9580 CONTINUE
L1377        DO 9584 M=1,8
L1378        QLIST(I,Q(I,J,1),M)=0
L1379   9584 CONTINUE
L1380        MKS=QUS-1
L1381        DO 9585 M=J,MKS
L1382        Q(I,M,1)=Q(I,(M+1),1)
L1383        Q(I,M,2)=Q(I,(M+1),2)
L1384        IF (Q(I,M,1).EQ.0) GOTO 9590
L1385        QLIST(I,Q(I,M,1),8)=M
L1386   9585 CONTINUE
L1387   9590 Q(I,QUS,1)=0
L1388        Q(I,QUS,2)=0
L1389        QCNTR=QCNTR+1
L1390        J=J-1
L1391        IF (QCNTR.EQ.PKMUX(I)) GOTO 9620
L1392   9600 J=J+1
L1393        IF (J.LE.QUS) GOTO 9510
L1394   9620 IF (QCNTR.EQ.0) SEMPRC(I,1)=(-100)
L1395        IF (QCNTR.EQ.0) GOTO 9712
L1396        DO 9650 M=1,NOI
L1397        DO 9650 MM=1,5
L1398        IF (SWITCH(M,MM).EQ.0) SWITCH(M,MM)=(-1)
L1399   9650 CONTINUE
L1400 C
L1401        KW1=NOI-1
L1402        DO 9675 JV=1,KW1
L1403        IF (SWITCH((JV+1),1).EQ.(-1)) GOTO 9680
L1404        KW2=JV+1
L1405        DO 9660 JW=KW2,NOI
L1406        IF (SWITCH(JV,3).EQ.SWITCH(JW,1) .AND. SWITCH(JV,4).EQ.SWITCH(JW,2))
CONT:   JU=JW
L1407        IF (SWITCH(JV,3).EQ.SWITCH(JW,1) .AND. SWITCH(JV,4).EQ.SWITCH(JW,2))
CONT:   GOTO 9665
L1408   9660 CONTINUE
L1409        GOTO 9675
L1410   9665 DO 9670 KA=1,5
L1411        KW3=SWITCH((JV+1),KA)
L1412        SWITCH((JV+1),KA)=SWITCH(JU,KA)
L1413        SWITCH(JU,KA)=KW3
L1414   9670 CONTINUE
L1415   9675 CONTINUE
L1416 C
```

```
      C       POINTER ALLOCATION
 9680 KK=NOCYC
      DO 9700 M=1,NOI
      IF (SWITCH(M,3).EQ.(-1)) GO TO 9700
      MCNT=MCNT+1
      IF (MCNT.EQ.1 .AND. NOCYC.EQ.1) SEMPRC(I,1)=SWITCH(M,1)
      IF (MCNT.EQ.1 .AND. NOCYC.EQ.1) SEMPRC(I,2)=SWITCH(M,2)
      IF (MCNT.EQ.1 .AND. NOCYC.EQ.1) LIN1=SWITCH(M,1)
      IF (MCNT.EQ.1 .AND. NOCYC.EQ.1) LIN2=SWITCH(M,2)
      IF (SWITCH(M,2).EQ.2) GO TO 9685
C
C     ICP
      PT2ICP(SWITCH(M,1),KK,1)=LIN1
      PT2ICP(SWITCH(M,1),KK,2)=LIN2
      PT2ICP(SWITCH(M,1),KK,3)=SWITCH(M,5)
      PT2ICP(SWITCH(M,1),KK,4)=SWITCH(M,3)
      PT2ICP(SWITCH(M,1),KK,5)=SWITCH(M,4)
      GO TO 9690
C
C     NCP
 9685 PT2NCP(SWITCH(M,1),KK,1)=LIN1
      PT2NCP(SWITCH(M,1),KK,2)=LIN2
      PT2NCP(SWITCH(M,1),KK,3)=SWITCH(M,5)
      PT2NCP(SWITCH(M,1),KK,4)=SWITCH(M,3)
      PT2NCP(SWITCH(M,1),KK,5)=SWITCH(M,4)
C
 9690 IF (MCNT.EQ.1 .AND. NOCYC.EQ.1) GO TO 9695
      IF (MCNT.EQ.1) GO TO 9692
C
      IF (LIN2.EQ.1) PT2ICP(LIN1,KK,6)=SWITCH(M,1)
      IF (LIN2.EQ.1) PT2ICP(LIN1,KK,7)=SWITCH(M,2)
      IF (LIN2.EQ.2) PT2NCP(LIN1,KK,6)=SWITCH(M,1)
      IF (LIN2.EQ.2) PT2NCP(LIN1,KK,7)=SWITCH(M,2)
      GO TO 9694
 9692 IF (LIN2.EQ.1) PT2ICP(LIN1,KK-1,6)=SWITCH(M,1)
      IF (LIN2.EQ.1) PT2ICP(LIN1,KK-1,7)=SWITCH(M,2)
      IF (LIN2.EQ.2) PT2NCP(LIN1,KK-1,6)=SWITCH(M,1)
      IF (LIN2.EQ.2) PT2NCP(LIN1,KK-1,7)=SWITCH(M,2)
 9694 CONTINUE
C
      LIN1=SWITCH(M,1)
      LIN2=SWITCH(M,2)
C
 9695 CONTINUE
C
      IF (SWITCH(M,2).EQ.1) PT2ICP(SWITCH(M,1),KK,8)=0
      IF (SWITCH(M,2).EQ.2) PT2NCP(SWITCH(M,1),KK,8)=0
      LZID=SWITCH(M,2)
      LZNO=SWITCH(M,1)
      LZCYC=KK
      LZZZ=M
C
 9700 CONTINUE
C
C     END OF CYCLE
      IF (SWITCH(LZZZ,2).EQ.1) PT2ICP(SWITCH(LZZZ,1),KK,8)=1
      IF (SWITCH(LZZZ,2).EQ.2) PT2NCP(SWITCH(LZZZ,1),KK,8)=1
C
      IF (NOCYC.EQ.CMAX) GO TO 9710
      NOLEVL=0
      GO TO 9480
C
C     END OF PERIOD: SET LAST PROCESSOR POINTER TO (-200)
 9710 IF (LZID.EQ.1) PT2ICP(LZNO,LZCYC,6)=(-200)
      IF (LZID.EQ.2) PT2NCP(LZNO,LZCYC,6)=(-200)
C
```

```
L1483 C      INCREMENT PRIORITIES
L1484  9712 DO 9715 J=1,QUS
L1485       IF (Q(I,J,1).EQ.0) GO TO 9716
L1486       Q(I,J,2)=Q(I,J,2)+QLIST(I,Q(I,J,1),7)
L1487       M1=J
L1488       N1=J
L1489  9714 M1=M1-1
L1490       IF (M1.EQ.0) GOTO 9715
L1491       IF (Q(I,N1,2).LE.Q(I,M1,2)) GOTO 9715
L1492       L1=Q(I,M1,1)
L1493       L2=Q(I,M1,2)
L1494       Q(I,M1,1)=Q(I,N1,1)
L1495       Q(I,M1,2)=Q(I,N1,2)
L1496       QLIST(I,Q(I,M1,1),8)=M1
L1497       Q(I,N1,1)=L1
L1498       Q(I,N1,2)=L2
L1499       QLIST(I,Q(I,N1,1),8)=N1
L1500       N1=N1-1
L1501       GO TO 9714
L1502  9715 CONTINUE
L1503 C
L1504  9716 ID=I+(4*N)+NONCPS+NONDS
L1505       TIMERZ(ID)=SWPROC
L1506       CN7=2
L1507       CALL PROGTM(TIMERZ,CLOCK,CNZ,ID)
L1508       SWCONT(I)=3
L1509  9720 IF (SIGNTM(I+(4*N)+NONCPS+NONDS).NE.3) GOTO 9750
L1510       SWCONT(I)=1
L1511       SEMPH(I)=1
L1512       BUSSEM(I)=1
L1513  9750 CONTINUE
L1514  9999 CONTINUE
L1515  1111 CONTINUE
L1516       STOP
L1517       END
L1518 C
```

PROGRAM SUBROUTINE : ACCESS

RLQ = 1, 2, 3, 4 : PROGRAM CONTROL VARIABLE

NUMBER: IS NUMBER OF BUFFER BLOCKS TO BE RELEASED OR ACCESSED

LINKNO: IS LOGICAL LINK NUMBER

ICPNO: IS ICP NUMBER

TYP: IS TYPE OF BUFFERS REQUIRED OR RELEASED

ACCSS: SIGNAL: = 1 BUFFERS GRANTED
= 2 BUFFERS REFUSED

SDEOM: SIGNAL: = 1 ALL BUFFERS RELEASED BY LINK
= 2 BUFFERS STILL OCCUPIED

NCO: NUMBER OF COMMON BUFFER BLOCKS FREE

NSI: NUMBER OF SINGLE PACKET BUFFER BLOCKS FREE

NSO: NUMBER OF SOURCE PACKET BUFFER BLOCKS FREE

NMU: NUMBER OF MULTIPACKET BUFFER BLOCKS FREE

SUBROUTINE ACCESS (RLQ, NUMBR, LINKNO, ICPNO, TYP, ACCSS,
SDEOM, NCO, NSO, NSI, NMU)

PROGRAM CONTROL VARIABLE: RLQ

IF RLQ = 1:

RELEASE OF BUFFER SPACE AT ICP

FIND LOCATIONS OF LINK NUMBER AND TYPE OF BUFFERS ACQUIRED

RELEASE THESE

IF RLQ = 2:

REQUEST FOR BUFFER SPACE AT ICP

DETERMINE WHETHER TOTAL NUMBER OF REQUIRED BUFFER BLOCKS CAN BE ALLOCATED.

IF NOT SIGNAL ACCSS = 2

OTHERWISE STORE RELEVANT LOGICAL LINK AND BUFFER TYPE PARAMETERS AND SIGNAL ACCSS = 1

IF RLQ = 3:

DETERMINE NUMBER OF FREE BUFFER BLOCKS FOR EACH TYPE: NSO, NSI, NMV, NCO

IF RLQ = 4:

INITIALIZATION OF SIMULATION: SET NUMBER OF BUFFER BLOCKS FOR EACH TYPE

END

```
L1519 C
L1520 C      PROGRAM  SUBROUTINES
L1521        SUBROUTINE ACCESS(RLQ,NUMBR,LINKNO,ICPNO,TYP,ACCSS,SDEOM,NCO,NSO,NSI
CONT: ,NMU)
L1522        INTEGER BLOCK(10,8), ALLOC(10,20,4)
L1523        INTEGER LFTTYP,LFTCOM,TOTAL,VAR1,VAR2,RLQ,NUMBR,LINKNO
L1524        INTEGER ICPNO,TYP,ACCSS,SDEOM,NTP,NC
L1525        INTEGER RELTYP,RELCOM,NOTAL,VAR3,VAR4
L1526 C
L1527 C      NUMBER OF ICPS IN NETWORK
L1528        NOICPS=10
L1529 C
L1530 C      NUMBER OF PORTS IN NETWORK
L1531        N=20
L1532 C
L1533        GO TO (100,200,300,400), RLQ
L1534 C
L1535 C      RELEASE  OF  BUFFER  SPACE  AT  ICP
L1536  100   I=ICPNO
L1537        DO 105 J=1,N
L1538        IF (ALLOC(I,J,1).NE.LINKNO .OR. ALLOC(I,J,2).NE.TYP) GO TO 105
L1539        RELTYP=ALLOC(I,J,3)
L1540        RELCOM=ALLOC(I,J,4)
L1541        NOTAL=RELTYP+RELCOM
L1542        IF (NUMBR.GT.NOTAL) WRITE (6,445)
L1543        VAR3=NUMBR-RELCOM
L1544        VAR4=RELCOM
L1545        ALLOC(I,J,3)=ALLOC(I,J,3)-VAR3
L1546        ALLOC(I,J,4)=ALLOC(I,J,4)-VAR4
L1547        IF (ALLOC(I,J,3).LT.0 .OR. ALLOC(I,J,4).LT.0) WRITE (6,450)
L1548        SDEOM=2
L1549        IF (ALLOC(I,J,3).EQ.0 .AND. ALLOC(I,J,4).EQ.0) SDEOM=1
L1550        IF (ALLOC(I,J,3).EQ.0 .AND. ALLOC(I,J,4).EQ.0) ALLOC(I,J,1)=0
L1551        IF (ALLOC(I,J,3).EQ.0 .AND. ALLOC(I,J,4).EQ.0) ALLOC(I,J,2)=0
L1552        GO TO 110
L1553  105   CONTINUE
L1554        WRITE (6,455)
L1555  110   J=TYP
L1556        K=TYP+4
L1557        BLOCK(I,J)=BLOCK(I,J)-VAR3
L1558        BLOCK(I,4)=BLOCK(I,4)-VAR4
L1559        IF (BLOCK(I,J).LT.0 .OR. BLOCK(I,4).LT.0) WRITE (6,460)
L1560        GO TO 435
L1561
```

```
L1562 C
L1563 C      REQUEST  FOR  BUFFER  SPACE  AT  ICP
L1564   200  I=ICPNO
L1565        J=TYP
L1566        K=TYP+4
L1567        LFTTYP=BLOCK(I,K)-BLOCK(I,J)
L1568        LFTCOM=BLOCK(I,8)-BLOCK(I,4)
L1569        TOTAL=LFTTYP+LFTCOM
L1570        IF (NUMBR.   .TOTAL) GO TO 220
L1571        VAR1=LFTTYP-NUMBR
L1572        IF (VAR1.GE.0) VAR2=0
L1573        IF (VAR1.GE.0) VAR1=NUMBR
L1574        IF (VAR1.LT.0) VAR2=-(VAR1)
L1575        IF (VAR1.LT.0) VAR1=LFTTYP
L1576        BLOCK(I,J)=BLOCK(I,J)+VAR1
L1577        BLOCK(I,4)=BLOCK(I,4)+VAR2
L1578 C      HERE J IS NUMBER OF LOGICAL LINKS FOR ALLOC(ARRAY)
L1579        DO 205 J=1,N
L1580        IF (ALLOC(I,J,1).NE.LINKNO .OR. ALLOC(I,J,2).NE.TYP) GO TO 205
L1581        ALLOC(I,J,3)=ALLOC(I,J,3)+VAR1
L1582        ALLOC(I,J,4)=ALLOC(I,J,4)+VAR2
L1583        ACCSS=1
L1584        GO TO 225
L1585   205  CONTINUE
L1586        DO 215 J=1,N
L1587        IF (ALLOC(I,J,1).NE.0) GO TO 215
L1588   210  ALLOC(I,J,1)=LINKNO
L1589        ALLOC(I,J,2)=TYP
L1590        ALLOC(I,J,3)=VAR1
L1591        ALLOC(I,J,4)=VAR2
L1592        ACCSS=1
L1593        GO TO 225
L1594   215  CONTINUE
L1595        WRITE (6,440)
L1596   220  ACCSS=2
L1597   225  GO TO 435
L1598 C
```

```
C      NUMBER  OF  BLOCKS  LEFT  IN  ICP  MEMORY
 300   I=ICPNO
       NSO=BLOCK(I,5)-BLOCK(I,1)
       NSI=BLOCK(I,6)-BLOCK(I,2)
       NMU=BLOCK(I,7)-BLOCK(I,3)
       NCO=BLOCK(I,8)-BLOCK(I,4)
       GO TO 435
C
C      INITIALIZATION  OF  ICP  MEMORY
 400   DO 410 I=1,NOICPS
       DO 410 J=1,4
       BLOCK(I,J)=0
 410   CONTINUE
       DO 415 I=1,NOICPS
       BLOCK(I,5)=8
       BLOCK(I,6)=5
       BLOCK(I,7)=8
       BLOCK(I,8)=50
 415   CONTINUE
       DO 420 I=1,NOICPS
       DO 420 J=1,N
       DO 420 K=1,4
       ALLOC(I,J,K)=0
 420   CONTINUE
C
C      END  OF  SUBROUTINE  ACCESS
 435   CONTINUE
 440   FORMAT(T2,'ERROR NO1')
 445   FORMAT(T2,'ERROR NO2')
 450   FORMAT(T2,'ERROR NO3')
 455   FORMAT(T2,'ERROR NO4')
 460   FORMAT(T2,'ERROR NO5')
       RETURN
       END
C
```

PROGRAM SUBROUTINE: RESERV

STAT = 3, 4, 5, 7 : PROGRAM CONTROL VARIABLE

ICPRES: ICP NUMBER

LI RES: LOGICAL LINK NUMBER

NOBUF: NUMBER OF BUFFERS REQUIRED

CLK: CLOCK VALUE

RESU: RESULT - 1 REQUEST GRANTED
- 2 REQUEST REFUSED

TP: TYPE OF BUFFERS REQUIRED

SUBROUTINE RESERV (STAT, ICPRES, LNKRES, NOBUF, CLK, RESU, TP)

PROGRAM CONTROL VARIABLE: STAT

IF STAT = 3:

REQUEST TO BE PLACED ON WAITING LIST FOR ICP BUFFERS

IF REQUEST GRANTED, STORE ALL RELEVANT PARAMETERS IN WAITLN
AND SIGNAL RESU = 1

IF REQUEST REFUSED - WAITING LIST LOCATIONS ALL OCCUPIED -
SIGNAL RESU = 2

IF STAT = 4:

DETERMINE PARAMETERS OF A LOGICAL LINK THAT IS WAITING FOR BUFFERS,

i.e., NOBUF : NUMBER OF BUFFERS REQUIRED
CLX : TIME AT WHICH REQUEST WAS MADE
TP : TYPE OF BUFFERS REQUIRED
RESU = 3: DUMMY VARIABLE

IF STAT = 5

INITIALIZATION OF SUBROUTINE

SET ALL WAITING LIST LOCATIONS TO ZERO (CONTENTS THEREOF)

IF STAT = 7

THIS SECTION EXECUTES THE WAITING-STATE ALGORITHM THAT DETERMINES WHICH LOGICAL LINKS ARE TO OBTAIN THE REQUIRED BUFFERS DEPENDING ON THE TYPE OF BUFFERS SOUGHT

THIS SECTION IS EXECUTED EVERY PERIOD IF THERE ARE REQUESTS

CALL SUER ACCESS TO DETERMINE NO OF FREE BUFFERS OF EACH TYPE

NCR : NO OF COMMON

NSOV : NO OF SOURCE

NSING : NO OF SINGLE PACKET

NMUL : NO OF MULTIPACKET

TYPES OF REQUESTS:

SOURCE BLOCKS: NSOU + NCR

SINGLE PACKET BLOCKS: NSING + NCR

MULTIPACKET BLOCKS: NMUL + NCR

LMA (I): I = ICP NUMBER

: REQUEST BEING SERVICED - LOGICAL LINK

ONCE A REQUEST IS CHOSEN FOR SERVICE, NO OTHER LOGICAL LINK IN THE ICP IS SERVICED UNTIL THE LINK BEING SERVICED HAS BEEN ALLOCATED ALL ITS BUFFERS

LMA (I) = O: NO REQUEST SERVICED

DETERMINE REQUEST WITH HIGHEST PRIORITY AND SERVICE IT

PROVIDED THERE ARE SOME BUFFERS FREE IN ITS TYPE

i.e. (NCR + NMUC) $\neq$ O

OR (NCR + NSOU) $\neq$ O

OR (NCR + NSING) $\neq$ O

ALLOCATE THE AVAILABLE BUFFERS

DECREASE TYPE (NCR + NMUL)
(NCR + SOU)
(NCR + NSING)

ACCORDING TO NUMBER OF BLOCKS ALLOCATED

CALL ACCESS SUBROUTINE TO ALLOCATE BLOCKS.

SIGNAL: LGLINK = 1 THAT REQUEST HAS BEEN GRANTED

GO BACK AND REPEAT FOR A NEW REQUEST

SIGNAL: LGLINK = 2 FOR OTHER LOGICAL LINKS
INDICATING THAT SERVICE REQUESTS STILL WAITING

INCREASE PRIORITIES OF REQUESTS

NPRSIN: SINGLE PACKET PRIORITY INCREMENT

NPRMUL: MULTIPACKET PRIORITY INCREMENT

NPRSOU: SOURCE PRIORITY INCREMENT

END

```
L1634 C
L1635 C
L1636       SUBROUTINE RESERV(STAT,ICPRES,LNKRES,NOBUF,CLK,RESU,TP)
L1637       INTEGER SIGNTM(130),LGLINK(20,2)
L1638       INTEGER WAITLN(10,10,5), LMA(10)
L1639       INTEGER STAT,ICPRES,LNKRES,NOBUF,CLK,RESU,TP
L1640       INTEGER RST,NRB,LINKNR,ICPNR,TNR,ACC,SDM,NTR,NCR
L1641       COMMON SIGNTM,LGLINK
L1642       I=ICPRES
L1643       NRSV=10
L1644       NOICPS=10
L1645       NOLNK=20
L1646       GO TO (800,800,300,400,500,800,700), STAT
L1647 C     WAITING LIST FOR ICP BUFFERS
L1648  300  DO 305 J=1,NRSV
L1649       IF (WAITLN(I,J,1).NE.0) GO TO 305
L1650       WAITLN(I,J,1)=LNKRES
L1651       WAITLN(I,J,2)=NOBUF
L1652       WAITLN(I,J,3)=CLK
L1653       WAITLN(I,J,4)=TP
L1654       WAITLN(I,J,5)=0
L1655       RESU=1
L1656       GO TO 800
L1657  305  CONTINUE
L1658       RESU=2
L1659       GOTO 800
L1660 C
L1661  400  DO 405 J=1,NRSV
L1662       IF (WAITLN(I,J,1).NE.LNKRES) GO TO 405
L1663       NOBUF=WAITLN(I,J,2)
L1664       CLK=WAITLN(I,J,3)
L1665       TP=WAITLN(I,J,4)
L1666       DO 404 KRS=1,5
L1667       WAITLN(I,J,KRS)=0
L1668  404  CONTINUE
L1669       RESU=3
L1670       GO TO 800
L1671  405  CONTINUE
L1672       WRITE (6,810)
L1673 C
L1674 C     INITIALIZATION OF SUBROUTINE
L1675  500  DO 505 I=1,NOICPS
L1676       LMA(I)=0
L1677       DO 505 J=1,NRSV
L1678       DO 505 K=1,5
L1679       WAITLN(I,J,K)=5555555
L1680  505  CONTINUE
L1681       GO TO 800
L1682 C
```

```
L1683 C      WAITING STATE ALGORITHM
L1684  700   I=ICPRES
L1685  710   RST=3
L1686        CALL ACCESS(RST,NRB,LINKNR,I,TNR,ACC,SDM,NCR,NSOU,NSING,NMUL)
L1687        IF (NCR.EQ.0 .AND. NSOU.EQ.0 .AND. NSING.EQ.0 .AND. NMUL.EQ.0) GOTO
CONT: 790
L1688        LPS=0
L1689        IF (LMA(I).NE.0) GOTO 775
L1690        IF ((NCR+NSOU).EQ.0) GO TO 730
L1691        DO 720 J=1,NRSV
L1692        IF (WAITLN(I,J,1).NE.0 .AND. WAITLN(I,J,4).EQ.1 .AND. WAITLN(I,J,5).
CONT: GE.LPS) LMA(I)=J
L1693        IF (WAITLN(I,J,1).NE.0 .AND. WAITLN(I,J,4).EQ.1 .AND. WAITLN(I,J,5).
CONT: GE.LPS) LPS=WAITLN(I,J,5)
L1694  720   CONTINUE
L1695  730   IF ((NCR+NMUL).EQ.0) GO TO 750
L1696        DO 740 J=1,NRSV
L1697        IF (WAITLN(I,J,1).NE.0 .AND. WAITLN(I,J,4).EQ.3 .AND. WAITLN(I,J,5).
CONT: GE.LPS) LMA(I)=J
L1698        IF (WAITLN(I,J,1).NE.0 .AND. WAITLN(I,J,4).EQ.3 .AND. WAITLN(I,J,5).
CONT: GE.LPS) LPS=WAITLN(I,J,5)
L1699  740   CONTINUE
L1700  750   IF ((NCR+NSING).EQ.0) GO TO 770
L1701        DO 760 J=1,NRSV
L1702        IF (WAITLN(I,J,1).NE.0 .AND. WAITLN(I,J,4).EQ.2 .AND. WAITLN(I,J,5).
CONT: GE.LPS) LMA(I)=J
L1703        IF (WAITLN(I,J,1).NE.0 .AND. WAITLN(I,J,4).EQ.2 .AND. WAITLN(I,J,5).
CONT: GE.LPS) LPS=WAITLN(I,J,5)
L1704  760   CONTINUE
L1705  770   IF (LMA(I).EQ.0) GO TO 790
L1706  775   RST=2
L1707        ICPNR=I
L1708        LINKNR=WAITLN(I,LMA(I),1)
L1709        IF (WAITLN(I,LMA(I),4).EQ.1) GO TO 761
L1710        IF (WAITLN(I,LMA(I),4).EQ.2) GO TO 762
L1711        IF (WAITLN(I,LMA(I),4).EQ.3) GO TO 763
L1712  761   NZLFT=(NCR+NSOU)-WAITLN(I,LMA(I),2)
L1713        IF (NZLFT.GE.0) NRB=WAITLN(I,LMA(I),2)
L1714        IF (NZLFT.LT.0) NRB=(NCR+NSOU)
L1715        TNR=1
L1716        GO TO 765
L1717  762   NZLFT=(NCR+NSING)-WAITLN(I,LMA(I),2)
L1718        IF (NZLFT.GE.0) NRB=WAITLN(I,LMA(I),2)
L1719        IF (NZLFT.LT.0) NRB=(NCR+NSING)
L1720        TNR=2
L1721        GO TO 765
L1722  763   NZLFT=(NCR+NMUL)-WAITLN(I,LMA(I),2)
L1723        IF (NZLFT.GE.0) NRB=WAITLN(I,LMA(I),2)
L1724        IF (NZLFT.LT.0) NRB=(NCR+NMUL)
L1725        TNR=3
L1726  765   WAITLN(I,LMA(I),2)=WAITLN(I,LMA(I),2)-NRB
L1727        CALL ACCESS(RST,NRB,LINKNR,ICPNR,TNR,ACC,SDM,NCR,NSOU,NSING,NMUL)
L1728        LGLINK(WAITLN(I,LMA(I),1),1)=1
L1729        LGLINK(WAITLN(I,LMA(I),1),2)=1
L1730        IF (WAITLN(I,LMA(I),2).EQ.0 .AND. WAITLN(I,LMA(I),4).EQ.1) LGLINK(W
CONT: ITLN(I,LMA(I),1),1)=2
L1731        IF (WAITLN(I,LMA(I),2).EQ.0 .AND. WAITLN(I,LMA(I),4).EQ.2) LGLINK(W
CONT: ITLN(I,LMA(I),1),2)=2
L1732        IF (WAITLN(I,LMA(I),2).EQ.0 .AND. WAITLN(I,LMA(I),4).EQ.3) LGLINK(W
CONT: ITLN(I,LMA(I),1),2)=2
L1733        IF (WAITLN(I,LMA(I),2).EQ.0) WAITLN(I,LMA(I),1)=0
L1734        IF (WAITLN(I,LMA(I),2).EQ.0) LMA(I)=0
L1735        IF (WAITLN(I,LMA(I),2).EQ.0) GOTO 710
```

```
L1736 C
L1737 C      NPRSIN=SINGLE PACKET PRIORITY INCREMENT
L1738 C      NPRMUL=MULTIPACKET PRIORITY INCREMENT
L1739 C      NPRSOU=SOURCE PRIORITY INCREMENT
L1740  790   NPRSIN=1
L1741        NPRMUL=1
L1742        NPRSOU=1
L1743        DO 795 J=1,NRSV
L1744        IF (WAITLN(I,J,1).EQ.0) GO TO 795
L1745        IF (WAITLN(I,J,4).EQ.1) WAITLN(I,J,5)=WAITLN(I,J,5)+NPRSOU
L1746        IF (WAITLN(I,J,4).EQ.2) WAITLN(I,J,5)=WAITLN(I,J,5)+NPRSIN
L1747        IF (WAITLN(I,J,4).EQ.3) WAITLN(I,J,5)=WAITLN(I,J,5)+NPRMUL
L1748  795   CONTINUE
L1749        GO TO 800
L1750 C
L1751 C      END OF SUBROUTINE
L1752  800   CONTINUE
L1753  805   FORMAT (T2,'ERROR NO6')
L1754  810   FORMAT (T2,'ERROR NO7')
L1755        RETURN
L1756        END
L1757 C
```

PROGRAM SUBROUTINE: PROGTM

TIMERZ : TIME INTERVAL

CLOCK : CLOCK VALUE

CNZ : 1, 2, 3, 4, 5, 6 : PROGRAM CONTROL

ID : IDENTIFIER

SUBROUTINE PROGTM (TIMERZ, CLOCK, CNZ, ID)

IF CNZ = 1:

NO OPERATION

IF CNZ = 2:

INTERVAL GENERATION

THE INTERVAL TIMERZ GENERATED BY IDENTIFIER ID
IS STORED IN ORDER OF EVENTS

IF CNZ = 3:

INTERVAL DELETION

REMOVE THE INTERVAL FROM THE QUEUE AS IDENTIFIED BY ID

IF CNZ = 4:

INTERVAL UPDATE

EVERY PERIOD THE INTERVAL AT THE HEAD-OF-QUEUE
BECOMES THE NEW CLOCK VALUE

IF CNZ = 5:

TRANSFER CLOCK VALUE TO MAIN PGM

IF CNZ = 6:

INITIALIZATION OF TIMER AND IDENTIFIER QUEUES

END

PROGRAM SUBROUTINE: TIMER

LNBITS : INTEGER, LENGTH OF MSG IN BITS

SPDBTS : INTEGER, LINE RATE IN BPS

CONVERTS ABOVE VARIABLES TO REAL AND DIVIDES TO
DETERMINE TIME TAKEN FOR MSG TO TRAVERSE CHANNEL

RSTV : REAL, DURATION

SUBROUTINE TIMER (LNBITS, SPDBITS, RSTV)

```
L1758 C      INTERVAL  TIMER  CONTROL
L1759        SUBROUTINE PROGTM(TIMERZ,CLOCK,CNZ,ID)
L1760        REAL TIMERZ(130), EVENT(130), CLOCK
L1761        INTEGER SIGNTM(130), LGLINK(20,2), IDTINV(130) , CNZ, ID
L1762        COMMON SIGNTM,LGLINK
L1763 C
L1764 C      NOLABL: NUMBER OF IDENTIFIERS
L1765        NOLABL=130
L1766 C
L1767        GO TO (100,200,300,400,500,600), CNZ
L1768 C
L1769 C      IDLE
L1770  100   CONTINUE
L1771        GO TO 700
L1772 C
L1773 C      INTERVAL GENERATION
L1774  200   SIGNTM(ID)=2
L1775        RESUL=CLOCK+TIMERZ(ID)
L1776        DO 210 I=1,NOLABL
L1777        IF (RESUL.LT.EVENT(I))MKR=I
L1778        IF (RESUL.LT.EVENT(I)) GO TO 230
L1779  210   CONTINUE
L1780        WRITE (6,220)
L1781  220   FORMAT (T2,'ERROR - INTERVAL GENERATION  STM 220  SUBR:PROGTM')
L1782  230   IF (MKR.EQ.NOLABL) GO TO 260
L1783        XX1=RESUL
L1784        MX1=ID
L1785        DO 240 I=MKR,NOLABL
L1786        XY1=EVENT(I)
L1787        MY1=IDTINV(I)
L1788        EVENT(I)=XX1
L1789        IDTINV(I)=MX1
L1790        XX1=XY1
L1791        MX1=MY1
L1792  240   CONTINUE
L1793  260   EVENT(MKR)=RESUL
L1794        IDTINV(MKR)=ID
L1795        GO TO 700
L1796 C
L1797 C      INTERVAL DELETION
L1798  300   DO 310 K=1,NOLABL
L1799        IF (IDTINV(K).NE.ID) GOTO 310
L1800        KMR=K
L1801        GOTO 330
L1802  310   CONTINUE
L1803        GOTO 700
L1804  330   KMZ=NOLABL-1
L1805        IF (KMR.EQ.NOLABL) GOTO 360
L1806        DO 340 K=KMR,KMZ
L1807        EVENT(K)=EVENT(K+1)
L1808        IDTINV(K)=IDTINV(K+1)
L1809  340   CONTINUE
L1810  360   EVENT(NOLABL)=1.0E+75
L1811        IDTINV(NOLABL)=0
L1812        GOTO 700
L1813 C
```

```
L1814 C      INTERVAL UPDATE
L1815  400   IF (CLOCK.GT.1.0E+73) WRITE (6,410)
L1816  410   FORMAT (T2,'ERROR - MAXIMUM CLOCK VALUE EXCEEDED')
L1817        IF (EVENT(1).GT.1.0E+74) GO TO 700
L1818        CLOCK=EVENT(1)
L1819  420   SIGNTM(IDTINV(1))=3
L1820        KSM=NOLABL-1
L1821        DO 430 I=1,KSM
L1822        EVENT(I)=EVENT(I+1)
L1823        IDTINV(I)=IDTINV(I+1)
L1824  430   CONTINUE
L1825        EVENT(NOLABL)=1.0E+75
L1826        IDTINV(NOLABL)=0
L1827        IF (EVENT(1).EQ.CLOCK) GO TO 420
L1828        GO TO 700
L1829 C
L1830 C      CLOCK VALUE
L1831  500   CLOCK=CLOCK
L1832        GO TO 700
L1833 C
L1834 C      INITIALIZATION
L1835  600   DO 610 I=1,NOLABL
L1836        EVENT(I)=1.0E+75
L1837        IDTINV(I)=0
L1838        TIMERZ(I)=0.0
L1839        SIGNTM(I)=1
L1840  610   CONTINUE
L1841        CLOCK=0.0
L1842        GO TO 700
L1843 C
L1844  700   CONTINUE
L1845        RETURN
L1846        END
L1847 C
L1848 C
L1849        SUBROUTINE TIMER(LNBITS,SPDBTS,RSTV)
L1850        INTEGER LNBITS,SPDBTS
L1851        REAL BITS,BPS,RSTV
L1852        BITS=LNBITS
L1853        BPS=SPDBTS
L1854        RSTV=(BITS/BPS)
L1855        RETURN
L1856        END
```

```
L1148 C      ***************************************************************
L1149        IF (INTERV.EQ.1000 .OR. INTERV.EQ.2000 .OR. INTERV.EQ.3000 .OR. IN
CONT: RV.EQ.4000) GOTO 1198
L1150        IF (INTERV.EQ.5000 .OR. INTERV.EQ.6000) GOTO 1198
L1151        GOTO 1199
L1152   1198 CONTINUE
L1153        WRITE (6,7753) ICPICP,NCPNCP
L1154   7753 FORMAT (T2,'ICPICP,NCPNCP',T30,2I8)
L1155        WRITE (6,1119) (LCVT(I),I=1,6)
L1156   1119 FORMAT (T2,'NODE THROUGHPUT',T20,6I8)
L1157        WRITE (6,1118) AVERAG,VARIAN,NUMAVG
L1158   1118 FORMAT (T2,'MEAN,MEANSQUARE,NUMBER',T35,2F15.4,T70,I8)
L1159        WRITE (6,9991) BMEAN,BVAR,NBEG
L1160   9991 FORMAT (T2,'SOURC:MEAN,MEAN2,NO',T35,2F15.4,T70,I8)
L1161        CNZ=5
L1162        CALL PROGTM(TIMER2,CLOCK,CN2,ID)
L1163        WRITE (6,1114) CLOCK
L1164   1114 FORMAT (T2,'CLOCK VALUE',T30,F16.4)
L1165        WRITE (6,1171) (NOCHL(I),I=1,7)
L1166        WRITE (6,1172) (NOCHL(I),I=8,14)
L1167        WRITE (6,1176) (NOCHL(I),I=15,20)
L1168   1176 FORMAT (T2,6I8)
L1169        WRITE (6,1173) PMEANC
L1170   1173 FORMAT (T2,'PMEANC',T20,1F15.3)
L1171   1171 FORMAT (T2,7I8)
L1172   1172 FORMAT (T2,7I8)
L1173        WRITE (6,1178)
L1174   1178 FORMAT (T2///)
L1175   1199 CONTINUE
L1176 C      ***************************************************************
```

ERROR MESSAGES

Subroutine ACCESS

'ERROR NO2' : Attempt to release more blocks than were allocated

'ERROR NO3' : More blocks released than allocated for a logical link (ALLOC ARRAY)

'ERROR NO4' : Logical link number for which buffer release requested not found

'ERROR NO5' : More blocks released than allocated for a logical link (BLOCK ARRAY)

Subroutine RESERV

'ERROR NO7' : Logical link number for which reservation requested, not found

Subroutine PROGTM

'ERROR-INTERVAL GENERATION' : Identifier unable to be stored in event queue

'MAXIMUM CLOCK VALUE EXCEEDED' : Simulation clock value greater than 1,OE + 74 seconds

Main Program

'ERROR-PACKET ARRAY OVERFLOW' :

'ERROR-NODEST ARRAY OVERFLOW' :

'ERROR-QLIST ARRAY OVERFLOW' :

Above arrays are used to store the simulation data. An overflow indicates that the dimensions of the array were not enough to store all the data. Note that the number of locations used by the program may vary during the simulation.

'ERROR-NO OF DEVIATES FOR RANDOM NO GEN EXC' :

The simulation has used its quota of deviates used for generating messages with random lengths and interarrival times.

'ERROR NO8' : The value of variable ACC when calling subroutine ACCESS was neither one nor two (buffers granted, refused resp.).

'ERROR NO9' : The value of variable RES when calling subroutine RESERV was neither one nor two (requested granted, refused resp.).

Internodal Packet Transmission

'ERROR-PRESENT NODE NOT FOUND' : present nodal number cannot be found in MAPNCP array.

'ERROR-DUPLICATION PROCEDURE' : duplicates of a packet are found in array PACKET, which is supposed to contain one copy only of each packet.

'ERROR NCP SIM 1' : Packet partition number cannot be found in NCP

'ERROR NCP SIM 2' : No storage for packet at NCP. A packet trm from the data bus to the NCP under control of the switch processor must always find free buffer blocks.

'ERROR-TRANSMISSION FIELDS' : Trm field flags are set to invalid values.

'ERROR-FRAME TRANSMISSION' : Receiver field flags are set to invalid values.

'ERROR-PACKET (CHANNEL) RELEASE' : Acknowledged packet cannot be found for release of buffers.

'ERROR-PARTITION MISSING' : Partition number at receiver cannot be found.

'ERROR-SYNCHRONIZATION' : Packet field flags and NCP transmitter field flags do not make a valid combination.

'ERROR-NODAL NUMBER NOT FOUND' : nodal number to which NCP belongs not found in MAPNCP array.

'ERROR-FRAME ACKNOWLEDGEMENT' : Acknowledgement flag settings are invalid.

A listing for the topologies of three networks is contained in the following pages. This list is the input data necessary to define and to simulate the networks.

NET1 defines the topology for the Network Simulation, NODD for the Nodal Simulation, and IOPD for a network used to conduct tests on the source node-to-destination node protocols. These tests were conducted and the results displayed in Chapter 4.

/D NET1

L.001	1	5000	2	500	8	4000	5	40	14
L.002	500	100	1	16	70	12	1	450	1
L.003	8	4	250	50					
L.004	1	1	1	7	7200	7200	400	00	0
L.005	1	1	1	7	7200	7200	400	00	0
L.006	1	2	1	8	7200	7200	400	00	0
L.007	1	1	2	9	7200	7200	400	00	0
L.008	1	2	2	10	7200	7200	400	00	0
L.009	1	3	3	17	7200	7200	400	00	0
L.010	1	4	3	18	7200	7200	400	00	0
L.011	1	5	4	25	7200	7200	400	00	0
L.012	1	6	4	26	7200	7200	400	00	0
L.013	1	7	5	33	7200	7200	400	00	0
L.014	1	8	5	34	7200	7200	400	00	0
L.015	2	9	1	1	7200	7200	400	00	0
L.016	2	10	1	2	7200	7200	400	00	0
L.017	2	9	2	15	7200	7200	400	00	0
L.018	2	10	2	16	7200	7200	400	00	0
L.019	2	11	3	19	7200	7200	400	00	0
L.020	2	12	3	20	7200	7200	400	00	0
L.021	2	13	4	27	7200	7200	400	00	0
L.022	2	14	4	28	7200	7200	400	00	0
L.023	2	15	5	35	7200	7200	400	00	0
L.024	2	16	5	36	7200	7200	400	00	0
L.025	3	17	1	3	7200	7200	400	00	0
L.026	3	18	1	4	7200	7200	400	00	0
L.027	3	17	2	11	7200	7200	400	00	0
L.028	3	18	2	12	7200	7200	400	00	0
L.029	3	19	3	23	7200	7200	400	00	0
L.030	3	20	3	24	7200	7200	400	00	0
L.031	3	21	4	29	7200	7200	400	00	0
L.032	3	22	4	30	7200	7200	400	00	0
L.033	3	23	5	37	7200	7200	400	00	0
L.034	3	24	5	38	7200	7200	400	00	0
L.035	4	25	1	5	7200	7200	400	00	0
L.036	4	26	1	6	7200	7200	400	00	0
L.037	4	25	2	13	7200	7200	400	00	0
L.038	4	26	2	14	7200	7200	400	00	0
L.039	4	27	3	21	7200	7200	400	00	0
L.040	4	28	3	22	7200	7200	400	00	0
L.041	4	29	4	31	7200	7200	400	00	0
L.042	4	30	4	32	7200	7200	400	00	0
L.043	4	31	5	39	7200	7200	400	00	0
L.044	4	32	5	40	7200	7200	400	00	0
L.045	5	33	1	7	7200	7200	400	00	0
L.046	5	34	1	8	7200	7200	400	00	0
L.047	5	33	2	15	7200	7200	400	00	0
L.048	5	34	2	16	7200	7200	400	00	0
L.049	5	35	3	23	7200	7200	400	00	0
L.050	5	36	3	24	7200	7200	400	00	0
L.051	5	37	4	31	7200	7200	400	00	0
L.052	5	38	4	32	7200	7200	400	00	0
L.053	5	39	5	33	7200	7200	400	00	0
L.054	5	40	5	34	7200	7200	400	00	0

L.055	3	5	0	0	0	0	0	0
L.056	4	0	0	0	0	0	0	0
L.057	2	0	0	0	0	0	0	0
L.058	1	2	0	0	0	0	0	0
L.059	4	0	0	0	0	0	0	0
L.060	5	0	0	0	0	0	0	0
L.061	1	3	0	0	0	0	0	0
L.062	4	5	0	0	0	0	0	0
L.063	2	0	0	0	0	0	0	0
L.064	1	0	0	0	0	0	0	0
L.065	3	0	0	0	0	0	0	0
L.066	5	0	0	0	0	0	0	0
L.067	1	3	0	0	0	0	0	0
L.068	2	4	0	0	0	0	0	0
L.069	0	2	3	4	3			
L.070	1	0	1	4	4			
L.071	1	1	0	4	5			
L.072	1	2	3	0	5			
L.073	3	4	3	4	0			
L.074	4	10	7	1	11	13	3	
L.075	9	8	2	5	14	6	12	
L.076	11	10	11	12	10			
L.077	1	2	3	4	5	6	7	8
L.078	9	10	11	12	13	14	15	16
L.079	17	18	19	20	21	22	23	24
L.080	25	26	27	28	29	30	31	32
L.081	33	34	35	36	37	38	39	40
L.082	1	2	3	0				
L.083	7	8	0	0				
L.084	4	5	6	0				
L.085	9	10	11	12				
L.086	13	14	0	0				
L.087	0	3	1	2	1			
L.088	7	0	7	8	8			
L.089	4	4	0	5	6			
L.090	10	9	11	0	12			
L.091	13	14	13	14	0			

/D NODD									
L.001	01	0001	2	500	8	4000	6	40	20
L.002	500	100	1	16	70	25	1	450	1
L.003	15	10	250	50					
L.004	1	1	2	16	7200	7200	400	0	000
L.005	1	1	2	16	7200	7200	400	0	000
L.006	1	2	2	17	7200	7200	400	0	000
L.007	1	3	2	18	7200	7200	400	0	000
L.008	1	4	3	21	7200	7200	400	0	000
L.009	1	5	3	22	7200	7200	400	0	000
L.010	1	6	3	23	7200	7200	400	0	000
L.011	1	7	4	26	7200	7200	400	0	000
L.012	1	8	4	27	7200	7200	400	0	000
L.013	1	9	4	28	7200	7200	400	0	000
L.014	1	10	5	31	7200	7200	400	0	000
L.015	1	11	5	32	7200	7200	400	0	000
L.016	1	12	5	33	7200	7200	400	0	000
L.017	1	13	6	36	7200	7200	400	0	000
L.018	1	14	6	37	7200	7200	400	0	000
L.019	1	15	6	38	7200	7200	400	0	000
L.020	2	16	1	1	7200	7200	400	0	000
L.021	2	17	3	24	7200	7200	400	0	000
L.022	2	18	4	29	7200	7200	400	0	000
L.023	2	19	5	34	7200	7200	400	0	000
L.024	2	20	6	39	7200	7200	400	0	000
L.025	3	21	1	2	7200	7200	400	0	000
L.026	3	22	2	20	7200	7200	400	0	000
L.027	3	23	4	30	7200	7200	400	0	000
L.028	3	24	5	35	7200	7200	400	0	000
L.029	3	25	6	40	7200	7200	400	0	000
L.030	4	26	1	3	7200	7200	400	0	000
L.031	4	27	2	16	7200	7200	400	0	000
L.032	4	28	3	21	7200	7200	400	0	000
L.033	4	29	5	31	7200	7200	400	0	000
L.034	4	30	6	36	7200	7200	400	0	000
L.035	5	31	1	4	7200	7200	400	0	000
L.036	5	32	2	17	7200	7200	400	0	000
L.037	5	33	3	22	7200	7200	400	0	000
L.038	5	34	4	27	7200	7200	400	0	000
L.039	5	35	6	37	7200	7200	400	0	000
L.040	6	36	1	4	7200	7200	400	0	000
L.041	6	37	2	18	7200	7200	400	0	000
L.042	6	38	3	22	7200	7200	400	0	000
L.043	6	39	4	28	7200	7200	400	0	000
L.044	6	40	5	32	7200	7200	400	0	000
L.045	6	40	5	32	7200	7200	400	0	000
L.046	6	39	4	28	7200	7200	400	0	000
L.047	6	38	3	22	7200	7200	400	0	000
L.048	6	37	2	18	7200	7200	400	0	000
L.049	6	36	1	4	7200	7200	400	0	000
L.050	5	35	6	37	7200	7200	400	0	000
L.051	5	34	4	27	7200	7200	400	0	000
L.052	5	33	3	22	7200	7200	400	0	000
L.053	5	32	2	17	7200	7200	400	0	000
L.054	5	31	1	4	7200	7200	400	0	000

L.055	2	0	0	0	0	0	0	0		
L.056	2	0	0	0	0	0	0	0		
L.057	3	0	0	0	0	0	0	0		
L.058	3	0	0	0	0	0	0	0		
L.059	4	0	0	0	0	0	0	0		
L.060	4	0	0	0	0	0	0	0		
L.061	5	0	0	0	0	0	0	0		
L.062	5	0	0	0	0	0	0	0		
L.063	6	0	0	0	0	0	0	0		
L.064	6	0	0	0	0	0	0	0		
L.065	1	3	4	5	6	0	0	0		
L.066	1	3	4	5	6	0	0	0		
L.067	1	2	4	5	6	0	0	0		
L.068	1	2	4	5	6	0	0	0		
L.069	1	2	3	5	6	0	0	0		
L.070	1	2	3	5	6	0	0	0		
L.071	1	2	3	4	6	0	0	0		
L.072	1	2	3	4	6	0	0	0		
L.073	1	2	3	4	5	0	0	0		
L.074	1	2	3	4	5	0	0	0		
L.075	0	2	3	4	5	6				
L.076	1	0	1	1	1	1				
L.077	1	1	0	1	1	1				
L.078	1	1	1	0	1	1				
L.079	1	1	1	1	0	1				
L.080	1	1	1	1	1	0				
L.081	11	12	13	14	15	16	17	18	19	20
L.082	1	2	3	4	5	6	7	8	9	10
L.083	25	10	10	10	10	10				
L.084	16	17	18	19	20					
L.085	21	22	23	24	25					
L.086	26	27	28	29	30					
L.087	31	32	33	34	35					
L.088	36	37	38	39	40					
L.089	1	2	3	4	5	6	7	8	9	10
L.090	11	12	0	0	0	0	0	0	0	0
L.091	13	14	0	0	0	0	0	0	0	0
L.092	15	16	0	0	0	0	0	0	0	0
L.093	17	18	0	0	0	0	0	0	0	0
L.094	19	20	0	0	0	0	0	0	0	0
L.095	0	1	3	5	7	9				
L.096	11	0	11	11	11	11				
L.097	13	13	0	13	13	13				
L.098	15	15	15	0	15	15				
L.099	17	17	17	17	0	17				
L.100	19	19	19	19	19	0				
L.101	0	2	4	6	8	10				
L.102	12	0	12	12	12	12				
L.103	14	14	0	14	14	14				
L.104	16	16	16	0	16	16				
L.105	18	18	18	18	0	18				
L.106	20	20	20	20	20	0				

/D I O P D

L.001	20	0250	2	500	8	4000	6	9	16
L.002	500	100	1	60	70	7	2	100	1
L.003	2	5	20	2					
L.004	1	1	3	4	9600	9600	800	6	100
L.005	1	1	3	4	9600	9600	800	6	100
L.006	1	1	3	4	9600	9600	800	6	100
L.007	1	1	3	4	9600	9600	800	6	100
L.008	1	1	3	4	9600	9600	800	6	100
L.009	1	1	3	4	9600	9600	800	6	100
L.010	1	1	3	4	9600	9600	800	6	100
L.011	1	1	3	4	9600	9600	800	6	100
L.012	1	1	3	4	9600	9600	800	6	100
L.013	1	1	3	4	9600	9600	800	6	100
L.014	3	4	1	1	9600	9600	800	6	100
L.015	3	4	1	1	9600	9600	800	6	100
L.016	3	4	1	1	9600	9600	800	6	100
L.017	3	4	1	1	9600	9600	800	6	100
L.018	3	4	1	1	9600	9600	800	6	100
L.019	3	4	1	1	9600	9600	800	6	100
L.020	3	4	1	1	9600	9600	800	6	100
L.021	3	4	1	1	9600	9600	800	6	100
L.022	3	4	1	1	9600	9600	800	6	100
L.023	3	4	1	1	9600	9600	800	6	100
L.024	5	7	1	2	0	0	250	0	0
L.025	2	3	6	9	0	0	250	0	0
L.026	2	3	4	0	0	0	0	0	
L.027	1	0	0	0	0	0	0	0	
L.028	2	0	0	0	0	0	0	0	
L.029	4	5	6	0	0	0	0	0	
L.030	4	5	6	0	0	0	0	0	
L.031	1	3	4	0	0	0	0	0	
L.032	1	2	3	0	0	0	0	0	
L.033	1	2	3	0	0	0	0	0	
L.034	6	0	0	0	0	0	0	0	
L.035	6	0	0	0	0	0	0	0	
L.036	5	0	0	0	0	0	0	0	
L.037	3	4	0	0	0	0	0	0	
L.038	3	4	0	0	0	0	0	0	
L.039	5	0	0	0	0	0	0	0	
L.040	6	0	0	0	0	0	0	0	
L.041	3	4	0	0	0	0	0	0	
L.042	0	2	3	4	4	4			
L.043	1	0	3	4	4	4			
L.044	1	2	0	4	5	6			
L.045	1	2	3	0	5	6			
L.046	3	3	3	4	0	6			
L.047	3	3	3	4	5	0			
L.048	2	1	6	8	7	3	5	4	
L.049	12	13	16	9	10	15	14	11	
L.050	3	2	5	7	3	6			
L.051	1	2							
L.052	3	0							
L.053	4	0							
L.054	5	6							
L.055	7	0							
L.056	8	9							
L.057	1	0	0	0	0				
L.058	6	0	0	0	0				
L.059	2	3	4	5	0				
L.060	7	8	9	10	11				
L.061	15	16	0	0	0				
L.062	12	13	14	0	0				

L.063	0	1	1	1	1	1
L.064	6	0	6	6	6	6
L.065	2	3	0	4	4	4
L.066	7	7	7	0	11	10
L.067	16	16	16	16	0	15
L.068	12	12	12	12	14	0
L.069	0	0	0	0	0	0
L.070	0	0	0	0	0	0
L.071	0	0	0	5	5	5
L.072	8	8	8	0	0	9
L.073	0	0	0	0	0	0
L.074	13	13	13	13	0	0

LINENO	SRCNOD	SRCICP	DSTNOD	DSTICP	SRCPC	DSTCPC	MLNGTH	MAXRVL	NO.MSG
1	2	1	3	4	9600	9600	800	6	100
2	1	1	3	4	9600	9600	800	6	100
3	1	1	3	4	9600	9600	800	6	100
4	1	1	3	4	9600	9600	800	6	100
5	1	1	3	4	9600	9600	800	6	100
6	1	1	3	4	9600	9600	800	6	100
7	1	1	3	4	9600	9600	800	6	100
8	1	1	3	4	9600	9600	800	6	100
9	1	1	3	4	9600	9600	800	6	100
10	1	1	3	4	9600	9600	800	6	100
11	3	4	1	1	9600	9600	800	6	100
12	3	4	1	1	9600	9600	800	6	100
13	3	4	1	1	9600	9600	800	6	100
14	3	4	1	1	9600	9600	800	6	100
15	3	4	1	1	9600	9600	800	6	100
16	3	4	1	1	9600	9600	800	6	100
17	3	4	1	1	9600	9600	800	6	100
18	3	4	1	1	9600	9600	800	6	100
19	3	4	1	1	9600	9600	800	6	100
20	3	4	1	1	9600	9600	800	6	100
INTERNAL PACKET GENERATION									
21	5	7	1	2	0	0	250	0	0
22	2	3	6	9	0	0	250	0	0

PROCESSOR PARTITION MATRIX

2	3	4	0	0	0	0	0
1	0	0	0	0	0	0	0
2	0	0	0	0	0	0	0
4	5	6	0	0	0	0	0
4	5	6	0	0	0	0	0
1	3	4	0	0	0	0	0
1	2	3	0	0	0	0	0
1	2	3	0	0	0	0	0
6	0	0	0	0	0	0	0
6	0	0	0	0	0	0	0
5	0	0	0	0	0	0	0
3	4	0	0	0	0	0	0
3	4	0	0	0	0	0	0
5	0	0	0	0	0	0	0
6	0	0	0	0	0	0	0
3	4	0	0	0	0	0	0

NODE PLOT MATRIX, PARTITIONS

0	2	3	4	4	4
1	0	3	4	4	4
1	2	0	4	5	6
1	2	3	0	5	6
3	3	3	4	0	6
3	3	3	4	5	0

NCP TO NCP CONNECTION

2	1	6	8	7	3	5	4	12	13	16	9	10	15	14	11

PACKET MULTIPLEXING ON BUS

3	2	5	7	3	6

MAPPING: NODE TO ICP

1	2
3	0
4	0
5	6
7	0
8	9

MAPPING:NODE TO NCP

1	0	0	0	0
6	0	0	0	0
2	3	4	5	0
7	8	9	10	11
15	16	0	0	0
12	13	14	0	0

ROUTING DATA: FIRST CHANNEL

0	1	1	1	1	1
6	0	6	6	6	6
2	3	0	4	4	4
7	7	7	0	11	10
16	16	16	16	0	15
12	12	12	12	14	0

ROUTING DATA: SECOND CHANNEL

0	0	0	0	0	0
0	0	0	0	0	0
0	0	0	5	5	5
8	8	8	0	0	9
0	0	0	0	0	0
13	13	13	13	0	0

20	250	2	500	8	4000	6	9	16
500	100	1	60	70	7	2	100	1
2	5	20	2					

APPENDIX C

PARAMETERS FOR NETWORK SIMULATION

Logical Link Data

Number	SRCNOD	SRCICP	DSTNOD	DSTICP
1	1	1	1	7
2	1	2	1	8
3	1	1	2	9
4	1	2	2	10
5	1	3	3	17
6	1	4	3	18
7	1	5	4	25
8	1	6	4	26
9	1	7	5	33
10	1	8	5	34
11	2	9	1	1
12	2	10	1	2
13	2	9	2	15
14	2	10	2	16
15	2	11	3	19
16	2	12	3	20
17	2	13	4	27
18	2	14	4	28
19	2	15	5	35
20	2	16	5	36
21	3	17	1	3
22	3	18	1	4
23	3	17	2	11
24	3	18	2	12

SRCCHC
DSTCHC
7200
BPS

SRCCHC : SOURCE CHANNEL CAPACITY

DSTCHC : DESTINATION CHANNEL CAPACITY

Logical Link Data (Contd.)

Number	SRCNOD	SRCICP	DSTNOP	DSTICP
25	3	19	3	23
26	3	20	3	24
27	3	21	4	29
28	3	22	4	30
29	3	23	5	37
30	3	24	5	38
31	4	25	1	5
32	4	26	1	6
33	4	25	2	13
34	4	26	2	14
35	4	27	3	21
36	4	28	3	22
37	4	29	4	31
38	4	30	4	32
39	4	31	5	39
40	4	32	5	40
41	5	33	1	7
42	5	34	1	8
43	5	33	2	15
44	5	34	2	16
45	5	35	3	23
46	5	36	3	24
47	5	37	4	31
48	5	38	4	32
49	5	39	5	33
50	5	40	5	34

Processor·Partition Matrix

Network	Partition							
Processor	1	2	3	4	5	6	7	8
1	3	5	0	0	0	0	0	0
2	4	0	0	0	0	0	0	0
3	2	0	0	0	0	0	0	0
4	1	2	0	0	0	0	0	0
5	4	0	0	0	0	0	0	0
6	5	0	0	0	0	0	0	0
7	1	3	0	0	0	0	0	0
8	4	5	0	0	0	0	0	0
9	2	0	0	0	0	0	0	0
10	1	0	0	0	0	0	0	0
11	3	0	0	0	0	0	0	0
12	5	0	0	0	0	0	0	0
13	1	3	0	0	0	0	0	0
14	2	4	0	0	0	0	0	0

Packet Multiplexing on Bus

Node	1	2	3	4	5
No Paks MUX	11	10	11	12	10

Mapping: Node to ICP

Node	ICP's							
1	1	2	3	4	5	6	7	8
2	9	10	11	12	13	14	15	16
3	17	18	19	20	21	22	23	24
4	25	26	27	28	29	30	31	32
5	33	34	35	36	37	38	39	40

Mapping: Node to NCP

Node	NCP's							
1	1	2	3	0	-	-	-	-
2	7	8	0	0	-	-	-	-
3	4	5	6	0	-	-	-	-
4	9	10	11	12	-	-	-	-
5	13	14	0	0	-	-	-	-

Node Plot Matrix, Partitions

		DESTINATION NODE				
		1	2	3	4	5
SOURCE NODE	1	0	2	3	4	3
	2	1	0	1	4	4
	3	1	1	0	4	5
	4	1	2	3	0	5
	5	3	4	3	4	0

NCP to NCP connection

Source NCP	1	2	3	4	5	6
Destination NCP	4	10	7	1	11	13

Source NCP	7	8	9	10	11	12
Destination NCP	3	9	8	2	5	14

Source NCP	13	14
Destination NCP	6	12

Route Map: First Channel

PRESENT NODE	DESTINATION NODE 1	2	3	4	5
1	0	3	1	2	1
2	7	0	7	8	8
3	4	4	0	5	6
4	10	9	11	0	12
5	13	14	13	14	0

Network Parameters

N	50	BITLNG	70
NUMBER	-	NOI	12
SCAN	2	MAXCH	1
BUFBLK	500	NOPCKS	450
NSOURC	8	CMAX	1
SGMENT	4000	NMAXIC	8
NONDS	5	NMAXIN	4
NOICPS	40	QUS	250
NONCPS	14	NVC	50
PSZNO	500	SWPROC	0,01
NRDN	100	MUXRT	64000
NRRN	1	TXMAX	0,040
MNOBFS	16	PXMAX	0,030
NPZ	0,0005	NODPRC	0,0005

APPENDIX D

PARAMETERS FOR NODAL SIMULATION

Logical Link Data

Number	SRCNOD	SRCICP	DSTNOD	DSTICP	
1	1	1	2	16	
2	1	2	2	17	
3	1	3	2	18	
4	1	4	3	21	
5	1	5	3	22	
6	1	6	3	23	
7	1	7	4	26	
8	1	8	4	27	
9	1	9	4	28	
10	1	10	5	31	
11	1	11	5	32	SRCCHC
12	1	12	5	33	DSTCHC
13	1	13	6	36	7200 BPS
14	1	14	6	37	
15	1	15	6	38	
16	2	16	1	1	
17	2	17	3	24	
18	2	18	4	29	
19	2	19	5	34	
20	2	20	6	39	
21	3	21	1	2	
22	3	22	2	20	
23	3	23	4	30	
24	3	24	5	35	
25	3	25	6	40	

SRCCHC : SOURCE CHANNEL CAPACITY

DSTCHC : DESTINATION CHANNEL CAPACITY

Logical Link Data (Contd.)

Number	SRCNOD	SRCICP	DSTNOD	DSTICP
26	4	26	1	3
27	4	27	2	16
28	4	28	3	21
29	4	29	5	31
30	4	30	6	36
31	5	31	1	4
32	5	32	2	17
33	5	33	3	22
34	5	34	4	27
35	5	35	6	37
36	6	36	1	4
37	6	37	2	18
38	6	38	3	22
39	6	39	4	28
40	6	40	5	32
41	6	40	5	32
42	6	39	4	28
43	6	38	3	22
44	6	37	2	18
45	6	36	1	4
46	5	35	6	37
47	5	34	4	27
48	5	33	3	22
49	5	32	2	17
50	5	31	1	4

Processor Partition Matrix

Network Processor	Partitions							
	1	2	3	4	5	6	7	8
1	1	0	0	0	0	0	0	0
2	2	0	0	0	0	0	0	0
3	3	0	0	0	0	0	0	0
4	3	0	0	0	0	0	0	0
5	4	0	0	0	0	0	0	0
6	4	0	0	0	0	0	0	0
7	5	0	0	0	0	0	0	0
8	5	0	0	0	0	0	0	0
9	6	0	0	0	0	0	0	0
10	6	0	0	0	0	0	0	0
11	1	3	4	5	6	0	0	0
12	1	3	4	5	6	0	0	0
13	1	2	4	5	6	0	0	0
14	1	2	4	5	6	0	0	0
15	1	2	3	5	6	0	0	0
16	1	2	3	5	6	0	0	0
17	1	2	3	4	6	0	0	0
18	1	2	3	4	6	0	0	0
19	1	2	3	4	5	0	0	0
20	1	2	3	4	5	0	0	0

Packet Multiplexing on Bus

Node	1	2	3	4	5	6
No Pak MUX	25	7	7	7	7	7

Mapping: Node to ICP

Node	ICP's														
1	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
2	16	17	18	19	20	0	0	0	0	0	0	0	0	0	0
3	21	22	23	24	25	0	0	0	0	0	0	0	0	0	0
4	26	27	28	29	30	0	0	0	0	0	0	0	0	0	0
5	31	32	33	34	35	0	0	0	0	0	0	0	0	0	0
6	36	37	38	39	40	0	0	0	0	0	0	0	0	0	0

Mapping: Node to NCP

Node	NCP's									
1	1	2	3	4	5	6	7	8	9	10
2	11	12	0	0	0	0	0	0	0	0
3	13	14	0	0	0	0	0	0	0	0
4	15	16	0	0	0	0	0	0	0	0
5	17	18	0	0	0	0	0	0	0	0
6	19	20	0	0	0	0	0	0	0	0

Node Plot Matrix Partition

		DESTINATION NODE					
		1	2	3	4	5	6
	1	0	2	3	4	5	6
	2	1	0	1	1	1	1
SOURCE	3	1	1	0	1	1	1
NODE	4	1	1	1	0	1	1
	5	1	1	1	1	0	1
	6	1	1	1	1	1	0

NCP to NCP Connection

SOURCE NCP	1	2	3	4	5	6	7	8	9	10
DEST NCP	11	12	13	14	15	16	17	18	19	20

SOURCE NCP	11	12	13	14	15	16	17	18	19	20
DEST NCP	1	2	3	4	5	6	7	8	9	10

Routing Map: First Channel

PRESENT NODE \ DESTINATION NODE	1	2	3	4	5	6
1	0	1	3	5	7	9
2	11	0	11	11	11	11
3	13	13	0	13	13	13
4	15	15	15	0	15	15
5	17	17	17	17	0	17
6	19	19	19	19	19	0

Routing Map: Second Channel

PRESENT NODE \ DESTINATION NODE	1	2	3	4	5	6
1	0	2	4	6	8	10
2	12	0	12	12	12	12
3	14	14	0	14	14	14
4	16	16	16	0	16	16
5	18	18	18	18	0	18
6	20	20	20	20	20	0

Network Parameters

N	50	BITLNG	70
NUMBER	-	NOI	25
SCAN	2	MAXCH	2
BUFBLK	500	NOPCKS	450
NSOURC	8	CMAX	1
SGMENT	4000	NMAXIC	15
NONDS	6	NMAXIN	10
NOICPS	40	QUS	250
NONCPS	20	NVC	50
PSZNO	500	SWPROC	0,01
NRDN	100	MUXRT	640000
NRRN	1	TXMAX	0,040
MNORFS	16	PXMAX	0,030
NPZ	0,0005	NODPRL	0,0005

APPENDIX E

SIMULATION RESULTS

This appendix contains the tables of all simulation performance results for the nodal and network simulations.

CONTENTS

NETWORK SIMULATION: EXTENDED RUNS -
TABLES E2 - E12

NETWORK SIMULATION: DELAY VALUES -
TABLES E13 - E15

NODAL SIMULATION: DELAY VALUES -
TABLES E16 - E19

NETWORK AND NODAL SIMULATION: RECORDED
THROUGHPUT - TABLES E20 - E21

NETWORK SIMULATION: PRIORITY VALUE VARIATION
TABLES E22 - E23

NODAL SIMULATION: RETRM INTERVAL VARIATION
TABLES E24 - E26

NODAL SIMULATION: BUS RATE & ALG EXEC
TABLES E27 - E29

NETWORK SIMULATION: ALG EXEC TIME
TABLES E30 - E31

NODAL SIMULATION: SINGLE CHANNEL CONNECTION
TABLES E32 - E33

TABLE E1 APPENDIX CONTENTS

NETWORK SIMULATION: EXTENDED RUNS

CYCLE AND SIMULATED TIME VALUES (SECONDS)

CYCLES	(2000)	(4000)	(6000)	(8000)	(10000)	(12000)	(14000)	(16000)
INPUT LEVEL IS 50 PACKETS/SEC								
PRIORITY(ENTER) = 1 PRIORITY(TRANSIT) = 5	5.85	11.31	16.92	22.52	28.38	34.50	40.38	46.23
PRIORITY(ENTER) = 5 PRIORITY(TRANSIT) = 1	5.85	11.31	16.92	22.52	28.38	34.50	40.38	46.23
INPUT LEVEL IS 525 PACKETS/SEC								
PRIORITY(ENTER) = 1 PRIORITY(TRANSIT) = 5	0.73	1.37	2.01	2.68	3.34	4.01	4.63	5.08
PRIORITY(ENTER) = 5 PRIORITY(TRANSIT) = 1	0.72	1.37	1.98	2.65	3.33	4.02	4.72	5.32
INPUT LEVEL IS 625 PACKETS/SEC								
PRIORITY(ENTER) = 1 PRIORITY(TRANSIT) = 5	0.62	1.16	1.74	2.31	2.91	3.50	4.05	4.56
PRIORITY(ENTER) = 5 PRIORITY(TRANSIT) = 1	0.60	1.18	1.76	2.36	2.93	3.51	4.01	4.50
INPUT LEVEL IS 750 PACKETS/SEC								
PRIORITY(ENTER) = 1 PRIORITY(TRANSIT) = 5	0.54	1.02	1.50	1.98	2.49	3.00	3.42	3.76
PRIORITY(ENTER) = 5 PRIORITY(TRANSIT) = 1	0.54	1.02	1.51	2.02	2.50	2.95	3.32	3.64
INPUT LEVEL IS 835 PACKETS/SEC								
PRIORITY(ENTER) = 1 PRIORITY(TRANSIT) = 5	0.50	0.96	1.40	1.78	2.20	2.59	2.92	3.25
PRIORITY(ENTER) = 5 PRIORITY(TRANSIT) = 1	0.50	0.96	1.42	1.88	2.33	2.79	3.17	3.55

TABLE E-2

NETWORK SIMULATION: EXTENDED RUNS

INPUT LEVEL IS 50 PACKETS/SEC

CYCLES	TOTAL DELAY MEAN	TOTAL DELAY DEV	ENTRY DELAY MEAN	ENTRY DELAY DEV	TRANSIT DELAY MEAN	THROUGHPUT PCKS/SEC
			MILLISECONDS			
PRIORITY(ENTER) = 1			PRIORITY(TRANSIT) = 5			
2000	31.43	17.17	11.43	2.33	20.00	49
4000	31.59	16.32	11.42	2.26	20.17	50
6000	31.02	16.38	11.51	2.33	19.51	51
8000	31.16	16.07	11.54	2.36	19.62	51
10000	31.19	15.81	11.51	2.34	19.68	50
12000	31.09	15.82	11.50	2.34	19.59	49
14000	31.01	15.67	11.53	2.38	19.48	49
16000	31.65	15.67	11.52	2.36	19.53	50
PRIORITY(ENTER) = 5			PRIORITY(TRANSIT) = 1			
2000	31.43	17.16	11.42	2.30	20.01	49
4000	31.59	16.32	11.41	2.22	20.18	50
6000	31.35	16.62	11.48	2.29	19.87	51
8000	31.58	16.68	11.49	2.26	20.09	50
10000	31.71	16.60	11.54	2.34	20.17	50
12000	31.53	17.04	11.51	2.31	20.01	50
14000	31.60	17.07	11.58	2.45	20.02	50
16000	31.77	17.05	11.60	2.45	20.17	50

BUS UTILIZATION FACTORS

CYCLES	NODAL NUMBERS (1)	(2)	(3)	(4)	(5)
PRIORITY(ENTER) = 1			PRIORITY(TRANSIT) = 5		
2000	0.02	0.01	0.02	0.01	0.01
4000	0.02	0.01	0.02	0.02	0.01
6000	0.02	0.01	0.02	0.02	0.01
8000	0.02	0.01	0.02	0.02	0.01
10000	0.02	0.01	0.02	0.02	0.01
12000	0.02	0.01	0.02	0.02	0.01
14000	0.02	0.01	0.02	0.02	0.01
16000	0.02	0.01	0.02	0.02	0.01
2000	0.02	0.01	0.02	0.01	0.01
4000	0.02	0.01	0.02	0.02	0.01
6000	0.02	0.01	0.02	0.02	0.01
8000	0.02	0.01	0.02	0.02	0.01
10000	0.02	0.01	0.02	0.02	0.01
12000	0.02	0.01	0.02	0.02	0.01
14000	0.02	0.01	0.02	0.02	0.01
16000	0.02	0.01	0.02	0.02	0.01

TABLE E-3

NETWORK SIMULATION: EXTENDED RUNS

LINE UTILIZATION FACTORS

CHANNELS	(2000)	(4000)	(6000)	CYCLES (8000)	(10000)	50 PACKETS/SEC (1200)	(14000)	(16000)
PRIORITY(ENTER) = 1 PRIORITY(TRANSIT) = 5								
(1)	0.06	0.05	0.05	0.05	0.05	0.05	0.05	0.05
(2)	0.01	0.01	0.01	0.02	0.02	0.02	0.02	0.02
(3)	0.03	0.03	0.03	0.03	0.03	0.03	0.03	0.03
(4)	0.07	0.05	0.05	0.05	0.05	0.05	0.05	0.05
(5)	0.02	0.02	0.02	0.02	0.02	0.02	0.02	0.02
(6)	0.04	0.04	0.04	0.04	0.04	0.03	0.03	0.03
(7)	0.03	0.02	0.03	0.03	0.03	0.03	0.03	0.03
(8)	0.03	0.03	0.03	0.03	0.04	0.04	0.03	0.04
(9)	0.04	0.04	0.04	0.03	0.03	0.03	0.03	0.03
(10)	0.02	0.01	0.02	0.02	0.02	0.02	0.02	0.02
(11)	0.02	0.02	0.01	0.02	0.02	0.02	0.02	0.01
(12)	0.03	0.05	0.04	0.04	0.04	0.04	0.04	0.04
(13)	0.04	0.04	0.04	0.04	0.03	0.03	0.03	0.03
(14)	0.03	0.04	0.04	0.03	0.03	0.03	0.03	0.03
PRIORITY(ENTER) = 5 PRIORITY(TRANSIT) = 1								
(1)	0.06	0.05	0.06	0.05	0.05	0.05	0.05	0.05
(2)	0.01	0.01	0.01	0.01	0.02	0.02	0.02	0.02
(3)	0.03	0.03	0.03	0.03	0.03	0.03	0.04	0.04
(4)	0.07	0.05	0.05	0.05	0.05	0.05	0.05	0.05
(5)	0.02	0.02	0.02	0.02	0.02	0.02	0.02	0.02
(6)	0.04	0.04	0.04	0.03	0.03	0.04	0.04	0.04
(7)	0.03	0.02	0.03	0.03	0.03	0.03	0.03	0.03
(8)	0.03	0.03	0.03	0.03	0.04	0.03	0.04	0.04
(9)	0.04	0.04	0.04	0.04	0.04	0.03	0.03	0.04
(10)	0.02	0.01	0.01	0.02	0.01	0.01	0.02	0.02
(11)	0.02	0.02	0.02	0.01	0.02	0.02	0.02	0.02
(12)	0.03	0.05	0.04	0.04	0.04	0.04	0.04	0.04
(13)	0.04	0.04	0.04	0.04	0.04	0.03	0.03	0.03
(14)	0.03	0.04	0.03	0.03	0.03	0.03	0.03	0.03

TABLE E-4

NETWORK SIMULATION: EXTENDED RUNS

INPUT LEVEL IS 625 PACKETS/SEC

CYCLES	TOTAL DELAY MEAN	TOTAL DELAY DEV	ENTRY DELAY MEAN	ENTRY DELAY DEV	TRANSIT DELAY MEAN	THROUGHPUT
			MILLISECONDS			PCKS/SEC
PRIORITY(ENTER) = 1			PRIORITY(TRANSIT) = 5			
2000	46.67	20.71	20.87	8.82	25.80	453
4000	48.38	23.23	21.06	10.02	27.32	497
6000	48.62	23.84	20.89	9.55	27.73	509
8000	49.16	24.57	20.95	9.42	28.21	512
10000	49.12	24.65	20.66	9.06	28.46	513
12000	49.55	25.30	20.63	9.03	28.92	517
14000	51.06	29.32	20.66	8.93	30.40	518
16000	51.83	28.74	20.57	8.80	31.26	518
PRIORITY(ENTER) = 5			PRIORITY(TRANSIT) = 1			
2000	47.25	25.26	17.20	4.96	30.05	455
4000	48.10	26.17	17.73	5.61	30.37	496
6000	50.60	27.62	18.07	5.66	32.53	511
8000	50.47	28.16	18.17	5.77	32.30	511
10000	50.09	27.81	18.08	5.76	32.01	509
12000	50.45	28.10	18.04	5.85	32.41	508
14000	49.69	27.85	17.99	5.80	31.70	505
16000	51.41	30.64	17.94	5.71	33.47	506

BUS UTILIZATION FACTORS

CYCLES	NODAL NUMBERS (1)	(2)	(3)	(4)	(5)
PRIORITY(ENTER) = 1			PRIORITY(TRANSIT) = 5		
2000	0.15	0.13	0.15	0.16	0.12
4000	0.17	0.13	0.17	0.16	0.13
6000	0.17	0.13	0.18	0.17	0.13
8000	0.17	0.13	0.17	0.17	0.13
10000	0.17	0.13	0.17	0.17	0.14
12000	0.17	0.13	0.17	0.17	0.14
14000	0.17	0.13	0.18	0.17	0.14
16000	0.17	0.13	0.17	0.17	0.14
PRIORITY(ENTER) = 5			PRIORITY(TRANSIT) =1		
2000	0.15	0.13	0.14	0.16	0.12
4000	0.16	0.13	0.16	0.17	0.13
6000	0.17	0.14	0.16	0.17	0.14
8000	0.17	0.14	0.17	0.17	0.13
10000	0.17	0.14	0.16	0.17	0.14
12000	0.17	0.14	0.17	0.17	0.13
14000	0.17	0.13	0.16	0.17	0.13
16000	0.16	0.14	0.16	0.17	0.13

TABLE E-5

NETWORK SIMULATION: EXTENDED RUNS

INPUT LEVEL IS 525 PACKETS/SEC LINE UTILIZATION FACTORS

CHANNELS	CYCLES (2000)	(4000)	(6000)	(8000)	(10000)	(12000)	(14000)	(16000)
PRIORITY(ENTER) = 1 PRIORITY(TRANSIT) = 5								
(1)	0.41	0.51	0.49	0.52	0.53	0.55	0.55	0.56
(2)	0.08	0.12	0.17	0.16	0.16	0.17	0.18	0.18
(3)	0.37	0.38	0.34	0.35	0.34	0.34	0.37	0.37
(4)	0.50	0.50	0.50	0.50	0.50	0.51	0.51	0.51
(5)	0.18	0.17	0.19	0.19	0.19	0.19	0.20	0.20
(6)	0.26	0.30	0.31	0.33	0.35	0.34	0.34	0.35
(7)	0.36	0.33	0.34	0.32	0.34	0.37	0.39	0.39
(8)	0.28	0.26	0.30	0.34	0.37	0.35	0.35	0.38
(9)	0.35	0.30	0.32	0.32	0.32	0.35	0.37	0.38
(10)	0.16	0.20	0.18	0.18	0.18	0.18	0.18	0.18
(11)	0.16	0.19	0.21	0.19	0.18	0.18	0.21	0.22
(12)	0.35	0.30	0.31	0.31	0.35	0.35	0.35	0.34
(13)	0.33	0.33	0.33	0.33	0.33	0.34	0.37	0.37
(14)	0.29	0.31	0.34	0.35	0.34	0.34	0.33	0.36
PRIORITY(ENTER) =5 PRIORITY(TRANSIT) = 1								
(1)	0.44	0.43	0.45	0.45	0.43	0.46	0.46	0.45
(2)	0.14	0.17	0.17	0.16	0.16	0.16	0.17	0.17
(3)	0.29	0.30	0.34	0.34	0.32	0.32	0.31	0.34
(4)	0.48	0.49	0.54	0.54	0.51	0.52	0.52	0.53
(5)	0.18	0.19	0.19	0.19	0.18	0.17	0.17	0.18
(6)	0.24	0.33	0.31	0.31	0.31	0.31	0.31	0.33
(7)	0.45	0.37	0.36	0.37	0.34	0.33	0.33	0.36
(8)	0.31	0.31	0.35	0.35	0.34	0.34	0.32	0.33
(9)	0.26	0.29	0.34	0.33	0.36	0.36	0.34	0.35
(10)	0.11	0.16	0.16	0.18	0.19	0.17	0.17	0.19
(11)	0.18	0.19	0.18	0.20	0.23	0.22	0.23	0.24
(12)	0.47	0.41	0.44	0.39	0.39	0.38	0.37	0.38
(13)	0.24	0.31	0.36	0.37	0.38	0.37	0.37	0.37
(14)	0.30	0.27	0.28	0.27	0.32	0.33	0.32	0.33

TABLE E-6

NETWORK SIMULATION: EXTENDED RUNS

INPUT LEVEL IS 625 PACKETS/SEC

CYCLES	TOTAL DELAY MEAN	TOTAL DELAY DEV	ENTRY DELAY MEAN	ENTRY DELAY DEV	TRANSIT DELAY MEAN	THROUGHPUT
	MILLISECONDS					PCKS/SEC
PRIORITY(ENTER) = 1			PRIORITY(TRANSIT) =5			
2000	52.43	32.56	24.80	14.97	27.63	557
4000	53.79	31.07	23.16	12.93	30.63	611
6000	53.07	29.83	22.87	11.65	30.20	623
8000	52.81	28.79	22.76	11.38	30.05	624
10000	52.06	27.84	22.63	11.44	29.43	617
12000	52.98	29.69	22.67	11.21	30.31	616
14000	53.07	29.63	22.76	11.47	30.31	623
16000	53.85	30.11	23.09	13.02	30.76	618
PRIORITY(ENTER) = 5			PRIORITY(TRANSIT) = 1			
2000	50.01	28.58	17.93	5.42	32.08	554
4000	51.07	29.46	18.51	6.49	32.56	596
6000	51.85	29.61	19.46	5.45	32.39	604
8000	51.70	29.60	19.08	6.34	32.62	602
10000	51.60	29.49	19.14	6.26	32.46	607
12000	52.88	31.28	19.22	6.25	33.66	603
14000	55.01	37.16	19.50	6.78	33.51	605
16000	58.38	43.80	19.63	6.99	38.78	605

BUS UTILIZATION FACTORS

CYCLES	NODAL NUMBERS (1)	(2)	(3)	(4)	(5)
PRIORITY(ENTER) = 1			PRIORITY(TRANSIT) = 5		
2000	0.19	0.15	0.19	0.18	0.14
4000	0.19	0.15	0.20	0.21	0.16
6000	0.19	0.15	0.21	0.21	0.16
8000	0.19	0.15	0.21	0.21	0.16
10000	0.19	0.15	0.20	0.21	0.16
12000	0.20	0.15	0.20	0.20	0.16
14000	0.20	0.15	0.20	0.20	0.16
16000	0.20	0.15	0.20	0.20	0.16
PRIORITY(ENTER) = 5			PRIORITY(TRANSIT) = 1		
2000	0.16	0.17	0.17	0.20	0.15
4000	0.19	0.17	0.19	0.19	0.16
6000	0.19	0.17	0.19	0.19	0.16
8000	0.18	0.17	0.19	0.20	0.16
10000	0.19	0.17	0.19	0.20	0.16
12000	0.19	0.17	0.19	0.20	0.16
14000	0.19	0.17	0.19	0.20	0.16
16000	0.19	0.17	0.19	0.20	0.16

TABLE E-7

NETWORK SIMULATION: EXTENDED RUNS

INPUT LEVEL IS 625 PACKETS/SEC LINE UTILIZATION FACTORS

CHANNELS	CYCLES (2000)	(4000)	(6000)	(8000)	(10000)	(12000)	(14000)	(16000)
PRIORITY(ENTER) = 1	PRIORITY(TRANSIT) = 5							
(1)	0.68	0.61	0.59	0.56	0.62	0.62	0.62	0.66
(2)	0.09	0.17	0.15	0.21	0.22	0.21	0.24	0.26
(3)	0.42	0.45	0.46	0.43	0.40	0.41	0.41	0.44
(4)	0.61	0.64	0.63	0.61	0.59	0.60	0.61	0.63
(5)	0.22	0.23	0.24	0.24	0.23	0.23	0.22	0.25
(6)	0.38	0.38	0.40	0.40	0.38	0.42	0.43	0.47
(7)	0.47	0.48	0.46	0.45	0.45	0.43	0.42	0.45
(8)	0.36	0.37	0.40	0.41	0.42	0.41	0.41	0.42
(9)	0.33	0.34	0.35	0.37	0.36	0.36	0.34	0.36
(10)	0.11	0.15	0.15	0.18	0.19	0.20	0.21	0.22
(11)	0.25	0.23	0.27	0.26	0.26	0.24	0.23	0.24
(12)	0.35	0.41	0.46	0.46	0.48	0.44	0.43	0.43
(13)	0.31	0.35	0.36	0.38	0.35	0.36	0.36	0.41
(14)	0.34	0.51	0.50	0.46	0.44	0.41	0.40	0.43
PRIORITY(ENTER) = 5	PRIORITY(TRANSIT) = 1							
(1)	0.35	0.46	0.51	0.49	0.50	0.55	0.61	0.61
(2)	0.19	0.21	0.17	0.16	0.19	0.18	0.19	0.20
(3)	0.45	0.42	0.34	0.33	0.34	0.37	0.40	0.39
(4)	0.55	0.57	0.55	0.53	0.55	0.59	0.60	0.61
(5)	0.21	0.24	0.26	0.23	0.23	0.25	0.26	0.25
(6)	0.25	0.40	0.41	0.35	0.38	0.37	0.42	0.44
(7)	0.47	0.44	0.45	0.42	0.41	0.43	0.45	0.45
(8)	0.35	0.37	0.42	0.42	0.44	0.43	0.41	0.41
(9)	0.48	0.44	0.45	0.45	0.43	0.43	0.44	0.43
(10)	0.19	0.18	0.21	0.21	0.21	0.20	0.20	0.19
(11)	0.24	0.21	0.23	0.26	0.27	0.28	0.28	0.28
(12)	0.46	0.41	0.39	0.39	0.41	0.39	0.38	0.39
(13)	0.37	0.43	0.44	0.40	0.37	0.39	0.41	0.42
(14)	0.43	0.39	0.41	0.44	0.42	0.42	0.44	0.43

TABLE E-8

NETWORK SIMULATION: EXTENDED RUNS

INPUT LEVEL IS 750 PACKETS/SEC

CYCLES	TOTAL DELAY MEAN	TOTAL DELAY DEV	ENTRY DELAY MEAN	ENTRY DELAY DEV	TRANSIT DELAY MEAN	THROUGHPUT PCKS/SEC
	MILLISECONDS					
PRIORITY(ENTER) = 1			PRIORITY(TRANSIT) = 5			
2000	53.62	30.51	24.06	13.93	29.56	637
4000	58.29	30.59	26.38	15.12	31.91	696
6000	60.99	36.52	28.66	21.84	32.33	710
8000	63.02	37.70	29.65	21.83	33.37	724
10000	63.91	38.57	29.67	21.51	34.24	732
12000	63.41	37.80	28.93	20.27	34.48	730
14000	65.14	46.13	28.93	19.84	36.30	726
16000	69.53	56.57	28.77	20.00	40.76	718
PRIORITY(ENTER) = 5			PRIORITY(TRANSIT) = 1			
2000	54.29	33.80	20.67	8.79	33.62	606
4000	64.82	46.60	21.91	9.30	42.91	693
6000	67.44	48.51	22.68	10.64	44.76	714
8000	69.73	54.59	23.10	11.65	46.63	715
10000	72.13	57.80	23.07	11.52	49.06	723
12000	73.47	63.71	23.00	11.33	50.47	725
14000	74.90	64.66	23.08	11.28	51.82	718
16000	78.31	69.60	23.04	11.09	55.27	708

BUS UTILIZATION FACTORS

CYCLES	NODAL NUMBERS (1)	(2)	(3)	(4)	(5)
PRIORITY(ENTER) = 1			PRIORITY(TRANSIT) = 5		
2000	0.22	0.19	0.20	0.21	0.17
4000	0.23	0.20	0.22	0.23	0.19
6000	0.23	0.20	0.23	0.24	0.20
8000	0.23	0.20	0.23	0.24	0.21
10000	0.23	0.20	0.23	0.24	0.21
12000	0.23	0.20	0.23	0.24	0.21
14000	0.23	0.20	0.23	0.24	0.21
16000	0.23	0.20	0.23	0.24	0.20
PRIORITY(ENTER) = 5			PRIORITY(TRANSIT) = 1		
2000	0.21	0.18	0.21	0.21	0.17
4000	0.23	0.20	0.23	0.23	0.20
6000	0.23	0.20	0.24	0.24	0.20
8000	0.23	0.20	0.24	0.24	0.19
10000	0.23	0.20	0.24	0.24	0.19
12000	0.23	0.19	0.24	0.24	0.20
14000	0.23	0.19	0.23	0.25	0.19
16000	0.23	0.19	0.23	0.25	0.19

TABLE E-9

NETWORK SIMULATION: EXTENDED RUNS

INPUT LEVEL IS 750 PACKETS/SEC LINE UTILIZATION FACTORS

CHANNELS	CYCLES (2000)	(4000)	(6000)	(8000)	(10000)	(12000)	(14000)	(16000)
PRIORITY(ENTER) = 1 PRIORITY(TRANSIT) = 5								
(1)	0.52	0.57	0.61	0.65	0.63	0.63	0.67	0.70
(2)	0.24	0.25	0.25	0.24	0.25	0.24	0.26	0.29
(3)	0.54	0.58	0.59	0.48	0.48	0.53	0.52	0.55
(4)	0.56	0.64	0.64	0.64	0.65	0.65	0.69	0.72
(5)	0.24	0.21	0.26	0.23	0.24	0.22	0.23	0.26
(6)	0.38	0.46	0.52	0.59	0.59	0.58	0.58	0.60
(7)	0.58	0.50	0.49	0.49	0.47	0.49	0.52	0.56
(8)	0.51	0.53	0.56	0.57	0.56	0.54	0.54	0.59
(9)	0.45	0.53	0.48	0.46	0.49	0.52	0.55	0.60
(10)	0.18	0.24	0.27	0.28	0.27	0.27	0.28	0.30
(11)	0.23	0.22	0.21	0.22	0.24	0.22	0.26	0.30
(12)	0.46	0.55	0.57	0.57	0.56	0.55	0.58	0.62
(13)	0.35	0.40	0.43	0.49	0.49	0.49	0.52	0.57
(14)	0.36	0.42	0.44	0.47	0.50	0.52	0.56	0.60
PRIORITY(ENTER) = 5 PRIORITY(TRANSIT) = 1								
(1)	0.62	0.67	0.69	0.72	0.76	0.80	0.82	0.83
(2)	0.23	0.24	0.23	0.25	0.30	0.30	0.32	0.36
(3)	0.48	0.48	0.46	0.47	0.48	0.44	0.50	0.54
(4)	0.60	0.69	0.69	0.74	0.76	0.74	0.77	0.79
(5)	0.27	0.26	0.28	0.24	0.27	0.26	0.31	0.36
(6)	0.40	0.52	0.50	0.49	0.47	0.55	0.60	0.63
(7)	0.66	0.56	0.57	0.56	0.56	0.54	0.59	0.63
(8)	0.36	0.44	0.53	0.52	0.53	0.57	0.61	0.65
(9)	0.39	0.49	0.49	0.51	0.51	0.53	0.55	0.59
(10)	0.10	0.24	0.22	0.26	0.25	0.26	0.28	0.32
(11)	0.28	0.26	0.24	0.25	0.25	0.26	0.29	0.35
(12)	0.49	0.49	0.52	0.54	0.52	0.56	0.56	0.58
(13)	0.41	0.44	0.44	0.41	0.40	0.43	0.49	0.54
(14)	0.38	0.45	0.53	0.52	0.54	0.56	0.56	0.59

TABLE E-10

NETWORK SIMULATION: EXTENDED RUNS

INPUT LEVEL IS 835 PACKETS/SEC

CYCLES	TOTAL DELAY MEAN	TOTAL DELAY DEV	ENTRY DELAY MEAN	ENTRY DELAY DEV	TRANSIT DELAY MEAN	THROUGHPUT
	MILLISECONDS					PCKS/SEC
PRIORITY(ENTER) =1			PRIORITY(TRANSIT) =5			
2000	58.95	35.31	28.43	21.19	30.52	656
4000	71.19	53.87	34.23	33.24	36.96	749
6000	78.15	61.75	37.38	39.43	40.77	772
8000	82.03	67.03	38.24	40.88	43.82	787
10000	83.61	70.43	39.50	45.58	44.11	790
12000	86.95	81.05	42.35	55.24	44.60	771
14000	93.49	94.09	44.41	64.87	49.08	756
16000	101.03	108.55	46.68	73.39	54.35	741
PRIORITY(ENTER) =5			PRIORITY(TRANSIT) = 1			
2000	54.23	33.36	21.28	8.28	32.95	696
4000	66.91	56.93	23.71	11.85	43.20	762
6000	71.64	60.22	24.53	13.03	47.11	775
8000	76.07	66.46	25.62	14.63	50.45	777
10000	80.36	73.12	26.60	17.07	53.76	789
12000	83.17	77.52	26.14	16.30	57.03	788
14000	83.94	79.68	26.33	16.08	57.61	782
16000	91.19	91.33	26.49	16.22	64.70	780

BUS UTILIZATION FACTORS

CYCLES	NODAL NUMBERS (1)	(2)	(3)	(4)	(5)
PRIORITY(ENTER) = 1			PRIORITY(TRANSIT) = 5		
2000	0.21	0.20	0.21	0.24	0.20
4000	0.23	0.22	0.24	0.25	0.21
6000	0.24	0.21	0.26	0.26	0.21
8000	0.26	0.21	0.26	0.26	0.22
10000	0.26	0.22	0.25	0.26	0.21
12000	0.25	0.21	0.25	0.26	0.21
14000	0.25	0.21	0.25	0.26	0.21
16000	0.25	0.21	0.24	0.26	0.21
PRIORITY(ENTER) = 5			PRIORITY(TRANSIT) = 1		
2000	0.22	0.19	0.23	0.24	0.19
4000	0.24	0.20	0.26	0.25	0.20
6000	0.25	0.21	0.26	0.26	0.20
8000	0.25	0.22	0.26	0.26	0.20
10000	0.25	0.22	0.26	0.26	0.21
12000	0.25	0.21	0.26	0.26	0.21
14000	0.25	0.21	0.26	0.26	0.21
16000	0.25	0.21	0.26	0.26	0.21

TABLE E-11

NETWORK SIMULATION: EXTENDED RUNS

INPUT LEVEL IS 835 PACKETS/SEC LINE UTILIZATION FACTORS

CHANNELS	CYCLES (2000)	(4000)	(6000)	(8000)	(10000)	(12000)	(14000)	(16000)
PRIORITY(ENTER) = 1 PRIORITY(TRANSIT) = 5								
(1)	0.64	0.75	0.81	0.82	0.86	0.88	0.89	0.90
(2)	0.18	0.15	0.21	0.26	0.28	0.27	0.30	0.36
(3)	0.54	0.55	0.51	0.55	0.59	0.63	0.67	0.70
(4)	0.76	0.81	0.86	0.88	0.89	0.91	0.92	0.93
(5)	0.28	0.33	0.32	0.28	0.27	0.33	0.37	0.41
(6)	0.38	0.43	0.47	0.50	0.52	0.56	0.61	0.63
(7)	0.57	0.64	0.61	0.62	0.66	0.71	0.74	0.77
(8)	0.51	0.52	0.60	0.65	0.62	0.61	0.65	0.69
(9)	0.56	0.54	0.60	0.62	0.63	0.65	0.68	0.71
(10)	0.28	0.23	0.21	0.27	0.28	0.27	0.28	0.32
(11)	0.27	0.28	0.28	0.27	0.30	0.33	0.39	0.42
(12)	0.56	0.52	0.58	0.64	0.62	0.66	0.69	0.73
(13)	0.42	0.51	0.53	0.55	0.57	0.60	0.65	0.68
(14)	0.59	0.52	0.60	0.61	0.61	0.66	0.70	0.73
PRIORITY(ENTER) = 5 PRIORITY(TRANSIT) = 1								
(1)	0.62	0.70	0.73	0.72	0.74	0.74	0.77	0.79
(2)	0.22	0.26	0.21	0.22	0.22	0.23	0.21	0.22
(3)	0.44	0.46	0.49	0.48	0.48	0.50	0.55	0.60
(4)	0.70	0.67	0.67	0.72	0.76	0.77	0.80	0.82
(5)	0.30	0.37	0.35	0.34	0.33	0.32	0.32	0.33
(6)	0.34	0.48	0.45	0.45	0.48	0.49	0.54	0.57
(7)	0.57	0.61	0.60	0.57	0.57	0.57	0.60	0.63
(8)	0.47	0.46	0.49	0.52	0.51	0.54	0.55	0.60
(9)	0.49	0.57	0.62	0.66	0.64	0.63	0.67	0.71
(10)	0.25	0.23	0.26	0.30	0.33	0.33	0.31	0.31
(11)	0.25	0.24	0.25	0.24	0.25	0.24	0.28	0.26
(12)	0.56	0.45	0.47	0.50	0.51	0.51	0.52	0.55
(13)	0.37	0.35	0.43	0.45	0.47	0.50	0.54	0.57
(14)	0.58	0.65	0.60	0.61	0.61	0.58	0.60	0.63

TABLE E-12

DELAY VALUES FOR NETWORK SIMULATION IN MILLISECONDS

	TOTAL DELAY MEAN	TOTAL DELAY $\sqrt{VAR}$	ENTRY DELAY MEAN	ENTRY DELAY $\sqrt{VAR}$	TRANSIT DELAY MEAN
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5		100 PACKETS/SEC
RUN ONE	33.21	16.71	12.77	3.66	20.44
RUN TWO	34.61	17.94	12.94	3.65	21.67
RUN THREE	33.33	16.91	12.45	3.24	20.88
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1		100 PACKETS/SEC
RUN ONE	33.30	16.25	12.63	3.34	20.67
RUN TWO	34.16	17.19	12.60	3.37	21.56
RUN THREE	33.21	17.16	12.49	3.11	20.72
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5		200 PACKETS/SEC
RUN ONE	36.63	17.27	15.20	4.90	21.43
RUN TWO	39.38	18.91	14.91	4.52	24.47
RUN THREE	38.09	19.03	14.90	4.63	23.19
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1		200 PACKETS/SEC
RUN ONE	36.07	18.00	14.54	4.01	21.53
RUN TWO	40.28	19.95	14.73	4.21	25.55
RUN THREE	36.53	19.33	14.47	4.05	22.06
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5		500 PACKETS/SEC
RUN ONE	47.76	22.35	20.49	7.76	27.27
RUN TWO	46.76	22.22	19.47	6.83	27.29
RUN THREE	47.48	23.33	19.76	7.79	27.72
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1		500 PACKETS/SEC
RUN ONE	50.76	31.79	18.40	6.03	32.36
RUN TWO	49.51	28.14	17.90	5.28	31.61
RUN THREE	48.54	26.26	17.88	5.99	30.66
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5		625 PACKETS/SEC
RUN ONE	60.42	43.15	26.05	20.18	34.37
RUN TWO	63.65	40.50	26.36	17.11	40.29
RUN THREE	53.64	30.81	22.73	12.07	30.91
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1		625 PACKETS/SEC
RUN ONE	60.36	43.42	20.45	7.98	39.91
RUN TWO	63.02	42.53	20.95	9.65	42.07
RUN THREE	52.31	30.26	18.81	5.94	33.50
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5		825 PACKETS/SEC
RUN ONE	96.83	86.64	61.18	73.82	35.65
RUN TWO	117.31	91.51	73.63	61.74	43.68
RUN THREE	89.03	73.35	53.87	60.87	35.16
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1		835 PACKETS/SEC
RUN ONE	94.78	97.30	52.53	58.81	42.25
RUN TWO	94.68	98.44	49.26	54.86	45.42
RUN THREE	83.03	76.86	40.24	40.44	42.79

TABLE E-13

NETWORK SIMULATION: BUS UTILIZATION FACTORS

NODAL NUMBERS	(1)	(2)	(3)	(4)	(5)
	INPUT LEVEL IS 100 PACKETS/SEC				
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5		
RUN ONE	0.03	0.03	0.03	0.03	0.03
RUN TWO	0.03	0.03	0.03	0.03	0.03
RUN THREE	0.03	0.03	0.03	0.03	0.03
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1		
RUN ONE	0.03	0.03	0.03	0.03	0.03
RUN TWO	0.03	0.03	0.03	0.03	0.03
RUN THREE	0.03	0.03	0.03	0.03	0.03
	INPUT LEVEL IS 200 PACKETS/SEC				
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5		
RUN ONE	0.07	0.05	0.06	0.06	0.05
RUN TWO	0.07	0.06	0.07	0.06	0.05
RUN THREE	0.06	0.05	0.07	0.07	0.05
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1		
RUN ONE	0.06	0.05	0.06	0.06	0.05
RUN TWO	0.07	0.05	0.07	0.07	0.05
RUN THREE	0.06	0.06	0.07	0.07	0.05
	INPUT LEVEL IS 500 PACKETS/SEC				
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5		
RUN ONE	0.16	0.14	0.15	0.16	0.12
RUN TWO	0.18	0.14	0.17	0.16	0.13
RUN THREE	0.16	0.13	0.16	0.16	0.12
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1		
RUN ONE	0.15	0.13	0.15	0.17	0.13
RUN TWO	0.16	0.14	0.17	0.16	0.14
RUN THREE	0.16	0.13	0.16	0.16	0.13
	INPUT LEVEL IS 625 PACKETS/SEC				
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5		
RUN ONE	0.19	0.15	0.20	0.21	0.16
RUN TWO	0.21	0.17	0.22	0.19	0.17
RUN THREE	0.21	0.17	0.20	0.20	0.17
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1		
RUN ONE	0.19	0.17	0.19	0.19	0.16
RUN TWO	0.21	0.18	0.21	0.21	0.17
RUN THREE	0.22	0.18	0.20	0.19	0.16
	INPUT LEVEL IS 835 PACKETS/SEC				
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5		
RUN ONE	0.30	0.27	0.31	0.37	0.27
RUN TWO	0.28	0.29	0.33	0.38	0.28
RUN THREE	0.30	0.31	0.31	0.36	0.28
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1		
RUN ONE	0.29	0.29	0.29	0.35	0.26
RUN TWO	0.28	0.26	0.32	0.36	0.30
RUN THREE	0.30	0.26	0.29	0.37	0.26

TABLE E-14

NETWORK SIMULATION: LINE UTILIZATION FACTORS

CHANNELS	-1	-2	-3	-4	-5	-6	-7	-8	-9	-10	-11	-12	-13	-14
	INPUT LEVEL IS 100 PACKETS/SEC													
	PRIORITY(ENTER)=1						PRIORITY(TRANSIT)=5							
RUN ONE	.11	.03	.06	.10	.03	.07	.08	.06	.05	.04	.03	.07	.08	.05
RUN TWO	.09	.04	.07	.09	.03	.07	.06	.06	.07	.03	.03	.06	.06	.07
RUN THREE	.10	.03	.06	.10	.04	.07	.07	.07	.07	.03	.04	.07	.08	.06
	PRIORITY(ENTER)=5						PRIORITY(TRANSIT)=1							
RUN ONE	.11	.03	.07	.10	.04	.07	.07	.06	.05	.04	.03	.07	.06	.06
RUN TWO	.08	.04	.07	.10	.03	.07	.05	.06	.08	.03	.03	.07	.06	.07
RUN THREE	.10	.04	.07	.10	.04	.07	.06	.06	.07	.03	.03	.07	.07	.06
	INPUT LEVEL IS 200 PACKETS/SEC													
	PRIORITY(ENTER)=1						PRIORITY(TRANSIT)=5							
RUN ONE	.16	.07	.19	.23	.07	.11	.15	.11	.12	.07	.06	.15	.13	.15
RUN TWO	.21	.05	.13	.20	.05	.13	.13	.10	.12	.06	.04	.13	.14	.15
RUN THREE	.21	.10	.11	.19	.09	.14	.13	.14	.18	.07	.08	.14	.12	.13
	PRIORITY(ENTER)=5						PRIORITY(TRANSIT)=1							
RUN ONE	.15	.06	.14	.20	.07	.11	.12	.12	.13	.07	.08	.15	.13	.14
RUN TWO	.19	.07	.14	.20	.06	.12	.12	.10	.15	.06	.07	.11	.12	.15
RUN THREE	.20	.10	.16	.20	.10	.15	.16	.14	.13	.08	.08	.13	.16	.16
	INPUT LEVEL IS 500 PACKETS/SEC													
	PRIORITY(ENTER)=1						PRIORITY(TRANSIT)=5							
RUN ONE	.41	.10	041	.48	.17	.27	.45	.27	.37	.18	.17	.33	.27	.38
RUN TWO	.42	.20	.44	.56	.20	.31	.29	.25	.37	.11	.13	.35	.30	.30
RUN THREE	.47	.20	.31	.45	.20	.34	.27	.40	.25	.17	.20	.31	.36	.34
	PRIORITY(ENTER)=5						PRIORITY(TRANSIT)=1							
RUN ONE	.41	.16	.31	.54	.14	.26	.32	.39	.28	.18	.18	.44	.35	.28
RUN TWO	.47	.15	.37	.47	.17	.33	.42	.29	.31	.10	.17	.36	.26	.35
RUN THREE	.53	.22	.34	.50	.17	.36	.37	.43	.23	.15	.23	.36	.32	.30
	INPUT LEVEL IS 625 PACKETS/SEC													
	PRIORITY(ENTER)=1						PRIORITY(TRANSIT)=5							
RUN ONE	.61	.15	.46	.65	.26	.39	.47	.37	.36	.15	.26	.42	.35	.51
RUN TWO	.60	.16	.43	.66	.24	.48	.36	.41	.42	.18	.16	.45	.46	.42
RUN THREE	.62	.18	.45	.68	.23	.43	.43	.42	.43	.16	.22	.43	.43	.49
	PRIORITY(ENTER)=5						PRIORITY(TRANSIT)=1							
RUN ONE	.47	.19	.37	.55	.28	.38	.46	.38	.44	.20	.20	.41	.45	.43
RUN TWO	.56	.22	.48	.59	.21	.34	.47	.45	.33	.18	.21	.46	.31	.36
RUN THREE	.57	.23	.42	.62	.21	.40	.49	.43	.41	.21	.21	.44	.44	.41
	INPUT LEVEL IS 835 PACKETS/SEC													
	PRIORITY(ENTER)=1						PRIORITY(TRANSIT)=5							
RUN ONE	.78	.30	.60	.78	.55	.61	.66	.69	.75	.45	.36	.63	.72	.72
RUN TWO	.81	.39	.76	.73	.34	.53	.88	.84	.81	.33	.46	.81	.75	.84
RUN THREE	.64	.35	.46	.72	.39	.61	.60	.76	.81	.34	.45/.69		.68	.84
	PRIORITY(ENTER)=5						PRIORITY(TRANSIT)=1							
RUN ONE	.76	.47	.86	.80	.39	.78	.75	.81	.70	.33	.36	.76	.68	.78
RUN TWO	.75	.38	.60	.80	.47	.68	.66	.72	.63	.35	.38	.63	.63	.77
RUN THREE	.87	.27	.89	.84	.55	.57	.82	.82	.76	.39	.40	.69	.56	.66

TABLE E-15

DELAY VALUES FOR NODAL SIMULATION IN MILLISECONDS

	TOTAL DELAY MEAN	TOTAL DELAY √VAR	ENTRY DELAY MEAN	ENTRY DELAY √VAR	TRANSIT DELAY MEAN	
PRIORITY(ENTRY)=1		PRIORITY(TRANSIT)=5		50.0	PACKETS/SEC	INPUT
RUN ONE	41.94	14.81	11.77	2.75	30.17	
RUN TWO	43.03	15.93	12.12	3.08	30.91	
RUN THREE	42.00	16.26	11.82	2.86	30.18	
PRIORITY(ENTRY)=5		PRIORITY(TRANSIT)=1		50.0	PACKETS/SEC	INPUT
RUN ONE	41.48	14.56	11.97	2.88	29.51	
RUN TWO	42.07	16.08	11.91	2.72	30.16	
RUN THREE	42.00	15.77	11.80	2.85	30.20	
PRIORITY(ENTRY)=1		PRIORITY(TRANSIT)=5		500.0	PACKETS/SEC	
RUN ONE	59.88	18.09	19.32	7.20	40.56	
RUN TWO	65.45	21.93	22.64	11.19	42.81	
RUN THREE	64.58	23.38	20.53	8.70	44.05	
PRIORITY(ENTRY)=5		PRIORITY(TRANSIT)=1		500.0	PACKETS/SEC	
RUN ONE	61.97	21.80	17.45	4.97	44.52	
RUN TWO	65.70	25.04	18.71	6.50	46.99	
RUN THREE	62.87	23.96	17.60	5.61	45.27	
PRIORITY(ENTRY)=1		PRIORITY(TRANSIT)=5		625.0	PACKETS/SEC	
RUN ONE	71.40	25.24	24.74	14.15	46.66	
RUN TWO	76.27	27.58	26.10	13.41	50.17	
RUN THREE	75.59	29.08	24.28	12.67	51.31	
PRIORITY(ENTRY)=5		PRIORITY(TRANSIT)=1		625.0	PACKET/SEC	
RUN ONE	67.73	26.12	19.76	7.53	47.97	
RUN TWO	73.82	31.86	20.37	7.85	53.45	
RUN THREE	70.91	30.10	20.12	9.22	50.79	
PRIORITY(ENTRY)=1		PRIORITY(TRANSIT)=5		835.0	PACKETS/SEC	
RUN ONE	146.78	81.35	79.11	75.92	67.67	
RUN TWO	148.97	84.78	75.99	71.27	72.98	
RUN THREE	143.67	85.96	73.03	71.89	70.64	
PRIORITY(ENTRY)=5		PRIORITY(TRANSIT)=1		835.0	PACKETS/SEC	
RUN ONE	142.02	98.76	55.83	55.58	86.19	
RUN TWO	144.25	96.78	61.74	69.01	82.51	
RUN THREE	140.15	97.03	58.61	62.23	81.54	

TABLE E-16

NODAL SIMULATION: BUS UTILIZATION FACTORS

NODAL NUMBERS	(1)	(2)	(3)	(4)	(5)	(6)
	INPUT LEVEL IS 50 PACKETS/SEC					
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5			
RUN ONE	0.04	0.01	0.01	0.01	0.01	0.01
RUN TWO	0.04	0.01	0.01	0.01	0.01	0.01
RUN THREE	0.03	0.01	0.01	0.01	0.01	0.01
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1			
RUN ONE	0.04	0.01	0.01	0.01	0.01	0.01
RUN TWO	0.04	0.01	0.01	0.01	0.01	0.01
RUN THREE	0.03	0.01	0.01	0.01	0.01	0.01
	INPUT LEVEL IS 500 PACKETS/SEC					
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5			
RUN ONE	0.35	0.11	0.10	0.10	0.12	0.12
RUN TWO	0.35	0.10	0.09	0.09	0.13	0.13
RUN THREE	0.33	0.09	0.09	0.09	0.13	0.12
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1			
RUN ONE	0.35	0.09	0.11	0.10	0.13	0.12
RUN TWO	0.36	0.09	0.11	0.09	0.13	0.13
RUN THREE	0.33	0.08	0.09	0.11	0.12	0.11
	INPUT LEVEL IS 625 PACKETS/SEC					
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5			
RUN ONE	0.44	0.12	0.12	0.12	0.16	0.16
RUN TWO	0.45	0.13	0.11	0.11	0.18	0.15
RUN THREE	0.42	0.11	0.11	0.13	0.15	0.15
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1			
RUN ONE	0.44	0.11	0.13	0.13	0.16	0.14
RUN TWO	0.44	0.12	0.12	0.11	0.17	0.15
RUN THREE	0.41	0.11	0.12	0.11	0.16	0.15
	INPUT LEVEL IS 835 PACKETS/SEC					
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5			
RUN ONE	0.70	0.20	0.21	0.20	0.25	0.25
RUN TWO	0.70	0.20	0.20	0.19	0.25	0.24
RUN THREE	0.65	0.19	0.19	0.21	0.24	0.25
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1			
RUN ONE	0.69	0.20	0.19	0.22	0.25	0.24
RUN TWO	0.69	0.20	0.20	0.20	0.26	0.24
RUN THREE	0.67	0.20	0.20	0.19	0.23	0.24

TABLE E-17

NODAL SIMULATION: LINE UTILIZATION FACTORS

CHANNEL NUMBERS	(1)	(2)	(3)	(4)	(5)	(6)	(7)	(8)	(9)	(10)	
	PRIORITY(ENTER)=1				PRIORITY(TRANSIT)=5						50 PACKETS/SEC
RUN ONE	0.03	0.03	0.04	0.04	0.04	0.04	0.03	0.02	0.04	0.04	
RUN TWO	0.04	0.04	0.03	0.04	0.03	0.03	0.04	0.05	0.03	0.03	
RUN THREE	0.03	0.03	0.04	0.03	0.04	0.03	0.03	0.03	0.04	0.03	
	PRIORITY(ENTER)=5				PRIORITY(TRANSIT)=1						
RUN ONE	0.04	0.03	0.03	0.03	0.04	0.03	0.03	0.03	0.04	0.04	
RUN TWO	0.03	0.04	0.03	0.03	0.04	0.03	0.04	0.04	0.03	0.03	
RUN THREE	0.03	0.03	0.03	0.04	0.04	0.04	0.03	0.03	0.03	0.03	
	PRIORITY(ENTER)=1				PRIORITY(TRANSIT)=5						500 PACKETS/SEC
RUN ONE	0.36	0.31	0.29	0.33	0.31	0.30	0.33	0.31	0.34	0.36	
RUN TWO	0.37	0.37	0.31	0.30	0.33	0.31	0.38	0.41	0.30	0.27	
RUN THREE	0.29	0.27	0.32	0.29	0.30	0.30	0.32	0.32	0.32	0.32	
	PRIORITY(ENTER)=5				PRIORITY(TRANSIT)=1						500 PACKETS/SEC
RUN ONE	0.28	0.32	0.31	0.32	0.39	0.35	0.33	0.29	0.31	0.31	
RUN TWO	0.29	0.34	0.41	0.36	0.30	0.33	0.41	0.39	0.33	0.39	
RUN THREE	0.30	0.29	0.33	0.36	0.38	0.39	0.29	0.33	0.27	0.21	
	PRIORITY(ENTER)=1				PRIORITY(TRANSIT)=5						625 PACKETS/SEC
RUN ONE	0.32	0.38	0.38	0.38	0.37	0.38	0.39	0.42	0.40	0.46	
RUN TWO	0.45	0.47	0.39	0.43	0.44	0.43	0.51	0.52	0.40	0.35	
RUN THREE	0.27	0.32	0.40	0.37	0.45	0.46	0.43	0.47	0.46	0.39	
	PRIORITY(ENTER)=5				PRIORITY(TRANSIT)=1						625 PACKETS/SEC
RUN ONE	0.39	0.38	0.36	0.43	0.45	0.46	0.40	0.42	0.33	0.34	
RUN TWO	0.44	0.45	0.45	0.50	0.37	0.37	0.41	0.41	0.46	0.44	
RUN THREE	0.39	0.36	0.38	0.42	0.33	0.40	0.37	0.39	0.38	0.38	
	PRIORITY(ENTER)=1				PRIORITY(TRANSIT)=5						835 PACKETS/SEC
RUN ONE	0.58	0.70	0.68	0.63	0.66	0.63	0.62	0.68	0.62	0.62	
RUN TWO	0.70	0.66	0.66	0.70	0.63	0.52	0.71	0.67	0.64	0.61	
RUN THREE	0.63	0.57	0.54	0.51	0.65	0.69	0.60	0.61	0.67	0.61	
	PRIORITY(ENTER)=5				PRIORITY(TRANSIT)=1						835 PACKETS/SEC
RUN ONE	0.63	0.61	0.73	0.68	0.55	0.64	0.69	0.62	0.56	0.55	
RUN TWO	0.67	0.55	0.65	0.63	0.61	0.56	0.78	0.78	0.65	0.67	
RUN THREE	0.61	0.65	0.68	0.72	0.69	0.75	0.67	0.59	0.59	0.69	

TABLE E-18

NODAL SIMULATION: LINE UTILIZATION FACTORS

CHANNEL NUMBERS	(11)	(12)	(13)	(14)	(15)	(16)	(17)	(18)	(19)	(20)	
	PRIORITY(ENTER)=1				PRIORITY(TRANSIT)=5						50 PACKETS/SEC
RUN ONE	0.03	0.02	0.03	0.02	0.02	0.02	0.05	0.04	0.04	0.04	
RUN TWO	0.03	0.03	0.02	0.02	0.02	0.02	0.04	0.03	0.06	0.05	
RUN THREE	0.02	0.02	0.03	0.03	0.02	0.02	0.04	0.04	0.03	0.04	
	PRIORITY(ENTER)=5				PRIORITY(TRANSIT)=5						50 PACKETS/SEC
RUN ONE	0.03	0.02	0.02	0.03	0.02	0.02	0.04	0.04	0.04	0.03	
RUN TWO	0.03	0.02	0.03	0.03	0.02	0.02	0.05	0.04	0.04	0.04	
RUN THREE	0.01	0.01	0.02	0.02	0.02	0.03	0.05	0.04	0.04	0.04	
	PRIORITY(ENTER)=1				PRIORITY(TRANSIT)=5						500 PACKETS/SEC
RUN ONE	0.27	0.32	0.23	0.24	0.19	0.20	0.30	0.32	0.34	0.36	
RUN TWO	0.20	0.20	0.18	0.18	0.18	0.25	0.41	0.42	0.41	0.40	
RUN THREE	0.19	0.22	0.19	0.22	0.20	0.21	0.40	0.37	0.38	0.39	
	PRIORITY(ENTER)=5				PRIORITY(TRANSIT)=1						500 PACKETS/SEC
RUN ONE	0.21	0.20	0.26	0.22	0.20	0.23	0.37	0.41	0.35	0.29	
RUN TWO	0.23	0.20	0.21	0.20	0.21	0.25	0.38	0.44	0.42	0.37	
RUN THREE	0.21	0.17	0.18	0.18	0.30	0.25	0.36	0.34	0.39	0.40	
	PRIORITY(ENTER)=1				PRIORITY(TRANSIT)=5						625 PACKETS/SEC
RUN ONE	0.33	0.34	0.26	0.28	0.23	0.27	0.47	0.44	0.39	0.44	
RUN TWO	0.32	0.36	0.25	0.21	0.24	0.24	0.51	0.51	0.51	0.60	
RUN THREE	0.25	0.23	0.30	0.26	0.27	0.34	0.47	0.45	0.53	0.54	
	PRIORITY(ENTER)=5				PRIORITY(TRANSIT)=1						625 PACKETS/SEC
RUN ONE	0.25	0.29	0.29	0.25	0.24	0.24	0.44	0.47	0.39	0.39	
RUN TWO	0.30	0.27	0.23	0.24	0.26	0.31	0.53	0.55	0.42	0.45	
RUN THREE	0.24	0.21	0.29	0.27	0.26	0.26	0.49	0.52	0.52	0.52	
	PRIORITY(ENTER)=1				PRIORITY(TRANSIT)=5						835 PACKETS/SEC
RUN ONE	0.56	0.49	0.52	0.62	0.57	0.47	0.75	0.67	0.67	0.64	
RUN TWO	0.43	0.51	0.54	0.56	0.50	0.51	0.72	0.70	0.76	0.76	
RUN THREE	0.55	0.57	0.51	0.50	0.59	0.51	0.72	0.67	0.71	0.76	
	PRIORITY(ENTER)=5				PRIORITY(TRANSIT)=1						835 PACKETS/SEC
RUN ONE	0.54	0.56	0.36	0.43	0.58	0.57	0.63	0.70	0.69	0.72	
RUN TWO	0.47	0.52	0.54	0.47	0.54	0.68	0.72	0.71	0.68	0.69	
RUN THREE	0.49	0.57	0.56	0.54	0.52	0.59	0.72	0.76	0.76	0.73	

TABLE I 19

NETWORK SIMULATION: RECORDED THROUGHPUT (PCKS/SEC)

I/P LEVEL	RUN 1	RUN 2	RUN 3	MEAN
PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5		
100	99	104	102	101.7
200	196	213	200	203.0
500	482	518	489	496.3
625	601	644	616	620.3
835	770	796	782	782.7
PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1		
100	100	104	100	101.3
200	198	212	198	202.7
500	483	515	484	494.0
625	614	620	613	615.7
835	773	793	757	774.3

NODAL SIMULATION: RECORDED THROUGHPUT (PCKS/SEC)

I/P LEVEL	RUN 1	RUN 2	RUN 3	MEAN
PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5		
50	51	51	46	49.3
500	478	482	445	468.3
625	582	587	555	574.7
835	767	735	702	734.7
PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1		
50	50	49	46	48.3
500	475	476	442	464.3
625	583	580	551	571.3
835	738	726	690	718.0

TABLE E-20

RECORDED NODAL THROUGHPUT IN PACKETS PER SECOND ON DATA BUS

	NODAL NUMBERS (1)	(2)	(3)	(4)	(5)	(6)
	INPUT LEVEL IS 50 PACKETS PER SECOND					
CAPACITY	50.0	14.0	14.0	14.0	18.0	18.0
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5			
RUN ONE	51.2	15.0	14.6	12.7	19.6	19.7
RUN TWO	46.2	12.5	14.6	13.1	16.6	16.0
RUN THREE	47.2	12.7	11.8	13.0	16.5	17.4
MEAN	48.2	13.4	13.7	12.9	17.6	17.7
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1			
RUN ONE	49.5	13.2	15.4	13.4	18.9	16.8
RUN TWO	46.4	11.9	13.0	13.8	17.7	16.6
RUN THREE	47.6	11.7	11.9	13.6	17.1	18.0
MEAN	47.8	12.3	13.4	13.6	17.9	17.1
	INPUT LEVEL IS 500 PACKETS PER SECOND					
CAPACITY	500.0	140.0	140.0	140.0	180.0	180.0
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5			
RUN ONE	492.2	131.7	128.1	125.2	181.4	178.5
RUN TWO	447.7	118.2	124.2	119.5	175.6	158.0
RUN THREE	475.1	133.3	126.9	141.1	166.7	166.7
MEAN	471.7	127.7	126.4	128.6	174.6	167.7
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1			
RUN ONE	482.6	125.3	144.3	129.0	182.2	181.4
RUN TWO	448.4	113.5	127.1	147.6	160.6	155.8
RUN THREE	464.8	121.3	132.5	136.0	162.7	169.0
MEAN	465.3	120.0	134.6	137.5	168.5	168.7
	INPUT LEVEL IS 625 PACKETS PER SECOND					
CAPACITY	625.0	175.0	175.0	175.0	225.0	225.0
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5			
RUN ONE	606.2	179.2	144.4	153.9	249.6	202.6
RUN TWO	565.6	144.7	155.6	179.0	209.2	210.0
RUN THREE	581.4	161.2	164.6	177.5	194.6	228.1
MEAN	584.4	161.7	154.9	170.1	217.8	213.6
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1			
RUN ONE	596.0	168.4	164.1	154.6	226.3	204.7
RUN TWO	564.0	151.5	166.3	145.7	217.4	198.4
RUN THREE	580.3	172.2	152.5	174.8	216.8	197.9
MEAN	580.1	164.0	161.0	158.4	220.2	200.3
	INPUT LEVEL IS 835 PACKETS PER SECOND					
CAPACIY	835.0	233.8	233.8	233.8	300.6	300.6
	PRIORITY(ENTER)=1		PRIORITY(TRANSIT)=5			
RUN ONE	769.8	203.1	217.0	202.1	309.0	276.9
RUN TWO	725.0	199.7	192.7	203.8	255.2	264.3
RUN THREE	765.4	202.7	192.1	222.8	287.2	271.3
MEAN	753.4	201.8	200.6	209.6	283.8	270.8
	PRIORITY(ENTER)=5		PRIORITY(TRANSIT)=1			
RUN ONE	755.0	211.8	219.3	186.4	279.6	278.6
RUN TWO	711.2	216.0	187.6	200.8	256.5	257.6
RUN THREE	743.2	179.8	199.6	201.7	296.9	271.8
MEAN	736.5	202.5	202.2	196.3	277.7	269.3

TABLE E-21

VARIATION OF SWITCHING ALGORITHM PRIORITIES

PRIORITY ENTRY	PRIORITY TRANSIT	DELAY(TOTAL) MEAN	DELAY(TOTAL) √VAR	DELAY(ENTRY) MEAN	DELAY(ENTRY) √VAR	DELAY(TRANSIT) MEAN
		DELAY FIGURES IN MILLISECONDS				INPUT LEVEL 750 PCKS/SEC
1	1	87.18	73.77	42.37	39.28	44.81
1	2	75.81	56.24	36.83	39.72	38.91
2	1	76.45	66.24	35.17	32.37	41.28
1	3	85.14	69.27	46.43	51.71	43.86
3	1	76.75	67.30	35.42	26.95	41.33
1	5	75.57	57.37	39.23	40.07	36.34
5	1	71.70	58.70	25.25	11.23	46.45
1	8	76.52	55.31	41.75	38.96	34.77
8	1	75.37	85.48	30.72	27.22	44.65
1	10	80.23	61.94	45.18	49.85	35.05
10	1	77.75	83.46	27.93	19.01	49.82
1	15	80.89	58.87	43.93	42.51	36.96
15	1	77.60	76.07	30.17	23.72	47.43

BUS UTILIZATION FACTORS

PRIORITY ENTRY	PRIORITY TRANSIT	NODAL NUMBERS (1)	(2)	(3)	(4)	(5)
1	1	0.27	0.24	0.28	0.32	0.25
1	2	0.27	0.25	0.26	0.30	0.24
2	1	0.26	0.23	0.29	0.31	0.24
1	3	0.27	0.25	0.26	0.31	0.24
3	1	0.28	0.25	0.27	0.28	0.24
1	5	0.27	0.24	0.27	0.30	0.23
5	1	0.27	0.24	0.28	0.31	0.26
1	8	0.27	0.25	0.28	0.33	0.25
8	1	0.27	0.21	0.28	0.32	0.23
1	10	0.26	0.25	0.28	0.33	0.25
10	1	0.27	0.24	0.28	0.31	0.23
1	15	0.27	0.25	0.28	0.32	0.24
15	1	0.25	0.24	0.26	0.30	0.24

TABLE E-22

LINE UTILIZATION FACTORS

(1)	(2)	(3)	(4)	(5)	(6)	(7)	(8)	(9)	(10)	(11)	(12)	(13)	(14)
PRIOITY(ENTRY)=1				PRIORITY(TRANSIT)=1									
0.74	0.27	0.54	0.71	0.40	0.65	0.57	0.65	0.66	0.39	0.40	0.64	0.58	0.66
PRIORITY(ENTRY)=1				PRIORITY(TRANSIT)=2									
0.72	0.30	0.63	0.75	0.32	0.62	0.68	0.69	0.60	0.29	0.25	0.69	0.55	0.61
PRIORITY(ENTRY)=2				PRIORITY(TRANSIT)=1									
0.73	0.30	0.55	0.69	0.39	0.51	0.57	0.66	0.51	0.27	0.34	0.64	0.64	0.64
PRIORITY(ENTRY)=1				PRIORITY(TRANSIT)=3									
0.74	0.33	0.54	0.71	0.32	0.55	0.70	0.62	0.56	0.36	0.30	0.52	0.67	0.62
PRIORITY(ENTRY)=3				PRIORITY(TRANSIT)=1									
0.73	0.28	0.61	0.70	0.34	0.61	0.65	0.51	0.54	0.40	0.30	0.49	0.51	0.63
PRIORITY(ENTRY)=1				PRIORITY(TRANSIT)=5									
0.71	0.19	0.59	0.76	0.39	0.49	0.59	0.64	0.66	0.35	0.32	0.55	0.59	0.62
PRIORITY(ENTRY)=5				PRIORITY(TRANSIT)=1									
0.78	0.25	0.52	0.74	0.34	0.56	0.67	0.59	0.51	0.29	0.33	0.58	0.61	0.68
PRIORITY(ENTRY)=1				PRIORITY(TRANSIT)=8									
0.76	0.22	0.58	0.75	0.34	0.58	0.70	0.68	0.66	0.25	0.29	0.65	0.61	0.66
PRIORITY(ENTRY)=8				PRIORITY(TRANSIT)=1									
0.76	0.33	0.62	0.76	0.48	0.62	0.60	0.60	0.52	0.37	0.34	0.56	0.55	0.64
PRIORITY(ENTRY)=1				PRIORITY(TRANSIT)=10									
0.76	0.28	0.47	0.73	0.45	0.49	0.71	0.65	0.70	0.28	0.37	0.58	0.53	0.78
PRIORITY(ENTRY)=10				PRIORITY(TRANSIT)=1									
0.66	0.28	0.60	0.78	0.40	0.54	0.58	0.69	0.62	0.29	0.34	0.51	0.56	0.72
PRIORITY(ENTRY)=1				PRIORITY(TRANSIT)=15									
0.78	0.34	0.60	0.72	0.49	0.56	0.63	0.69	0.67	0.26	0.32	0.50	0.50	0.64
PRIORITY(ENTRY)=15				PRIORITY(TRANSIT)=1									
0.78	0.24	0.70	0.77	0.35	0.77	0.74	0.67	0.65	0.37	0.29	0.61	0.59	0.71

TABLE E-23

NODAL SIMULATION: RETRANSMISSION INTERVAL VARIATION

RETRM INTERVL	TOTAL DELAY MEAN MILLISECONDS	TOTAL DELAY $\sqrt{VAR}$	ENTRY DELAY MEAN	ENTRY DELAY $\sqrt{VAR}$	TRANSIT DEL MEAN	THROUGHPU PCKS/SEC
INPUT LEVEL IS 625 PACKETS/SEC						
5	133.28	71.19	30.34	21.95	102.94	446
10	116.24	59.81	30.12	18.35	86.12	476
20	108.19	61.41	32.48	21.21	75.71	491
30	68.15	23.05	22.93	10.92	45.22	579
50	64.46	22.90	23.87	11.87	40.59	576
100	64.46	22.90	23.87	11.87	40.59	576
INPUT LEVEL IS 750 PACKETS/SEC						
5	142.31	85.78	38.20	26.94	104.11	505
50	96.42	36.73	35.18	22.96	61.24	743
500	93.76	44.18	38.73	36.05	55.03	732
1000	93.76	44.18	38.73	36.05	55.03	732
INPUT LEVEL IS 835 PACKETS/SEC						
5	171.56	93.73	60.00	56.08	111.56	477
10	169.23	86.71	60.73	49.40	108.50	479
20	162.49	90.79	66.23	55.44	96.26	500
30	157.92	85.37	82.89	72.75	75.03	711
50	164.79	95.63	91.09	85.77	73.70	689
100	164.79	95.63	91.09	85.77	73.70	689

BUS UTILIZATION FACTORS

RETRM INTRVL	NODAL NUMBERS (1)	(2)	(3)	(4)	(5)	(6)
INPUT LEVEL IS 625 PACKETS/SEC						
5	0.36	0.10	0.11	0.09	0.13	0.14
10	0.39	0.11	0.10	0.12	0.14	0.13
20	0.38	0.10	0.10	0.11	0.15	0.13
30	0.43	0.13	0.13	0.12	0.14	0.16
50	0.43	0.13	0.11	0.12	0.16	0.15
100	0.43	0.13	0.11	0.12	0.16	0.15
INPUT LEVEL IS 750 PACKETS/SEC						
5	0.45	0.13	0.12	0.12	0.15	0.16
50	0.56	0.16	0.15	0.17	0.21	0.21
500	0.55	0.16	0.15	0.16	0.20	0.19
1000	0.55	0.16	0.15	0.16	0.20	0.19
INPUT LEVEL IS 835 PACKETS/SEC						
5	0.47	0.14	0.13	0.15	0.18	0.18
10	0.51	0.14	0.13	0.15	0.19	0.19
20	0.52	0.15	0.13	0.14	0.19	0.20
30	0.70	0.21	0.19	0.21	0.25	0.25
50	0.70	0.21	0.18	0.22	0.25	0.24
100	0.70	0.21	0.18	0.22	0.25	0.24

TABLE E-24

NODAL SIMULATION: RETRANSMISSION INTERVAL VARIATION

LINE UTILIZATION FACTORS

CHANNEL NOS RETRM. INTERVAL	100	LINE UTILIZATION FACTORS (MILLISECONDS) 50	30	20	10	5
INPUT LEVEL IS 625 PACKETS/SEC						
1	0.39	0.39	0.36	0.77	0.84	0.87
2	0.44	0.44	0.42	0.77	0.70	0.72
3	0.28	0.28	0.40	0.67	0.74	0.75
4	0.34	0.34	0.42	0.71	0.76	0.84
5	0.45	0.45	0.41	0.72	0.82	0.86
6	0.44	0.44	0.44	0.69	0.81	0.80
7	0.36	0.36	0.34	0.77	0.89	0.85
8	0.36	0.36	0.37	0.77	0.83	0.83
9	0.38	0.38	0.47	0.71	0.93	0.96
10	0.40	0.40	0.46	0.79	0.83	0.88
11	0.25	0.25	0.24	0.58	0.66	0.54
12	0.26	0.26	0.23	0.60	0.64	0.59
13	0.26	0.26	0.28	0.48	0.53	0.65
14	0.26	0.26	0.30	0.49	0.53	0.71
15	0.22	0.22	0.30	0.59	0.65	0.56
16	0.21	0.21	0.24	0.65	0.69	0.66
17	0.51	0.51	0.44	0.89	0.86	0.96
18	0.52	0.52	0.44	0.84	0.96	0.98
19	0.42	0.42	0.44	0.81	0.90	0.92
20	0.44	0.44	0.51	0.81	0.95	0.95
INPUT LEVEL IS 835 PACKETS/SEC						
1	0.54	0.54	0.63	0.84	0.93	0.93
2	0.61	0.61	0.61	0.90	0.89	0.89
3	0.61	0.61	0.68	0.84	0.96	0.96
4	0.71	0.71	0.70	0.89	0.88	0.88
5	0.64	0.64	0.74	0.91	0.92	0.94
6	0.68	0.68	0.72	0.89	0.95	0.94
7	0.75	0.75	0.70	0.90	0.95	0.95
8	0.67	0.67	0.67	0.92	0.99	0.97
9	0.50	0.50	0.58	0.89	0.96	0.96
10	0.55	0.55	0.62	0.83	0.96	0.96
11	0.57	0.57	0.56	0.90	0.94	0.94
12	0.54	0.54	0.54	0.92	0.93	0.94
13	0.39	0.39	0.50	0.85	0.87	0.87
14	0.46	0.46	0.45	0.85	0.81	0.85
15	0.46	0.46	0.52	0.80	0.92	0.92
16	0.49	0.49	0.57	0.87	0.95	0.92
17	0.65	0.65	0.62	0.93	0.96	0.96
18	0.75	0.75	0.76	0.88	0.96	0.99
19	0.77	0.77	0.65	0.91	0.94	0.94
20	0.70	0.70	0.77	0.97	1.00	0.99

TABLE E-25

NODAL SIMULATION: RETRANSMISSION INTERVAL VARIATION

LINE UTILIZATION FACTORS

CHANNEL NOS RETRM INTERVAL	1000	LINE UTILIZATION FACTORS (MILLISECONDS) 500	50	5
INPUT LEVEL IS 750 PACKETS/SEC				
1	0.53	0.53	0.53	0.82
2	0.54	0.54	0.52	0.86
3	0.48	0.48	0.51	0.81
4	0.53	0.53	0.56	0.78
5	0.49	0.49	0.47	0.75
6	0.50	0.50	0.48	0.74
7	0.41	0.41	0.49	0.95
8	0.50	0.50	0.54	0.97
9	0.51	0.51	0.53	0.96
10	0.41	0.41	0.45	0.93
11	0.33	0.33	0.34	0.70
12	0.37	0.37	0.39	0.72
13	0.31	0.31	0.34	0.69
14	0.32	0.32	0.28	0.71
15	0.33	0.33	0.36	0.73
16	0.36	0.36	0.37	0.79
17	0.63	0.63	0.58	0.98
18	0.57	0.57	0.62	0.99
19	0.55	0.55	0.64	0.91
20	0.56	0.56	0.60	0.96

TABLE E-26

NODAL SIMULATION: BUS RATE & ALG. EXEC. TIME VARIATION

BUS RATE BPS	TOTAL DELAY MEAN	TOTAL DELAY DEV	ENTRY DELAY MEAN	ENTRY DELAY DEV	TRANSIT DELAY MEAN	THROUGHPUT PCKS/SEC
	MILLISECONDS					
SWITCH ALG. EXECUTION TIME = 0.5 mSECS						
6 E 5	17.49	12.91	1.29	0.78	16.20	464
8 E 5	16.74	13.29	1.06	0.53	15.68	474
10E 5	17.89	14.39	0.98	0.51	16.91	479
15E 5	16.19	12.68	0.81	0.23	15.38	463
SWITCH ALG. EXECUTION TIME = 1.0 mSECS						
1 E 5	120.99	59.98	26.30	45.72	94.69	210
4 E 5	21.28	14.97	2.56	1.87	18.72	460
6 E 5	19.90	15.18	1.93	1.06	17.97	476
8 E 5	19.12	13.49	1.68	0.71	17.44	477
10E 5	17.31	12.28	1.53	0.51	15.78	468
15E 5	17.66	13.05	1.40	0.38	16.26	464
SWITCH ALG. EXECUTION TIME = 5.0 mSECS						
1 E 5	181.75	98.19	43.59	87.74	138.16	218
4 E 5	36.33	16.22	9.12	29.77	27.21	464
6 E 5	34.47	15.93	8.64	3.12	25.83	466
8 E 5	34.92	15.08	8.39	3.06	26.53	466
10E 5	34.44	15.19	8.62	3.04	25.82	474
15E 5	33.54	15.29	7.88	2.61	25.66	478
SWITCH ALG. EXECUTION TIME = 10.0 mSECS						
1 E 5	166.34	80.27	45.78	63.66	120.56	181
4 E 5	65.33	22.26	21.81	8.88	43.52	476
6 E 5	62.77	21.85	21.01	9.63	41.76	462
8 E 5	59.73	20.78	19.89	8.53	39.84	457
10E 5	60.93	20.85	19.75	8.02	41.18	465
15E 5	58.68	19.12	18.95	7.14	39.73	480
SWITCH ALG. EXECUTION TIME = 15.0 mSECS						
1 E 5	154.04	52.23	55.14	39.05	98.90	170
4 E 5	99.58	30.73	36.57	17.98	63.01	451
6 E 5	92.55	28.74	34.72	15.56	58.03	449
8 E 5	91.35	30.43	34.78	19.27	56.57	448
10E 5	99.51	36.50	36.13	19.87	63.38	448
15E 5	90.07	30.71	33.60	17.25	56.47	461

LOG FORM FOR BUS RATE VARIATION (BUS RATE IS 1.5 MBPS)

ALG EXEC TIME	10LOGx	MEAN TOTAL DELAY (mSECS)
15 mSECS	-18.24	90.07
10 mSECS	-20.00	58.68
5 mSECS	-23.01	33.54
1 mSECS	-30.00	17.66
0.5mSECS	-33.01	16.19

TABLE E-27

BUS UTILIZATION FACTORS

NODAL SIMULATION: BUS RATE & ALG. EXEC. TIME VARIATION

BUS RATE BPS	NODAL NUMBERS (1)	(2)	(3)	(4)	(5)	(6)
SWITCH ALG. EXECUTION TIME = 0.5 mSECS						
6 E 5	0.37	0.11	0.09	0.11	0.13	0.14
8 E 5	0.28	0.08	0.08	0.08	0.10	0.10
10E 5	0.23	0.07	0.05	0.07	0.09	0.08
15E 5	0.15	0.04	0.04	0.04	0.05	0.05
SWITCH ALG. EXECUTION TIME = 1.0 mSECS						
1 E 5	0.99	0.32	0.34	0.41	0.60	0.59
4 E 5	0.55	0.16	0.16	0.16	0.19	0.19
6 E 5	0.38	0.11	0.11	0.11	0.13	0.14
8 E 5	0.28	0.08	0.08	0.08	0.11	0.10
10E 5	0.31	0.08	0.08	0.09	0.11	0.11
15E 5	0.15	0.04	0.04	0.04	0.06	0.06
SWITCH ALG. EXECUTION TIME = 5.0 mSECS						
1 E 5	0.99	0.34	0.40	0.39	0.59	0.54
4 E 5	0.55	0.14	0.16	0.16	0.20	0.20
6 E 5	0.37	0.10	0.10	0.11	0.13	0.12
8 E 5	0.28	0.08	0.07	0.08	0.10	0.10
10E 5	0.23	0.06	0.06	0.06	0.09	0.08
15E 5	0.15	0.04	0.04	0.04	0.06	0.05
SWITCH ALG. EXECUTION TIME = 10.0 mSECS						
1 E 5	0.89	0.38	0.30	0.39	0.53	0.52
4 E 5	0.57	0.16	0.15	0.15	0.22	0.20
6 E 5	0.37	0.10	0.11	0.10	0.13	0.13
8 E 5	0.27	0.07	0.07	0.08	0.10	0.10
10E 5	0.22	0.06	0.07	0.06	0.08	0.08
15E 5	0.15	0.05	0.04	0.04	0.06	0.05
SWITCH ALG. EXECUTION TIME = 15.0 mSECS						
1 E 5	0.94	0.30	0.32	0.32	0.57	0.48
4 E 5	0.54	0.15	0.14	0.16	0.19	0.21
6 E 5	0.36	0.10	0.09	0.10	0.13	0.13
8 E 5	0.27	0.07	0.07	0.08	0.10	0.10
10E 5	0.22	0.06	0.06	0.06	0.08	0.08
15E 5	0.15	0.04	0.04	0.04	0.05	0.05

TABLE E-28

NODAL SIMULATION: BUS RATE & ALG. EXEC. TIME VARIATION

LINE UTILIZATION FACTORS

BUS RATE (MBPS)	CHANNEL NUMBERS 1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
SWITCH ALG. EXECUTION TIME = 0.5 mSECS																				
0.6	.36	.38	.29	.27	.33	.33	.33	.32	.26	.27	.15	.21	.16	.16	.20	.20	.35	.32	.43	.41
0.8	.31	.33	.34	.28	.33	.31	.26	.29	.37	.38	.22	.26	.21	.22	.21	.23	.39	.40	.27	.30
1.0	.30	.32	.32	.23	.42	.33	.33	.38	.40	.33	.21	.21	.17	.19	.20	.23	.49	.36	.35	.38
1.5	.30	.28	.32	.31	.37	.33	.31	.29	.29	.36	.17	.19	.19	.21	.16	.20	.40	.34	.40	.38
SWITCH alg. execution time = 1.0 mSECS																				
0.1	.18	.20	.20	.17	.15	.15	.23	.17	.18	.12	.11	.17	.19	.25	.28	.23	.37	.29	.33	.36
0.4	.36	.32	.27	.29	.34	.35	.26	.30	.34	.29	.21	.20	.23	.24	.18	.21	.42	.32	.36	.31
0.6	.41	.36	.31	.32	.32	.33	.30	.34	.29	.34	.22	.20	.22	.25	.23	.19	.40	.37	.42	.38
0.8	.39	.35	.29	.28	.32	.31	.41	.32	.27	.29	.19	.21	.27	.21	.15	.26	.40	.41	.36	.36
1.0	.31	.34	.31	.29	.30	.27	.28	.33	.31	.29	.13	.17	.20	.21	.23	.27	.37	.36	.37	.34
1.5	.32	.32	.37	.35	.26	.26	.26	.33	.29	.36	.19	.22	.24	.19	.20	.21	.45	.39	.41	.39
SWITCH ALG. EXECUTION TIME = 5.0 mSECS																				
0.1	.13	.12	.18	.23	.19	.16	.22	.19	.21	.23	.13	.16	.14	.15	.22	.22	.27	.26	.27	.32
0.4	.30	.29	.35	.34	.33	.32	.32	.29	.30	.34	.19	.14	.21	.23	.18	.20	.34	.34	.39	.40
0.6	.29	.28	.35	.34	.35	.31	.34	.33	.31	.28	.19	.20	.16	.21	.22	.20	.37	.35	.30	.36
0.8	.30	.31	.34	.32	.34	.36	.30	.29	.31	.32	.23	.23	.21	.20	.18	.16	.37	.37	.36	.37
1.0	.30	.32	.33	.33	.34	.36	.32	.32	.37	.36	.22	.19	.21	.21	.18	.18	.39	.37	.35	.32
1.5	.28	.31	.32	.31	.33	.32	.31	.39	.36	.36	.20	.23	.24	.30	.19	.24	.44	.38	.30	.30
SWITCH ALG. EXECUTION TIME = 10.0 mSECS																				
0.1	.12	.21	.20	.20	.17	.18	.20	.18	.16	.17	.23	.14	.11	.17	.21	.21	.41	.28	.26	.35
0.4	.29	.31	.31	.32	.39	.37	.34	.33	.36	.36	.24	.28	.25	.22	.19	.17	.38	.42	.32	.33
0.6	.31	.30	.36	.35	.28	.31	.32	.32	.28	.31	.19	.21	.20	.26	.23	.19	.35	.35	.35	.37
0.8	.24	.28	.27	.28	.32	.33	.32	.32	.35	.35	.20	.20	.16	.20	.19	.18	.38	.34	.38	.38
1.0	.31	.31	.36	.37	.34	.33	.35	.31	.25	.28	.24	.24	.20	.23	.20	.20	.36	.40	.36	.33
1.5	.33	.31	.39	.38	.39	.26	.34	.38	.37	.37	.27	.24	.23	.22	.21	.26	.35	.42	.33	.32
SWITCH ALG. EXECUTION TIME = 15.0 mSECS																				
0.1	.12	.14	.11	.17	.15	.14	.29	.22	.25	.16	.17	.14	.18	.15	.20	.19	.34	.32	.26	.29
0.4	.29	.30	.32	.33	.32	.32	.30	.29	.31	.32	.18	.20	.18	.18	.21	.21	.40	.35	.37	.41
0.6	.28	.28	.26	.26	.33	.30	.35	.38	.28	.28	.24	.25	.16	.17	.21	.22	.31	.37	.36	.39
0.8	.32	.30	.29	.26	.34	.37	.30	.31	.32	.27	.18	.22	.20	.19	.21	.22	.37	.41	.32	.39
1.0	.29	.31	.30	.29	.30	.36	.27	.30	.35	.30	.23	.23	.20	.23	.21	.20	.34	.32	.35	.40
1.5	.27	.28	.32	.30	.32	.30	.33	.28	.34	.32	.20	.18	.21	.22	.21	.20	.37	.40	.37	.33

TABLE E-29

NETWORK SIMULATION:SWITCHING ALG EXEC TIME IS 1MSEC

I/P LEVEL	TOTAL DELAY MEAN	TOTAL DELAY $\sqrt{VAR}$	ENTRY DELAY MEAN	ENTRY DELAY $\sqrt{VAR}$	TRANSIT DEL MEAN
PCKS/SEC		MILLISECONDS			
625	20.41	24.31	1.87	0.75	18.54
835	20.27	22.53	2.03	0.93	18.24
1000	39.58	40.95	2.18	2.11	37.40

BUS UTILIZATION FACTORS

I/P LEVEL	NODAL NUMBERS (1)	(2)	(3)	(4)	(5)
625	0.27	0.21	0.25	0.26	0.20
835	0.30	0.25	0.31	0.32	0.25
1000	0.37	0.32	0.39	0.43	0.31

LINE UTILIZATION FACTORS

CHANNEL	INPUT TRAFFIC IN PACKETS/SEC 625	835	1000
1	0.83	0.80	0.93
2	0.20	0.28	0.40
3	0.50	0.57	0.72
4	0.67	0.83	0.92
5	0.25	0.33	0.48
6	0.50	0.63	0.75
7	0.61	0.67	0.60
8	0.43	0.66	0.90
9	0.44	0.52	0.72
10	0.33	0.21	0.53
11	0.28	0.30	0.65
12	0.47	0.70	0.82
13	0.51	0.56	0.75
14	0.46	0.53	0.75

TABLE E-30

NODAL SIMULATION: SWITCHING ALG EXEC TIME IS 1MSEC DOUBLE CHANNEL

I/P LEVEL	TOTAL DELAY MEAN	TOTAL DELAY √VAR	ENTRY DELAY MEAN	ENTRY DELAY √VAR	TRANSIT DEL MEAN
PCKS/SEC		MILLISECONDS			
500	19.90	15.18	1.93	1.06	17.97
625	23.74	16.68	1.95	0.93	21.67
835	30.06	23.52	2.13	1.14	27.93
1000	41.33	28.00	2.45	1.54	38.88

BUS UTILIZATION FACTORS

I/P LEVEL	NODAL NUMBERS (1)	(2)	(3)	(4)	(5)	(6)
500	0.35	0.10	0.10	0.10	0.12	0.13
625	0.57	0.16	0.15	0.18	0.19	0.21
835	0.68	0.20	0.18	0.20	0.25	0.25
1000	0.84	0.25	0.25	0.22	0.32	0.31

LINE UTILIZATION FACTORS

CHANNEL	INPUT TRAFFIC IN PACKETS/SEC 500	625	835	1000
1	0.41	0.48	0.58	0.76
2	0.36	0.46	0.65	0.70
3	0.31	0.53	0.60	0.85
4	0.32	0.58	0.60	0.76
5	0.32	0.50	0.60	0.71
6	0.33	0.61	0.74	0.71
7	0.30	0.42	0.54	0.73
8	0.34	0.47	0.55	0.74
9	0.29	0.48	0.55	0.65
10	0.34	0.51	0.59	0.66
11	0.22	0.31	0.42	0.62
12	0.20	0.35	0.39	0.47
13	0.22	0.28	0.33	0.52
14	0.25	0.30	0.32	0.55
15	0.23	0.33	0.48	0.49
16	0.19	0.36	0.42	0.50
17	0.40	0.59	0.67	0.89
18	0.37	0.57	0.65	0.96
19	0.42	0.59	0.69	0.81
20	0.38	0.55	0.75	0.81

TABLE E-31

NODAL SIMULATION: SINGLE CHANNEL CONNECTION

DELAY VALUES FOR NETWORK SIMULATION IN MILLISECONDS

I/P LEVEL PCKS/SEC	TOTAL DELAY MEAN	TOTAL DELAY $\sqrt{VAR}$	ENTRY DELAY MEAN	ENTRY DELAY $\sqrt{VAR}$	TRANSIT DEL MEAN	THROUGHPUT PCKS/SEC
		MILLISECONDS				
ALGORITHM EXECUTION TIME 1MSECS						
100	16.56	13.71	1.60	0.58	14.96	96
200	28.86	20.47	1.67	0.67	27.19	191
400	51.31	51.54	1.74	0.69	49.57	338
500	155.53	118.84	1.82	0.80	153.71	364
ALGORITHM EXECUTION TIME 10MSECS						
100	45.85	16.67	13.33	4.36	32.52	98
200	54.86	19.58	16.56	6.94	38.30	195
400	89.95	47.70	27.33	23.35	62.62	373
500	186.66	128.09	99.24	100.97	87.42	398

BUS UTILIZATION FACTORS

I/P LEVEL PCKS/SEC	NODAL NUMBERS (1)	(2)	(3)	(4)	(5)	(6)
ALGORITHM EXECUTION TIME 1MSECS						
100	0.07	0.02	0.02	0.02	0.02	0.03
200	0.14	0.04	0.04	0.04	0.05	0.05
400	0.26	0.07	0.07	0.07	0.10	0.10
500	0.37	0.09	0.08	0.09	0.14	0.13
ALGORITHM EXECUTION TIME 10MSECS						
100	0.07	0.02	0.02	0.02	0.03	0.03
200	0.14	0.04	0.04	0.04	0.05	0.05
400	0.28	0.08	0.08	0.08	0.10	0.10
500	0.38	0.11	0.10	0.11	0.14	0.13

TABLE E-32

NODAL SIMULATION: SINGLE CHANNEL CONNECTION

LINE UTILIZATION FACTORS

CHANNEL	TRAFFIC INPUT IN PACKETS/SEC			
	100	200	400	500
	ALGORITHM EXECUTION TIME 1MSECS			
1	0.14	0.36	0.64	0.96
2	0	0	0	0
3	0.16	0.55	0.66	0.95
4	0	0	0	0
5	0.13	0.53	0.63	0.93
6	0	0	0	0
7	0.11	0.64	0.67	0.96
8	0	0	0	0
9	0.12	0.52	0.66	0.94
10	0	0	0	0
11	0.08	0.35	0.53	0.82
12	0	0	0	0
13	0.08	0.45	0.54	0.87
14	0	0	0	0
15	0.09	0.29	0.53	0.87
16	0	0	0	0
17	0.17	0.67	0.70	0.98
18	0	0	0	0
19	0.15	0.42	0.65	0.97
20	0	0	0	0
	ALGORITHM EXECUTION TIME 10MSECS			
1	0.14	0.24	0.53	0.75
2	0	0	0	0
3	0.14	0.32	0.48	0.74
4	0	0	0	0
5	0.12	0.28	0.57	0.69
6	0	0	0	0
7	0.13	0.24	0.57	0.73
8	0	0	0	0
9	0.13	0.28	0.52	0.74
10	0	0	0	0
11	0.09	0.16	0.31	0.49
12	0	0	0	0
13	0.08	0.22	0.33	0.53
14	0	0	0	0
15	0.08	0.17	0.37	0.57
16	0	0	0	0
17	0.14	0.36	0.66	0.60
18	0	0	0	0
19	0.17	0.26	0.62	0.85
20	0	0	0	0

TABLE E-33

REFERENCES

REFERENCES

1. Martin, J
Telecommunications and the Computer
Prentice-Hall - 1976

2. Christiansen, H M and Senft, F
'PCM 30/32, a Time-Division Multiplex Transmission System for Local and Short-Haul Networks'
Siemens Review - 38, pp. 190 - 194, 1971

3. Davies, D W and Barber, D L
Communication Networks for Computers
Wiley - 1973

4. Roberts, L G
'The Evolution of Packet-Switching'
Proceedings of the IEEE - Vol. 66, No. 11, pp. 1307 - 1313, 1978

5. Fick, H and Kammerl, A
'Multiplexing and Switching of Data in Synchronous Networks and the Realization in the EDS system'
IEEE Transactions on Communication - Vol. 61, No. 8,
pp. 925 - 927, 1973

6. Schwartz, M
Computer Communication Network Design and Analysis
Prentice-Hall - 1977

7. Gray, P J
'Network Services in Systems Network Architecture'
IEEE Transactions on Communication - Vol. COMM-25, No. 1,
pp 104 - 116, 1977

8. Fischer, M J and Harris, F C
'A Model for Evaluating the Performance of an Integrated Circuit and Packet Switched Multiplex Structure'
IEEE Transaction on Communication - Vol. 24, No. 2, pp. 195 - 202, 196

9. Jenny, C J and Künmerle
'Distributed Processing Within an Integrated Circuit Packet Switching Node'
IEEE Transactions on Communications - Vol. 24, No. 10, pp. 1089 - 1100, 1976

10. Miyahara, H, Teshigawara, T, Hasegawa, T
'Delay and Throughput Evaluation of Switching Methods in Computer Communication Networks'
IEEE Transactions in Communications - Vol. 26, No. 3, pp. 337 - 343, 1978

11. Newport, C B and Ryzlak, Y
'Communication Processors'
Proceedings of the IEEE - Vol. 60, No. 11, pp. 1321 - 1332, 1972

12. Mills, D L
'Communication Software'
Proceedings of the IEEE - Vol. 60, No. 11, pp. 1333 - 1341, 1972

13. Steele, J and Mattson, R C
'Architecture of a Universal Communications Processor'
Computer Design - No. 11, pp. 63 - 68, 1973

14. Mann, W F, et al
'A network-oriented multiprocessor'
Proc. AFIPS National Computer Conference
Montvale, Vol. 45, pp. 533 - 540, 1976

15. Roberts, L G
'Packet Network Design - the third generation'
IFIP Congress Proceedings
North Holland Publishing, pp. 541 - 545, 1977

16. Sarch, R
'Communication Processors - Trends'
Data Communications - Special Report, Jan. 1979

17. Fuchs and Jackson, I E
'Estimates of Distributions of Random Variables for Certain Computer Communication Traffic Models'
Communications of the ACM - No. 12, Vol. 13, pp. 752 - 757, 1970

18. Crowther, W R, et al
'Issues in Packet-Switching Network Design'
AFIPS Conference Proceedings
Montvale, Vol. 44, pp. 161 - 175, 1975

19. Kleinrock, L
'Principles and Lessons in Packet Communications'
Proceedings of the IEEE - Vol. 66, No. 11, pp. 1320 - 1329, 1978

20. Frank, H and Kahn, R E
'Computer Communication Network Design - Experience with Theory and Practice'
Proc. of AFIPS Spring Joint Computer Conference
Montvale, Vol. 37, pp. 255 - 270, 1972

21. Kleinrock, L
Queueing Systems, Theory and Application, Vol. 2
Wiley, 1976

22. Davis, D W
'The Control of Congestion in Packet-Switch Networks'
IEEE Transactions on Communications
Vol. 20, No. 3, pp. 546 - 556, 1972

23. Kahn, R E and Crowther, P
'Flow Control in a Resource-Sharing Network'
IEEE Transactions on Communications
Vol. 20, No. 3, pp. 539 - 565, 1972

24. Lain, S S and Reiser, M
'Congestion Control by Input Buffer Limits - An Analysis'
IEEE Transactions on Communications
Vol. 27, No. 1, pp. 127 - 133, 1979

25. Pennotti, M C and Schwarz, M
'Congestion Control in Store-and-Forward Links'
IEEE Transactions on Communications
Vol. 23, No. 12, pp. 1434 - 1443, 1975

26. Pauzin, L and Zimmerman, H
'A Tutorial on Protocols'
Proceedings of the IEEE
Vol. 16, No. 11, p. 1346 - 1370, 1978

27. Gray, J P
'Line Control Procedures'
Proceedings of the IEEE
Vol. 60, No. 11, pp. 1301 - 1312, 1972

28. Ferrari, D
Computer Systems Performance Evaluation
Prentice-Hall, 1978

Author Reinink K
Name of thesis Data Adaptor unit for an electronic exchange: system design and simulation study 1981

PUBLISHER:
University of the Witwatersrand, Johannesburg
©2013

LEGAL NOTICES:

Copyright Notice: All materials on the University of the Witwatersrand, Johannesburg Library website are protected by South African copyright law and may not be distributed, transmitted, displayed, or otherwise published in any format, without the prior written permission of the copyright owner.

Disclaimer and Terms of Use: Provided that you maintain all copyright and other notices contained therein, you may download material (one machine readable copy and one print copy per page) for your personal and/or educational non-commercial use only.

The University of the Witwatersrand, Johannesburg, is not responsible for any errors or omissions and excludes any and all liability for any errors in or omissions from the information on the Library website.

Author Reinink K
Name of thesis Data Adaptor unit for an electronic exchange: system design and simulation study 1981

PUBLISHER:
University of the Witwatersrand, Johannesburg
©2013

LEGAL NOTICES:

Copyright Notice: All materials on the University of the Witwatersrand, Johannesburg Library website are protected by South African copyright law and may not be distributed, transmitted, displayed, or otherwise published in any format, without the prior written permission of the copyright owner.

Disclaimer and Terms of Use: Provided that you maintain all copyright and other notices contained therein, you may download material (one machine readable copy and one print copy per page) for your personal and/or educational non-commercial use only.

The University of the Witwatersrand, Johannesburg, is not responsible for any errors or omissions and excludes any and all liability for any errors in or omissions from the information on the Library website.